

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Enabling SDMA in H-ARQ Map IE's	
Date Submitted	2004-11-04	
Source(s)	Frederick W. Vook Kevin L. Baum Xiangyang (Jeff) Zhuang Mark Cudak Motorola Labs 1301 E. Algonquin Road Schaumburg, IL 60196	Voice: +1-847-576-7939 Fred.Vook@motorola.com
Re:	IEEE P802.16-REVe/D5-2004	
Abstract	Modifications to H-ARQ Map IEs to enable SDMA allocations	
Purpose	Adoption of proposed changes into P802.16e	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

Enabling SDMA in H-ARQ Map IE's

*Frederick W. Vook, Kevin L. Baum, Xiangyang (Jeff) Zhuang, Mark Cudak
Motorola Labs, Schaumburg, IL, USA*

1 Introduction

Spatial Division Multiple Access (SDMA) requires the ability to allocate the same subchannels to two or more SS's. Currently, SDMA cannot be used with H-ARQ because the H-ARQ Map IE's do not support the allocation of a subchannel to more than one SS. The main reason is that the time/frequency resource allocations made using H-ARQ based IE's are relative and cumulative in nature. Before any allocations are made, a starting point is defined in the OFDMA frame. Then, the first allocation is assumed to begin at the previously defined starting point, and the second allocation begins at the end of the first allocation, and so forth. Therefore, there is no way to assign the same set of resources to a multiple SS's.

This contribution provides a solution for the downlink by introducing an SDMA flag and an SS identification field into the MIMO-Compact-DL-MAP IE so that the same allocation can be given to multiple SS's. For the uplink, the same problem exists in the MIMO Compact UL-MAP IE. Even though collaborative spatial multiplexing is mentioned in the IE, it does not support allocating the same subchannel to more than one SS. An SDMA flag and an SS identification field are introduced in the MIMO Compact UL-MAP IE to resolve the problem.

2 Specific Text Changes

----- Beginning of Text Changes -----

[In Section **6.3.2.3.43.6.7**, modify Table 97a and add text after it as follows (Modifications in [blue](#)):]

Table 97a—MIMO/[SDMA](#) Compact DL-MAP IE format

Syntax	Size (bits)	Notes
MIMO_Compact_DL-MAP_IE() {		
Compact DL-MAP Type	3	Type = 7
DL-MAP Sub-type	5	MIMO = 0x01
Length	4	Length of the IE in Bytes
SDMA flag	1	0 = MIMO allocation 1 =SDMA allocation
Matrix indicator	2	DL STC matrices (see 8.4.8.3)
Num_layer	2	Number of multiple coding/modulation layers 00 – 1 layer 01 – 2 layers 10 – 3 layers

		11 – 4 layers
for (j=1;j<Num_layer;j++) {		This loop specifies the Nep for layers 2 and above when required for STC. If SDMA flag = 0 , The same Nsch and RCID applied for each layer
<u>If (SDMA flag = 1)</u>	<u>RCID</u>	<u>SS identifier for the current layer of the SDMA allocation</u>
if (H-ARQ Mode =CTC Incremental Redundancy) { Nep } elseif (H-ARQ Mode = Generic Chase) { DIUC }	4	H-ARQ Mode is specified in the H-ARQ Compact_DL-MAP IE format for Switch H-ARQ Mode.
CQI Feedback_type	3	Type of contents on CQICH for this SS 000 = Default feedback 001 = Precoding weight matrix W 010 = Channel matrix H 011 = MIMO mode and permutation zone 100 -111 = Reserved
CQICH_Num	2	Total number of CQICHs assigned to this SS is (CQICH_Num +1)
for (i=1;i<CQICH_Num;i++) {		
Allocation index	6	Index to uniquely identify the additional CQICH resources assigned to the SS
}		
Padding	variable	The padding bits are used to ensure the IE size is integer number of bytes
}		

When SDMA flag = 1, Num_layer means the number of SDMA users (2, 3, or 4). The number of SDMA users also sets the pilot format (e.g., for 2 SDMA users, the two-antenna pilot and subchannel format is used for the allocation)

[In Section 6.3.2.3.43.7.8, modify Table 14b and add text after the table as follows (Modifications in [blue](#), deletions in [red](#)):]

Table 14b —MIMO/[SDMA](#) Compact UL-MAP IE format

Syntax	Size (bits)	Notes
MIMO Compact UL-MAP IE()		
Compact UL-MAP Type	3	Type = 7
UL-MAP Sub-type	5	MIMO = 0x01
Length	4	Length of the IE in Bytes
SDMA flag	1	0 = MIMO allocation 1 =SDMA allocation
Matrix indicator	1	UL STC matrices (see 8.4.8.4) For 2-antenna SS, 0 = Matrix A 1 = Matrix B For Collaborative SM capable SS 0 = Pilot pattern A 1 = Pilot pattern B
Num layer	1	Number of multiple coding/modulation layers 00 – 1 layer 01 – 2 layers
for (j=1;j<Num_layer; j++) {		This loop specifies the Nep for layers 2 and above when required for STC. If SDMA flag = 0, then The same Nsch and RCID applied for each layer
If (SDMA flag = 1)	RCID	SS identifier for the current layer of the SDMA allocation
if (H-ARQ Mode =CTC Incremental Redundancy) { Nep } elseif (H-ARQ Mode = Generic Chase) { UIUC }	4	H-ARQ Mode is specified in the HARQ Compact_UL-MAP IE format for Switch HARQ Mode.
Padding	variable	The padding bits are used to ensure the IE size is integer number of bytes
}		

[When SDMA flag = 1, Num_layer means the number of SDMA users, and the first layer/user will use pilot pattern A and the second layer/user will use pilot pattern B.](#)

----- End of Text Changes -----