
Project	IEEE 802.16 Broadband Wireless Access Working Group <http://ieee802.org/16>		
Title	Editorial Changes on Accepted Contribution C802.16e-05/038r1		
Date Submitted	2005-03-17		
Source(s)	Wonil Roh, JeongTae Oh, Kyunbyoung Ko, Chan-Byoung Chae, Hongsil Jeong, Sung-Ryul Yun, Seungjoo Maeng, Jaeho Jeon, Jaeyeol Kim, Soonyoung Yoon, Yong Chang	wonil.roh@samsung.com	Voice: +82-31-279-3868
	Samsung Electronics Co., Ltd.		
	Erik Lindskog, Kamlesh Rath, Dave Garrett and Brett Schein.	elindskog@beceem.com	Voice: +1-408-387-5014
	Beceem Communications, Inc.		
Re:			
Abstract	Editorial Changes on Accepted Contribution C802.16e-05/038r1		
Purpose	Adoption of proposed changes into P802.16e		
<u>Crossed out indicates deleted text, underlined blue indicates new text change to the Standard</u>			
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.		
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.		
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures (Version 1.0) < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, if there is technical justification in the opinion of the standards-developing committee and provided the IEEE receives assurance from the patent holder that it will license applicants under reasonable terms and conditions for the purpose of implementing the standard."		
	Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:r.b.marks@ieee.org > as early as possible, in written or electronic form, of any patents (granted or under application) that may cover technology that is under consideration by or has been approved by IEEE 802.16. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.		

Editorial Changes on Accepted Contribution C802.16e-05/038r1

1. Introduction

The H-ARQ MAP IE for MIMO bursts was introduced in [2] and accepted by the Working Group in 35th meeting in Sanya, but it failed to be added to the current draft standard [1]. The same proposal is re-written with proper Section and Table numbers in line with the existing texts.

2. Specific Text Changes

[Modify the text from line 27 on page 260 to line 30 on page 261 of [1] as follows]

----- Start of Text Change -----

Table 285m -- H-ARQ DL MAP IE Format

Syntax	Size	Note
H-ARQ DL MAP IE {		
Extended DIUC 2	4	Set to 0x1
Length	8	Length of the IE in bytes
RCID_Type	2 bits	00 = Normal CID 01 = RCID11 10 = RCID7 11 = RCID3
While (data remains) {		
OFDMA Symbol offset	8 bits	Offset from the start symbol of DL sub-frame
Subchannel offset	6 bits	
Boosting	3 bits	000: normal (not boosted); 001: +6dB; 010: -6dB; 011: +9dB; 100: +3dB; 101: -3dB; 110: -9dB; 111: -12dB;
No. OFDMA Symbols	7 bits	
No. Subchannels	6 bits	
Mode	4 bit	Indicates the mode of this IE 0000 = Chase H-ARQ 0001 = Incremental redundancy H-ARQ for CTC 0010 = Incremental redundancy H-ARQ for convolutional code 0011 = MIMO Chase H-ARQ 0100 = MIMO IR H-ARQ 0101 = MIMO IR H-ARQ for Convolutional Code 0110 = MIMO STC H-ARQ 0111-1111 Reserved
If (Mode==000) {	variable	
DL H-ARQ Chase Sub-Burst IE ()		
} else if (Mode==001) {	variable	
DL H-ARQ IR Sub-Burst IE ()		
} else if (Mode==010) {	variable	
DL H-ARQ IR CC Sub-Burst IE ()		

<code>} else if (Mode==011) {</code>			
<code> MIMO DL Chase H-ARQ Sub-Burst IE ()</code>	variable		
<code>} else if (Mode==100) {</code>			
<code> MIMO DL IR H-ARQ Sub-Burst IE ()</code>	variable		
<code>} else if (Mode==101) {</code>			
<code> MIMO DL IR H-ARQ for CC Sub-Burst IE ()</code>	variable		
<code>} else if (Mode == 110) {</code>			
<code> MIMO DL STC H-ARQ Sub-Burst IE ()</code>	variable		
<code>}</code>			
<code>}</code>			
Padding	Variable	Padding to byte; shall be set to 0	
<code>}</code>			

- End of Text Change

[Add the following text after line 65 on page 264]

- Start of Text Change

Table 285q -- MIMO DL Chase H-ARQ Sub-Burst IE Format

<u>MIMO DL Chase H-ARQ Sub-Burst IE {</u>		
<u>N sub burst</u>	<u>5</u>	<u>Number of sub-bursts in the region</u>
<u>For (j=0; j< N sub burst; j++){</u>		
<u> MU Indicator</u>	<u>1 bit</u>	<u>Indicates whether this DL burst is intended for multiple SS</u>
<u> Dedicated MIMO DL Control Indicator</u>	<u>1 bit</u>	
<u> If(MU indicator == 0) {</u>		
<u> RCID IE()</u>	<u>Variable</u>	
<u> }</u>		
<u> If (Dedicated MIMO DL Control Indicator ==1) {</u>		
<u> Dedicated MIMO DL Control IE ()</u>	<u>variable</u>	
<u> }</u>		
<u> Length</u>	<u>10 bits</u>	
<u> For (i=0;i<N_layer;i++) {</u>		
<u> if(MU indicator == 1) {</u>		
<u> RCID IE()</u>	<u>Variable</u>	
<u> }</u>		
<u> DIUC</u>	<u>4 bits</u>	
<u> Repetition Coding Indication</u>	<u>2 bits</u>	<u>0b00 – No repetition coding</u> <u>0b01 – Repetition coding of 2 used</u> <u>0b10 – Repetition coding of 4 used</u> <u>0b11 – Repetition coding of 6 used</u>
<u> ACID</u>	<u>4 bits</u>	
<u> AI_SN</u>	<u>1 bit</u>	

{					
{					
}					

For each multi SS sub-burst (MU Indicator = 1), if the dedicated pilot bit is set to 1 in the STC_ZONE IE (section 8.4.5.3.4) for the zone in which the sub-burst allocations are being made, N_layer for this sub-burst selects the pilot format for the sub-burst by interpreting N_layer as the number of transmit antennas (as defined in 8.4.8), and the SS with the first RCID shall be assigned the pilot pattern corresponding to antenna 1, of section 8.4.8, the second to the pilot pattern corresponding to antenna 2, and so on.

Table 285r -- MIMO DL IR H-ARQ Sub-Burst IE Format

MIMO DL IR H-ARQ Sub-Burst IE {					
N sub burst	5				Number of sub-bursts in the 2D region
For (j=0; j< N sub burst; j++) {					
MU Indicator	1 bit				Indicates whether this DL burst is intended for multiple SS
Dedicated MIMO DL Control Indicator	1 bit				
ACK Disable	1 bit				When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.
If (MU indicator == 0) {					
RCID IE()	Variable				
}					
If (Dedicated MIMO DL Control Indicator ==1) {					
Dedicated MIMO DL Control IE ()	variable				
}					
Nsch	4 bits				
If (ACK Disable ==0) {					
SPID	2 bits				
ACID	4 bits				
AI_SN	1 bit				
}					
For (i=0;i<N_layer;i++) {					
if (MU indicator == 1) {					
RCID IE()	Variable				
}					
Nep	4 bits				
}					
}					
}					

Table 285s -- MIMO DL IR H-ARQ for CC Sub-Burst IE Format

MIMO DL IR H-ARQ for CC Sub-Burst IE {				
N sub burst	5			Number of sub-bursts in the 2D region

<u>For (j=0; j< N sub burst; j++){</u>			
<u>MU Indicator</u>	<u>1 bit</u>	<u>Indicates whether this DL burst is intended for multiple SS</u>	
<u>Dedicated MIMO DL Control Indicator</u>	<u>1 bit</u>		
<u>If (MU indicator == 0) {</u>			
<u>RCID IE()</u>	<u>Variable</u>		
<u>}</u>			
<u>If (Dedicated MIMO DL Control Indicator ==1) {</u>			
<u>Dedicated MIMO DL Control IE ()</u>	<u>variable</u>		
<u>}</u>			
<u>Length</u>	<u>10 bits</u>		
<u>For (i=0;i<N_layer;i++) {</u>			
<u>if (MU indicator == 1) {</u>			
<u>RCID IE()</u>	<u>Variable</u>		
<u>}</u>			
<u>DIUC</u>	<u>4 bits</u>		
<u>Repetition Coding Indication</u>	<u>2 bits</u>	<u>0b00 – No repetition coding</u> <u>0b01 – Repetition coding of 2 used</u> <u>0b10 – Repetition coding of 4 used</u> <u>0b11 – Repetition coding of 6 used</u>	
<u>ACID</u>	<u>4 bits</u>		
<u>AI_SN</u>	<u>1 bit</u>		
<u>SPID</u>	<u>2 bits</u>		
<u>}</u>			
<u>}</u>			
<u>}</u>			

Table 285t -- MIMO DL STC H-ARQ Sub-Burst IE Format

<u>MIMO DL STC H-ARQ Sub-Burst IE {</u>			
<u>N sub burst</u>	<u>5</u>	<u>Number of sub-bursts in the region</u>	<u>2D</u>
<u>For (j=0; j< N sub burst; j++){</u>			
<u>Tx count</u>	<u>2 bits</u>	<u>00: first transmission</u> <u>01: second transmission</u> <u>10: third transmission</u> <u>11: fourth transmission</u>	
<u>Length</u>	<u>10 bits</u>		
<u>if (Tx count ==00) {</u>			
<u>MU Indicator</u>	<u>1 bit</u>	<u>Indicates whether this DL burst is intended for multiple SS</u>	
<u>Dedicated MIMO DL Control Indicator</u>	<u>1 bit</u>		
<u>If (MU indicator == 0) {</u>			
<u>RCID IE()</u>	<u>Variable</u>		
<u>}</u>			
<u>If (Dedicated MIMO DL Control Indicator ==1) {</u>			
<u>Dedicated MIMO DL Control IE ()</u>	<u>variable</u>		

<u>}</u>								
<u>For (i=0;i<N_layer;i++) {</u>								
<u> if (MU indicator == 1) {</u>								
<u> RCID IE()</u>					Variable			
<u> }</u>								
<u> DIUC</u>				4 bits				
<u> Repetition Coding Indication</u>				2 bits				
<u> }</u>						0b00 – No repetition coding		
<u> ACID</u>						0b01 – Repetition coding of 2 used		
<u> }</u>						0b10 – Repetition coding of 4 used		
<u> }</u>						0b11 – Repetition coding of 6 used		
<u>}</u>								

8.4.5.3.22.1 Dedicated MIMO DL Control IE Format

Dedicated DL Control IE for MIMO contains additional control information for each sub-burst. Because each sub-burst may have its own control information format dependent on the MSS capability, the length of the Dedicated DL Control IE for MIMO is variable.

Table 285u -- Dedicated MIMO DL Control IE Format

Syntax	size	Note
<u>Dedicated MIMO DL Control IE()</u> {	-	-
<u> Length</u>	<u>5 bits</u>	<u>Length of following control information in Nibble.</u>
<u> Control Header</u>	<u>3 bits</u>	<u>Bit #0 : MIMO Control Info</u> <u>Bit #1 : CQI Control Info</u> <u>Bit #2 : Reserved</u>
<u> N_layer</u>	<u>2 bits</u>	<u>Number of coding/modulation layers</u> <u>00 = 1 layer</u> <u>01 = 2 layers</u> <u>10 = 3 layers</u> <u>11 = 4 layers</u>
<u> if(MIMO Control Info == 1){</u>		
<u> Matrix</u>	<u>2 bits</u>	<u>Indicates transmission matrix (See 8.4.8)</u>
<u> }</u>		
<u> If(CQICH Control Info == 1){</u>		
<u> Period</u>	<u>2 bits</u>	<u>Period (in frame) = 2^period</u>
<u> Frame offset</u>	<u>3 bits</u>	
<u> Duration</u>	<u>4 bits</u>	<u>A CQI feedback is transmitted on the CQI channels indexed by the CQICH ID for 10 x 2^d frames.</u>
<u> for (j=0:N_layer+1;j++) {</u>		
<u> Allocation index¹</u>	<u>6 bits</u>	<u>Index to CQICH assigned to this layer.</u>
<u> }</u>		
<u> CQICH_Num</u>	<u>2 bits</u>	<u>Number of additional CQICHs assigned to this SS (0-3)</u>
<u> for (i=0; i<CQICH_Num; i++) {</u>		
<u> Feedback type</u>	<u>3 bits</u>	<u>Type of feedback on this CQICH</u>

<u>Allocation index</u>	<u>6 bits</u>		
{ }			
{ }	<u>Variable</u>		
<u>Padding</u>		<u>Padding to Nibble; shall be set to 0</u>	
{ }			

Control Header

4 bits are used to indicate the following control information. If the first bit is set to 1, this means that MIMO Control information follows. If the second bit is set to 1, this IE shall contain CQI control information. Other bits are reserved for future extension.

N layer

Specifies the number of layers contained in this burst. The layer is defined as a separate coding/modulation path.

Matrix Indicator

This field indicates MIMO matrix for the burst.

Period

Informs the SS of the period of CQI reports. A CQI feedback is transmitted on the CQICH every 2^p frames

Frame Offset

Informs the SS when to start transmitting reports. The SS starts reporting at the frame number which has the same 3 LSBs as the specified Frame Offset. If the current frame is specified, the SS shall start reporting in 8 frames.

Duration

Indicates when the SS should stop reporting unless the CQICH allocation is refreshed beforehand. If Duration is set to 0b0000, the BS shall de-allocate the CQICH. If Duration is set to 0b1111, the CQICH is allocated indefinitely and the SS should report until it receives another MAP IE with Duration set to 0b0000.

Allocation Index¹

Indicates position from the start of the CQICH region.

Feedback Type

Indicates the type of feedback content on the allocated CQICH from SS. Its mapping shall be

000 = Fast DL measurement/Default Feedback

001 = Quantized precoding weight feedback

010-111 = Reserved

----- **End of Text Change** -----

[Modify the text from line 4 on page 348 to line 24 on page 349 of [1] as follows]

----- **Start of Text Change** -----

Table 302I -- H-ARQ UL MAP IE

Syntax	Size	Note
H-ARQ UL MAP IE()		
Extended UIUC	4	Set to 0x1
Length	8	Indicates the length of the IE in bytes
RCID_Type	2 bits	00 = Normal CID 01 = RCID11 10 = RCID7 11 = RCID3
while (data remains) {		
Allocation Start Indication	1 bit	0: No allocation start information 1: Allocation start information follows
If (Allocation Start Indication == 1) {		
OFDMA Symbol offset	8 bits	This value indicates start Symbol offset of

Subchannel offset		7 bits	subsequent sub-bursts in this H-ARQ UL MAP IE
}			This value indicates start Subchannel offset of subsequent sub-bursts in this H-ARQ UL MAP IE
Mode		3 bit	Indicates the mode of this IE 000 = Chase H-ARQ 001 = Incremental redundancy H-ARQ for CTC 010 = Incremental redundancy H-ARQ for convolutional code 011 = MIMO Chase H-ARQ 100 = MIMO IR H-ARQ 101 = MIMO IR H-ARQ for Convolutional Code 110 = MIMO STC H-ARQ 111 = Reserved
N sub-Burst			This field indicates the number of bursts in this UL MAP IE
For (i=0 ; i < N Sub-burst; i++) {		4 bits	
if (Mode == 000) {			
UL HARQ Chase Sub-Burst IE ()			
} else if (Mode== 001) {			
UL HARQ IR CTC Sub-Burst IE ()			
} else if (Mode== 010) {			
UL HARQ IR CC Sub-Burst IE ()			
} else if (Mode== 011) {			
MIMO UL Chase HARQ Sub-Burst IE ()			
} else if (Mode== 100) {			
MIMO UL IR H-ARQ Sub-Burst IE ()			
} else if (Mode== 101) {			
MIMO UL IR HARQ for CC Sub-Burst IE ()			
} else if (Mode == 110) {			
MIMO UL STC HARQ Sub-Burst IE ()			
}			
}			
}			
Padding		Variable	Padding to byte; shall be set to 0
}			

----- End of Text Change -----

[Add the following text after line 27 on page 351]

----- Start of Text Change -----

[Table 302p -- MIMO UL Chase HARQ Sub-Burst IE Format](#)

MIMO UL Chase HARQ Sub-Burst IE{				
MU Indicator		1 bit		Indicates whether this UL burst is

<u>Dedicated MIMO UL Control Indicator</u>			<u>intended for multiple SS</u>	
<u>if (MU indicator == 0) {</u>				
<u> RCID IE()</u>				
<u> If (Dedicated MIMO UL Control Indicator ==1){</u>				
<u> Dedicated MIMO UL Control IE ()</u>				
<u> }</u>				
<u>}</u>				
<u>Duration</u>			<u>10 bits</u>	
<u>For (j=0;j<N_layer;j++) {</u>				
<u> if (MU indicator == 1) {</u>				
<u> RCID IE()</u>			<u>Variable</u>	
<u> }</u>				
<u> UIUC</u>			<u>4 bits</u>	
<u> Repetition Coding Indication</u>			<u>2 bits</u>	
<u> ACID</u>			<u>4 bits</u>	
<u> AI_SN</u>			<u>1 bit</u>	
<u>}</u>				
<u>}</u>				

For each single SS sub-burst (MU indicator = 0) matrix and layer information shall be read from Dedicated MIMO UL Control IE, if set by the indicator bit, and be applied to the burst accordingly. For each multi SS sub-burst (MU Indicator = 1), N_layer for this sub-burst shall be set to 2 and the first SS with the first RCID shall use the pilot pattern A in 8.4.8.1.5 and the first UIUC, whereas the second SS with the second RCID shall use the pilot pattern B and the second UIUC.

Table 302q -- MIMO UL IR HARQ Sub-Burst IE Format

<u>MIMO UL IR HARQ Sub-Burst IE{</u>				
<u> MU Indicator</u>				
<u> Dedicated MIMO UL Control Indicator</u>				
<u> if (MU indicator == 0) {</u>				
<u> RCID IE()</u>				
<u> If (Dedicated MIMO UL Control Indicator ==1){</u>				
<u> Dedicated MIMO UL Control IE ()</u>				
<u> }</u>				
<u> }</u>				
<u> Nsch</u>				
<u> SPID</u>				
<u> ACID</u>				
<u> AI_SN</u>				
<u> For (i=0;i<N_layer;i++) {</u>				
<u> if (MU indicator == 1) {</u>				

<u>RCID IE()</u>	<u>Variable</u>	<u>4 bits</u>	
{			
<u>Nep</u>			
{			
}			

Table 302r -- MIMO UL IR HARQ for CC Sub-Burst IE Format

<u>MIMO UL IR HARQ for CC Sub-Burst IE{</u>			
<u>MU Indicator</u>	<u>1 bit</u>		<u>Indicates whether this UL burst is intended for multiple SS</u>
<u>Dedicated MIMO UL Control Indicator</u>	<u>1 bit</u>		
<u>if(MU indicator == 0) {</u>			
<u> RCID IE()</u>	<u>Variable</u>		
<u> If(Dedicated MIMO UL Control Indicator ==1) {</u>			
<u> Dedicated MIMO UL Control IE ()</u>	<u>variable</u>		
<u> }</u>			
<u>}</u>			
<u>Duration</u>	<u>10 bits</u>		
<u>For (i=0;i<N_layer;i++) {</u>			
<u> if(MU indicator == 1) {</u>			
<u> RCID IE()</u>	<u>Variable</u>		
<u> }</u>			
<u> UIUC</u>	<u>4 bits</u>		
<u> Repetition Coding Indication</u>	<u>2 bits</u>		<u>0b00 – No repetition coding</u> <u>0b01 – Repetition coding of 2 used</u> <u>0b10 – Repetition coding of 4 used</u> <u>0b11 – Repetition coding of 6 used</u>
<u> ACID</u>	<u>4 bits</u>		
<u> AI_SN</u>	<u>1 bit</u>		
<u> SPID</u>	<u>2 bit</u>		
<u>}</u>			
<u>}</u>			

Table 302s -- MIMO UL STC HARQ Sub-Burst IE Format

<u>MIMO UL STC HARQ Sub-Burst IE{</u>			
<u>Tx count</u>	<u>2 bits</u>		<u>00: first transmission</u> <u>01: second transmission</u> <u>10: third transmission</u> <u>11: fourth transmission</u>
<u>Duration</u>	<u>10 bits</u>		
<u>if(Tx count ==0) {</u>			
<u> if(MU indicator == 0) {</u>			
<u> RCID IE()</u>	<u>Variable</u>		
<u> If(Dedicated MIMO UL Control Indicator ==1) {</u>			
<u> Dedicated MIMO UL Control IE ()</u>	<u>variable</u>		

<u>}</u>								
<u>}</u>								
<u>For (i=0;i<N_layer;i++) {</u>								
<u> If (MU indicator == 1) {</u>								
<u> RCID IE()</u>					Variable			
<u> }</u>								
<u> UIUC</u>					4 bits			
<u> Repetition Coding Indication</u>					2 bits			
<u> }</u>						0b00 – No repetition coding		
<u> ACID</u>						0b01 – Repetition coding of 2 used		
<u> }</u>						0b10 – Repetition coding of 4 used		
<u>}</u>						0b11 – Repetition coding of 6 used		

----- End of Text Change -----

[Add the following text after line 61 on page 351]

----- Start of Text Change -----

8.4.5.4.25.2 Dedicated MIMO UL Control IE Format

Dedicated UL Control IE for MIMO contains additional control information for each sub bursts.

Table 302t -- Dedicated MIMO UL Control IE Format

Syntax	size	Note
<u>Dedicated MIMO UL Control IE()</u> {	-	-
<u> Matrix</u>	2 bits	Indicates transmission matrix (See 8.4.8) 00 = Matrix A (Transmit Diversity) 01 = Matrix B (Spatial Multiplexing) 10-11 = Reserved
<u> N_layer</u>	2 bits	Number of coding/modulation layers 00 = 1 layer 01 = 2 layers 10-11 = Reserved
<u>}</u>		

----- End of Text Change -----

References

- [1] IEEE P802.16e/D6 Air Interface for Fixed and Mobile Broadband Wireless Access Systems – Amendment for Physical and Medium Access Control Layers for Combined Fixed and Mobile Operation in Licensed Bands
- [2] IEEE C802.16e-05/038r1 “Normal MAP Extension for MIMO H-ARQ”, accepted at 35th 802.16 Meeting in Jan. 2005

