

Project	<b>IEEE 802.16 Broadband Wireless Access Working Group</b> < <a href="http://ieee802.org/16">http://ieee802.org/16</a> >	
Title	<b>Corrections to MBS in 802.16REV2</b>	
Date Submitted	<b>2008-05-11</b>	
Source(s)	E-mail:	
	Kamran Etemad (Intel)	<a href="mailto:kamran.etemad@intel.com">kamran.etemad@intel.com</a>
	Jonathan Segev, Yaron Alpert (Comsys)	<a href="mailto:jonathan.segev@comsystemobile.com">jonathan.segev@comsystemobile.com</a> <a href="mailto:aron.alpert@comsystemobile.com">aron.alpert@comsystemobile.com</a>
	Nadav Lavi, Vladimir Yanover, (Alvarion)	<a href="mailto:Nadav.lavi@alvarion.com">Nadav.lavi@alvarion.com</a> ; <a href="mailto:Vladimir.yanover@alvarion.com">Vladimir.yanover@alvarion.com</a>
	Peretz Shkalim (Runcom);	<a href="mailto:peretz@runcom.co.il">peretz@runcom.co.il</a>
Re:	P802.16Rev2/D5, LB26d	
Abstract	MBS definitions and procedures in the REV2 D5 draft needs some correction.	
Purpose	Adoption toward REV2/D6	
Notice	<i>This document does not represent the agreed views of the IEEE 802.16 Working Group or any of its subgroups. It represents only the views of the participants listed in the "Source(s)" field above. It is offered as a basis for discussion. It is not binding on the contributor(s), who reserve(s) the right to add, amend or withdraw material contained herein.</i>	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy	The contributor is familiar with the IEEE-SA Patent Policy and Procedures: < <a href="http://standards.ieee.org/guides/bylaws/sect6-7.html#6">http://standards.ieee.org/guides/bylaws/sect6-7.html#6</a> > and < <a href="http://standards.ieee.org/guides/opman/sect6.html#6.3">http://standards.ieee.org/guides/opman/sect6.html#6.3</a> >. Further information is located at < <a href="http://standards.ieee.org/board/pat/pat-material.html">http://standards.ieee.org/board/pat/pat-material.html</a> > and < <a href="http://standards.ieee.org/board/pat">http://standards.ieee.org/board/pat</a> >.	

## **Correction to MBS in 802.16REV2**

*Kamran Etemad (Intel)*

*Jonathan Segev, Yaron Alpert (Comsys)*

*Nadav Lavi, Vladimir Yanover (Alvarion)*

*Peretz Shkalim (Runcom);*

### **Introduction**

Rev2D5 removed to requirement for a separate permutation zone. The purpose of this removal was to enable a flexible scheduling of MBS bursts such they are not part of dedicated permutation zone for MBS. However the PHY initialization of the PRBS generator (see 8.3.3.4.2) mandates the knowledge of the relative position within the permutation zone.

As a result the MBS daisy chain mechanism is broken as there is no longer a requirement to transmit a separate permutation zone and the MS must (also for IDLE ):

1. First decode the DL MAP
2. Identify all permutation zones described in the DL MAP.
3. Calculate the burst relative position within the relevant permutation zone.

Only than it can perform demodulation of the MBS burst.

This effectively diminishes the benefit of daisy chain:

Reduces the probability of correct MBS burst decoding (as the correct decoding is now dependent on 2 consecutive DL MAPs in addition to the correct decoding of the MBS MAP and the PDU in the burst).

And increase power consumption when MS with active MBS connection in Sleep mode or in IDLE mode during unavailability interval.

Since Macro-diversity only mandates the transmission of DL MAP in some of the bursts this problem pertains to both Macro-diversity and non Macro-diversity MBS zones.

### **Proposed Solution**

- Return the requirement of a separate permutation zone for MBS zone (MBS zones may share a single permutation zone) – return to the previous state of Rev2D3.
- Correct the MBS MAP IE which is broken for the non macro diversity case such it supports the daisy chain.

## Proposed Text Modification

[In 6.3.2.3.52, modify the text:]

### 6.3.2.3.52 MBS\_MAP (multicast and broadcast service map) message

The BS shall send an MBS\_MAP message on the Broadcast CID to specify the location and size of ~~multi-BS~~ MBS data bursts which are located in [DL permutation zones designated for MBS in](#) frames that are from 2 to 5 frames in the future from the frame containing the MBS MAP message. If present, an MBS\_MAP message shall be located at the first symbol and the first subchannel in [the DL permutation zone for MBS](#). The MBS\_MAP message format is presented in Table 153. This message includes the MBS\_DATA\_IE, Extended\_MBS\_DATA\_IE and MBS\_DATA\_Time\_Diversity\_IE which define the access information for the MBS burst. See Tables 155, 156, 157 and 158.

[Insert text after table 154:]

[The MBS DL permutation zone start position of the next MBS MAP shall be indicated on MBS MAP via the Next MBS OFDMA Symbol Offset parameter which identifies the MBS permutation Zone.](#)

[The start position of the MBS DL permutation zone of the MBS data bursts is indicated by the smallest OFDMA Symbol Offset parameter of MBS DATA IE, Extended MBS DATA IE and MBS DATA Time Diversity IE conveyed by the relevant MBS MAP.](#)

[The permutation type, DL\\_PermBase and PRBS\\_ID of the MBS permutation zone shall not change.](#)

[Modify table 335:]

Syntax	Size (bit)	Notes
MBS_MAP_IE() {	-	-
Extended-2 DIUC	4	MBS MAP IE = 0x00
Length	8	-
MBS Zone identifier	7	MBS Zone identifier corresponds to the identifier provided by the BS at connection initiation
Macro diversity enhanced	1	0: Non Macro-Diversity enhanced zone; 1: Macro-Diversity enhanced zone
<del>    If(Macro diversity enhanced Multi-BS MBS = 1){</del>	-	-
Permutation	2	0b00: PUSC permutation 0b01: FUSC permutation 0b10: Optional FUSC permutation 0b11: Adjacent subcarrier permutation
DL_PermBase	5	-
PRBS_ID	2	-
OFDMA Symbol Offset	7	The offset of the OFDMA symbol measured in OFDMA symbols from beginning of the DL frame in which the DL-MAP is transmitted. Counting from the frame preamble and starting from 0
MBS MAP message allocation included indication	1	Used to indicate if the MBS MAP message allocation parameters are included
Reserved	3	Shall be set to zero
if (MBS MAP message allocation included = 1) {	-	-
Reserved	3	-
Boosting	3	Refer to Table 319

DIUC	4	-
No. Subchannels	6	Indication of burst size of MBS MAP message with the number of subchannels
NO. OFDMA symbols	6	Indication of burst size of MBS MAP message with the number of OFDMA symbols
Repetition Coding Indication	2	0b00—No repetition coding 0b01—Repetition coding of 2 used 0b10—Repetition coding of 4 used 0b11—Repetition coding of 6 used
<del>————— } ————— } else {</del>	<del>-</del>	<del>-</del>
<del>————— DIUC</del>	<del>4</del>	<del>-</del>
<del>————— CID</del>	<del>16</del>	<del>CID for single BS MBS</del>
<del>————— OFDMA Symbol Offset</del>	<del>8</del>	<del>The offset of the first OFDMA symbol of the MBS region measured in OFDMA symbols from beginning of this DL frame.</del>
<del>————— Subchannel offset</del>	<del>6</del>	<del>The lowest index OFDMA subchannel used for carrying the burst, starting from subchannel 0.</del>
<del>————— Boosting</del>	<del>3</del>	<del>Refer to Table 319</del>
<del>————— SLC_3_indication</del>	<del>1</del>	<del>Used to notify sleep mode class 3 is used for single BS MBS service</del>
<del>————— NO. OFDMA Symbols</del>	<del>6</del>	<del>-</del>
<del>————— NO. Subchannels</del>	<del>6</del>	<del>-</del>
<del>————— Repetition Coding Indication</del>	<del>2</del>	<del>0b00—No repetition coding 0b01—Repetition coding of 2 used 0b10—Repetition coding of 4 used 0b11—Repetition coding of 6 used</del>
<del>————— if (SLC_3_indication = 1) { ————— Next MBS_MAP_IE Frame Offset</del>	<del>-</del>	<del>-</del>
<del>————— } ————— } if !(byte boundary) {     Padding Nibble</del>	<del>-</del>	<del>-</del>
<del>    }</del>	<del>Variable</del>	<del>Padding to reach byte boundary</del>
<del>}</del>	<del>-</del>	<del>-</del>

The burst carrying MBS MAP message shall be located at the first subchannel and first OFDMA symbol of the DL permutation zone designated for the MBS Zone region that is specified by the MBS MAP IE ~~when ‘Macro diversity enhanced’ is set to 1~~. This ~~MBS region~~ burst shall be located in the same frame as the MBS MAP IE that specifies it. The location of this DL permutation zone designated for the MBS zone region within the frame is specified by ‘OFDMA Symbol Offset’ in MBS MAP IE. The parameters of the DL permutation zone designated for MBS shall only be changed such that the daisy chain mechanism continues uninterrupted.

[In 11.13.23, modify the text:]

### 11.13.23 MBS service TLV

This TLV indicates whether the MBS service is being requested or provided for the connection that is being setup. A value of 1 indicates that an MBS service limited to the serving BS is being requested and a value of 2 indicates multi-BS-MBS is being requested (either with or without Macro-diversity). If MS or BS wants to initiate MBS service, DSA-REQ with MBS service TLV

shall be used. The DSA-RSP message shall contain the acceptance or rejection of request and if there is no available MBS, MBS service value shall be set to 0.

Type	Length	Value	Scope
[145/146].4	1	0: No available MBS 1: MBS in Serving BS Only 2: MBS in a multi-BS Zone	DSA-REQ DSA-RSP DSA-ACK

## Introduction

[1] Clarifications and Improvement in the MBS definitions and procedures in 802.16REV2, (IEEE C802.16maint-08/064r8, 2008-03-20).