

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Support for Closed-Loop MIMO in H-ARQ MAP IE	
Date Submitted	2005-04-28	
Source(s)	<p>Wonil Roh, JeongTae Oh, Kyunbyoung Ko, Chan-Byoung Chae, Hongsil Jeong, Sung-Ryul Yun, Seungjoo Maeng, Jaeho Jeon, Jaeyeol Kim, Soonyoung Yoon, Yong Chang</p> <p>Samsung Electronics Co., Ltd.</p> <p>Erik Lindskog, Kamlesh Rath, Dave Garrett and Brett Schein.</p> <p>Beceem Communications, Inc.</p> <p>Wen Tong, Mo-Han Fong</p> <p>Nortel Networks</p> <p>Yigal Eliaspur, Jose Puthenkulam, Randall Schwartz</p> <p>Intel</p> <p>Bin-Chul Ihm, Jin Young Chun</p> <p>LGE</p> <p>Mark Cudak, Kevin Baum</p> <p>Motorola</p> <p>Sean Cai, Jason Hou</p> <p>ZTE</p>	<p>wonil.roh@samsung.com</p> <p>Voice: +82-31-279-3868</p> <p>elindskog@beceem.com</p> <p>Voice: +1-408-387-5014</p>
Re:		
Abstract	Support for Closed-Loop MIMO in H-ARQ MAP IE	
Purpose	Adoption of proposed changes into P802.16e	
	Crossed-out indicates deleted text, <u>underlined blue indicates new text change to the Standard</u>	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	

Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures (Version 1.0) < http://ieee802.org/16/ipr/patents/policy.htm >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, if there is technical justification in the opinion of the standards-developing committee and provided the IEEE receives assurance from the patent holder that it will license applicants under reasonable terms and conditions for the purpose of implementing the standard."

Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair <<mailto:r.b.marks@ieee.org>> as early as possible, in written or electronic form, of any patents (granted or under application) that may cover technology that is under consideration by or has been approved by IEEE 802.16. The Chair will disclose this notification via the IEEE 802.16 web site <<http://ieee802.org/16/ipr/patents/notices>>.

Support for Closed-Loop MIMO in H-ARQ MAP IE

1. Introduction

[Note: This contribution is prepared to help the Editor to adopt the contents of this accepted contribution into the draft standard. It only contains minor editorial changes (proper Section and Table numbers, correct page and lines numbers etc) from the original accepted one (C802.16e-05/156r2 by Comment #3333)]

There are two objectives that this document is prepared to achieve: one editorial and one technical. The editorial part is to provide the correct Section/Table numbers and the technical part is to provide an important feature with small amount of text changes.

The H-ARQ MAP IE for MIMO bursts was introduced in [2] and accepted by the Working Group in 35th meeting in Sanya, but it failed to be added to the current draft standard [1]. The same proposal is re-written with proper Section and Table numbers in line with the existing texts. This is the editorial part. Based on this accepted texts, a much needed closed-loop capability is proposed with a minimal impact to the spec, which is the technical part of the document. The CL-MIMO functionalities included in the text change are identical to the accepted CL-MIMO DL MAP IE (8.4.5.3.25) with additional H-ARQ features.

This document is the results of harmonization efforts among the following comments:
3326, 3327, 3333, 3334, 3527, 3528

2. Specific Text Changes

[Add the following text after line 32 on page 279 in section 8.4.5.3.22]

----- Start of Text Change -----

Table 285q -- MIMO DL Chase H-ARQ Sub-Burst IE Format

<u>MIMO DL Chase H-ARQ Sub-Burst IE {</u>			
<u>N sub burst</u>	<u>5</u>	<u>Number of sub-bursts in the region</u>	<u>2D</u>
<u>For (j=0; j< N sub burst; j++){</u>			
<u>MU Indicator</u>	<u>1 bit</u>	<u>Indicates whether this DL burst is intended for multiple SS</u>	
<u>Dedicated MIMO DL Control Indicator</u>	<u>1 bit</u>		
<u>ACK Disable</u>	<u>1 bit</u>	<u>When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.</u>	
<u>If (MU indicator == 0) {</u>			
<u>RCID IE()</u>	<u>Variable</u>		
<u> }</u>			
<u>If (Dedicated MIMO DL Control Indicator ==1) {</u>			
<u>Dedicated MIMO DL Control IE ()</u>	<u>variable</u>		
<u> }</u>			

<u>Length</u>	<u>10 bits</u>	
<u>For (i=0;i<N_layer;i++) {</u>		
<u>if (MU indicator == 1) {</u>		
<u>RCID IE()</u>	<u>Variable</u>	
<u>}</u>		
<u>DIUC</u>	<u>4 bits</u>	
<u>Repetition Coding Indication</u>	<u>2 bits</u>	<u>0b00 – No repetition coding</u> <u>0b01 – Repetition coding of 2 used</u> <u>0b10 – Repetition coding of 4 used</u> <u>0b11 – Repetition coding of 6 used</u>
<u>If (ACK Disable ==0) {</u>		
<u>ACID</u>	<u>4 bits</u>	
<u>AI_SN</u>	<u>1 bit</u>	
<u>}</u>		
<u>}</u>		
<u>}</u>		
<u>}</u>		

When MU Indicator = 1 for a particular loop index j in the MIMO DL Chase H-ARQ Sub-Burst IE, MIMO DL IR H-ARQ Sub-Burst IE, or the MIMO DL IR H-ARQ for CC Sub-Burst IE, each layer shall be allocated its associated ACK channel. In this case, the number of ACK channels associated with the sub-burst IE will be greater than N_sub_burst.

For each multi SS sub-burst (MU Indicator = 1), if the dedicated pilot bit is set to 1 in the STC_ZONE IE (section 8.4.5.3.4) for the zone in which the sub-burst allocations are being made, N_layer for this sub-burst selects the pilot format for the sub-burst by interpreting N_layer as the number of transmit antennas (as defined in 8.4.8), and the SS with the first RCID shall be assigned the pilot pattern corresponding to antenna 1, of section 8.4.8, the second to the pilot pattern corresponding to antenna 2, and so on.

Table 285r -- MIMO DL IR H-ARQ Sub-Burst IE Format

<u>MIMO DL IR H-ARQ Sub-Burst IE {</u>		
<u>N sub burst</u>	<u>5</u>	<u>Number of sub-bursts in the 2D region</u>
<u>For (j=0; j< N sub burst; j++){</u>		
<u>MU Indicator</u>	<u>1 bit</u>	<u>Indicates whether this DL burst is intended for multiple SS</u>
<u>Dedicated MIMO DL Control Indicator</u>	<u>1 bit</u>	
<u>ACK Disable</u>	<u>1 bit</u>	<u>When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.</u>
<u>If (MU indicator == 0) {</u>		
<u>RCID IE()</u>	<u>Variable</u>	
<u>}</u>		
<u>If (Dedicated MIMO DL Control Indicator ==1) {</u>		
<u>Dedicated MIMO DL Control IE ()</u>	<u>variable</u>	
<u>}</u>		
<u>Nsch</u>	<u>4 bits</u>	
<u>If (ACK Disable ==0) {</u>		
<u>SPID</u>	<u>2 bits</u>	

<u>ACID</u>	<u>4 bits</u>	
<u>AI SN</u>	<u>1 bit</u>	
<u>}</u>		
<u>For (i=0;i<N_layer;i++) {</u>		
<u> if (MU indicator == 1) {</u>		
<u> RCID IE()</u>	<u>Variable</u>	
<u> }</u>		
<u> Nep</u>	<u>4 bits</u>	
<u> }</u>		
<u>}</u>		
<u>}</u>		

Table 285s -- MIMO DL IR H-ARQ for CC Sub-Burst IE Format

<u>MIMO DL IR H-ARQ for CC Sub-Burst IE {</u>			
<u> N sub burst</u>	<u>5</u>		<u>Number of sub-bursts in the 2D region</u>
<u> For (j=0; j< N sub burst; j++){</u>			
<u> <u>MU Indicator</u></u>	<u>1 bit</u>		<u>Indicates whether this DL burst is intended for multiple SS</u>
<u> <u>Dedicated MIMO DL Control Indicator</u></u>	<u>1 bit</u>		
<u> <u>ACK Disable</u></u>	<u>1 bit</u>		<u>When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.</u>
<u> <u>If (MU indicator == 0) {</u></u>			
<u> <u>RCID IE()</u></u>	<u>Variable</u>		
<u> <u>}</u></u>			
<u> <u>If (Dedicated MIMO DL Control Indicator ==1) {</u></u>			
<u> <u>Dedicated MIMO DL Control IE ()</u></u>	<u>variable</u>		
<u> <u>}</u></u>			
<u> <u>Length</u></u>	<u>10 bits</u>		
<u> <u>For (i=0;i<N_layer;i++) {</u></u>			
<u> <u>if (MU indicator == 1) {</u></u>			
<u> <u>RCID IE()</u></u>	<u>Variable</u>		
<u> <u>}</u></u>			
<u> <u>DIUC</u></u>	<u>4 bits</u>		
<u> <u>Repetition Coding Indication</u></u>	<u>2 bits</u>		<u>0b00 – No repetition coding 0b01 – Repetition coding of 2 used 0b10 – Repetition coding of 4 used 0b11 – Repetition coding of 6 used</u>
<u> <u>If (ACK Disable ==0) {</u></u>			
<u> <u>ACID</u></u>	<u>4 bits</u>		
<u> <u>AI SN</u></u>	<u>1 bit</u>		
<u> <u>SPID</u></u>	<u>2 bits</u>		
<u> <u>}</u></u>			
<u> <u>}</u></u>			
<u> }</u>			

}		
---	--	--

Table 285t -- MIMO DL STC H-ARO Sub-Burst IE Format

This IE is used to support the STC subpacket retransmission .

<u>MIMO DL STC H-ARO Sub-Burst IE {</u>		
<u>N sub burst</u>	<u>5</u>	<u>Number of sub-bursts in the 2D region</u>
<u>For (j=0; j< N sub burst; j++){</u>		
<u>Tx count</u>	<u>2 bits</u>	<u>00: initial transmission</u> <u>01: odd retransmission</u> <u>10: even retransmission</u> <u>11: reserved</u>
<u>Length</u>	<u>10 bits</u>	
<u>Sub-burst offset indication</u>	<u>1 bits</u>	<u>Indicates the inclusion of sub-burst offset</u>
<u>Reserved</u>	<u>3 bits</u>	
<u>If (Sub-burst offset indication == 1) {</u>		
<u>Sub-burst offset</u>	<u>8 bits</u>	<u>Offset in slots with respect to the previous sub-burst defined in this data region. If this is the first subburst within the data region, this offset is with respect to slot 0 of the data region.</u>
<u>}</u>		
<u>RCID IE()</u>	<u>Variable</u>	
<u>if (Tx count ==00) {</u>		
<u>Dedicated MIMO DL Control Indicator</u>	<u>1 bit</u>	
<u>ACK Disable</u>	<u>1 bit</u>	<u>When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.</u>
<u>If (Dedicated MIMO DL Control Indicator ==1) {</u>		
<u>Dedicated MIMO DL Control IE ()</u>	<u>variable</u>	
<u>}</u>		
<u>DIUC</u>	<u>4 bits</u>	
<u>Repetition Coding Indication</u>	<u>2 bits</u>	<u>0b00 – No repetition coding</u> <u>0b01 – Repetition coding of 2 used</u> <u>0b10 – Repetition coding of 4 used</u> <u>0b11 – Repetition coding of 6 used</u>
<u>}</u>		
<u>If (ACK Disable ==0) {</u>		
<u>ACID</u>	<u>4 bits</u>	
<u>}</u>		
<u>}</u>		

8.4.5.3.22.1 Dedicated MIMO DL Control IE Format

Dedicated DL Control IE for MIMO contains additional control information for each sub-burst. Because each sub-burst may have its own control information format dependent on the MSS capability, the length of the Dedicated DL Control IE for MIMO is variable.

Table 285u -- Dedicated MIMO DL Control IE Format

<u>Syntax</u>	<u>size</u>	<u>Note</u>
<u>Dedicated MIMO DL Control IE() {</u>	-	-
<u> Length</u>	<u>5 bits</u>	<u>Length of following control information in Nibble.</u>
<u> Control Header</u>	<u>3 bits</u>	<u>Bit #0 : MIMO Control Info</u> <u>Bit #1 : COI Control Info</u> <u>Bit #2 : Closed MIMO Control Info</u>
<u> N_layer</u>	<u>2 bits</u>	<u>Number of coding/modulation layers</u> <u>00 = 1 layer</u> <u>01 = 2 layers</u> <u>10 = 3 layers</u> <u>11 = 4 layers</u>
<u> if(MIMO Control Info == 1){</u>		
<u> Matrix</u>	<u>2 bits</u>	<u>Indicates transmission matrix (See 8.4.8)</u>
<u> if(Dedicated Pilots == 1) {</u>		<u>Dedicated Pilots field in STC_Zone_IE()</u>
<u> Num_Beamformed_Streams</u>	<u>2 bits</u>	<u>Indicates the number of beamformed streams which is equal to the number of pilot patterns</u> <u>00 = 1 stream</u> <u>01 = 2 streams</u> <u>10 = 3 streams</u> <u>11 = 4 streams</u>
<u> }</u>		
<u> }</u>		
<u> If(COICH Control Info == 1){</u>		
<u> Period</u>	<u>3 bits</u>	<u>Period (in frame) = 2^period</u>
<u> Frame offset</u>	<u>3 bits</u>	
<u> Duration</u>	<u>4 bits</u>	<u>A COI feedback is transmitted on the COI channels indexed by the COICH_ID for 10 x 2^d frames.</u>
<u> For (j=0;N_layer+1;j++) {</u>		
<u> Allocation index¹</u>	<u>6 bits</u>	<u>Index to COICH assigned to this layer.</u>
<u> }</u>		
<u> COICH_Num</u>	<u>2 bits</u>	<u>Number of additional COICHs assigned to this SS (0-3)</u>
<u> for (i=0; i<COICH_Num; i++) {</u>		
<u> Feedback type</u>	<u>3 bits</u>	<u>Type of feedback on this COICH</u>
<u> Allocation index</u>	<u>6 bits</u>	
<u> }</u>		
<u> }</u>		
<u> if(Closed MIMO Control Info == 1){</u>		
<u> if(MIMO Control Info==1)</u>		
<u> MIMO mode = Matrix</u>		
<u> else</u>		
<u> MIMO mode = Matrix in</u>		
<u> STC_Zone_IE()</u>		
<u> If(MIMO mode == 00 or 01) {</u>		
<u> Antenna Grouping Index }</u>	<u>3 bits</u>	<u>Indicates the index of antenna grouping</u> <u>See 8.4.8.3.4 and 8.4.8.3.5</u> <u>If((Matrix_indicator == 00)</u>

			000~010 = 0b101110~0b110000 in Table 298c else 000~101 = 0b110001~0b110110 in Table 298c
<u>elseif (MIMO mode == 10) {</u>			
<u> Num_stream</u>	<u>2 bits</u>		<u>Indicates the number of streams in Table 316f for 3 Tx and Table 316g for 4 Tx.</u>
<u> Antenna Selection Index }</u>	<u>3 bits</u>		<u>Indicates the index of antenna selection</u> <u>See 8.4.8.3.4 and 8.4.8.3.5</u> <u>000~110 = 0b110000~0b110101 in Table 298d</u>
<u>elseif (MIMO mode == 11) {</u>			
<u> Num_stream</u>	<u>2 bits</u>		<u>Indicates number of streams</u>
<u> Codebook Precoding Index }</u>	<u>6 bits</u>		<u>Indicates the index of precoding matrix W in the codebook</u> <u>See 8.4.8.3.6</u>
<u> }</u>			
<u> Padding</u>	<u>Variable</u>		<u>Padding to Nibble; shall be set to 0</u>
<u>}</u>			

Control Header

4 bits are used to indicate the following control information. If the first bit is set to 1, this means that MIMO Control information follows. If the second bit is set to 1, this IE shall contain COI control information. Other bits are reserved for future extension.

N_layer

Specifies the number of layers contained in this burst. The layer is defined as a separate coding/modulation path.

Matrix Indicator

This field indicates MIMO matrix for the burst.

Period

Informs the SS of the period of COI reports. A COI feedback is transmitted on the CQICH every 2^p frames

Frame Offset

Informs the SS when to start transmitting reports. The SS starts reporting at the frame number which has the same 3 LSBs as the specified Frame Offset. If the current frame is specified, the SS shall start reporting in 8 frames.

Duration

Indicates when the SS should stop reporting unless the CQICH allocation is refreshed beforehand. If Duration is set to 0b0000, the BS shall de-allocate the CQICH. If Duration is set to 0b1111, the CQICH is allocated indefinitely and the SS should report until it receives another MAP_IE with Duration set to 0b0000.

Allocation Index¹

Indicates position from the start of the CQICH region.

Feedback Type

Indicates the type of feedback content on the allocated CQICH from SS. Its mapping shall be

- 000 = Fast DL measurement/Default Feedback with antenna grouping
- 001 = Fast DL measurement/Default Feedback with antenna selection
- 010 = Fast DL measurement/Default Feedback with reduced code book
- 011 = Quantized precoding weight feedback
- 100 = Index to precoding matrix in code book
- 101 = Channel Matrix Information
- 110 = Per stream power control
- 111 = Reserved

----- End of Text Change -----

[Add the following text after line 41 on page 371 in 8.4.5.4.24]

----- Start of Text Change -----

Table 302p – MIMO UL Chase HARQ Sub-Burst IE Format

MIMO UL Chase HARQ Sub-Burst IE{		
<u>MU Indicator</u>	1 bit	<u>Indicates whether this UL burst is intended for multiple SS</u>
<u>Dedicated MIMO UL Control Indicator</u>	1 bit	
<u>ACK Disable</u>	1 bit	<u>When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.</u>
<u>if (MU indicator == 0) {</u>		
<u>RCID IE()</u>	Variable	
<u>If (Dedicated MIMO UL Control Indicator ==1) {</u>		
<u>Dedicated MIMO UL Control IE ()</u>	variable	
<u>}</u>		
<u>} else {</u>		
<u>Matrix</u>	1 bit	<u>Indicates transmission matrix (See 8.4.8) for MS with dual Tx antennas</u> <u>0 = Matrix A</u> <u>1 = Matrix B</u> <u>Ignored by MS with single Tx antenna</u>
<u>}</u>		
<u>Duration</u>	10 bits	
<u>For (i=0;i<N_layer;i++) {</u>		
<u>if (MU indicator == 1) {</u>		
<u>RCID IE()</u>	Variable	
<u>}</u>		
<u>UIUC</u>	4 bits	
<u>Repetition Coding Indication</u>	2 bits	<u>0b00 – No repetition coding</u> <u>0b01 – Repetition coding of 2 used</u> <u>0b10 – Repetition coding of 4 used</u> <u>0b11 – Repetition coding of 6 used</u>
<u>If (ACK Disable ==0) {</u>		
<u>ACID</u>	4 bits	
<u>AI_SN</u>	1 bit	
<u>}</u>		
<u>}</u>		
<u>}</u>		

When MU Indicator = 1 for a particular loop index j in the MIMO UL Chase H-ARQ Sub-Burst IE, MIMO UL IR H-ARQ Sub-Burst IE, or the MIMO UL IR H-ARQ for CC Sub-Burst IE, each layer shall be allocated its associated bit position in the ACK channel bitmap. In this case, the number of bits in the ACK channel bitmap associated with the sub-burst IE will be greater than N_sub_burst.

For each single MS sub-burst (MU indicator = 0) matrix and layer information shall be read from Dedicated MIMO UL Control IE, if set by the indicator bit, and be applied to the burst accordingly. For each multi SS sub-burst (MU Indicator = 1), N_layer for this sub-burst shall be set to 2 and the first SS with the first RCID shall use the pilot pattern A for single antenna MS or the pilot pattern A/B for dual antenna MS in 8.4.8.1.5 and the first UIUC, whereas the second MS with the second RCID shall use the pilot pattern B for single antenna MS or the pilot pattern C/D for dual antenna MS and the second UIUC.

Table 302q -- MIMO UL IR HARQ Sub-Burst IE Format

<u>MIMO UL IR HARQ Sub-Burst IE</u> {			
<u>MU Indicator</u>	<u>1 bit</u>		<u>Indicates whether this UL burst is intended for multiple SS</u>
<u>Dedicated MIMO UL Control Indicator</u>	<u>1 bit</u>		
<u>ACK Disable</u>	<u>1 bit</u>		<u>When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.</u>
<u>if (MU indicator == 0) {</u>			
<u>RCID IE()</u>	<u>Variable</u>		
<u>If (Dedicated MIMO UL Control Indicator ==1) {</u>			
<u>Dedicated MIMO UL Control IE ()</u>	<u>variable</u>		
<u>}</u>			
<u>} else {</u>			
<u>Matrix</u>	<u>1 bit</u>		<u>Indicates transmission matrix (See 8.4.8) for MS with dual Tx antennas</u> <u>0 = Matrix A</u> <u>1 = Matrix B</u> <u>Ignored by MS with single Tx antenna</u>
<u>}</u>			
<u>Nsch</u>	<u>4 bits</u>		
<u>If (ACK Disable ==0) {</u>			
<u>SPID</u>	<u>2 bits</u>		
<u>ACID</u>	<u>4 bits</u>		
<u>AI_SN</u>	<u>1 bit</u>		
<u>}</u>			
<u>For (i=0;i<N_layer;i++) {</u>			
<u>if (MU indicator == 1) {</u>			
<u>RCID IE()</u>	<u>Variable</u>		
<u>}</u>			
<u>Nep</u>	<u>4 bits</u>		
<u>}</u>			
<u>}</u>			

Table 302r -- MIMO UL IR HARQ for CC Sub-Burst IE Format

<u>MIMO UL IR HARQ for CC Sub-Burst IE</u> {			
<u>MU Indicator</u>	<u>1 bit</u>		<u>Indicates whether this UL burst is intended for multiple SS</u>
<u>Dedicated MIMO UL Control Indicator</u>	<u>1 bit</u>		
<u>ACK Disable</u>	<u>1 bit</u>		<u>When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.</u>
<u>if (MU indicator == 0) {</u>			
<u>RCID IE()</u>	<u>Variable</u>		
<u>If (Dedicated MIMO UL Control Indicator ==1) {</u>			
<u>Dedicated MIMO UL Control IE ()</u>	<u>variable</u>		
<u>}</u>			
<u>} else {</u>			
<u>Matrix</u>	<u>1 bit</u>		<u>Indicates transmission matrix (See 8.4.8) for MS with dual Tx antennas</u>

		0 = Matrix A 1 = Matrix B Ignored by MS with single Tx antenna
}		
<u>Duration</u>	10 bits	
<u>For (i=0;i<N_layer;i++) {</u>		
<u>if (MU indicator == 1) {</u>		
<u>RCID IE()</u>	Variable	
}		
<u>UIUC</u>	4 bits	
<u>Repetition Coding Indication</u>	2 bits	0b00 – No repetition coding 0b01 – Repetition coding of 2 used 0b10 – Repetition coding of 4 used 0b11 – Repetition coding of 6 used
<u>If (ACK Disable ==0) {</u>		
<u>ACID</u>	4 bits	
<u>AI_SN</u>	1 bit	
<u>SPID</u>	2 bit	
}		
}		
}		

Table 302s -- MIMO UL STC HARQ Sub-Burst IE Format

MIMO UL STC HARQ Sub-Burst IE{		
<u>Tx count</u>	2 bits	00: initial transmission 01: odd retransmission 10: even retransmission 11: reserved
<u>Duration</u>	10 bits	
<u>ACK Disable</u>	1 bit	When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.
<u>Dedicated MIMO DL Control Indicator</u>	1 bit	
<u>if (Tx count ==0) {</u>		
<u>if (MU indicator == 0) {</u>		
<u>RCID IE()</u>	Variable	
<u>If (Dedicated MIMO UL Control Indicator ==1) {</u>		
<u>Dedicated MIMO UL Control IE ()</u>	variable	
}		
} else {		
<u>Matrix</u>	1 bit	Indicates transmission matrix (See 8.4.8) for MS with dual Tx antennas 0 = Matrix A 1 = Matrix B Ignored by MS with single Tx antenna
}		
<u>For (i=0;i<N_layer;i++) {</u>		
<u>If (MU indicator == 1) {</u>		

<u>RCID IE()</u>	<u>Variable</u>	
<u>}</u>		
<u>UIUC</u>	<u>4 bits</u>	
<u>Repetition Coding Indication</u>	<u>2 bits</u>	<u>0b00 – No repetition coding</u> <u>0b01 – Repetition coding of 2 used</u> <u>0b10 – Repetition coding of 4 used</u> <u>0b11 – Repetition coding of 6 used</u>
<u>}</u>		
<u>If (ACK Disable ==0) {</u>		
<u>ACID</u>	<u>4 bits</u>	
<u>}</u>		
<u>}</u>		
<u>}</u>		

----- End of Text Change -----

[Add the following text after line 59 on page 372]

----- Start of Text Change -----

8.4.5.4.24.2 Dedicated MIMO UL Control IE Format

Dedicated UL Control IE for MIMO contains additional control information for each sub bursts.

Table 302t -- Dedicated MIMO UL Control IE Format

<u>Syntax</u>	<u>size</u>	<u>Note</u>
<u>Dedicated MIMO UL Control IE() {</u>	<u>-</u>	<u>-</u>
<u>Matrix</u>	<u>2 bits</u>	<u>Indicates transmission matrix (See 8.4.8)</u> <u>00 = Matrix A (Transmit Diversity)</u> <u>01 = Matrix B (Spatial Multiplexing)</u> <u>10-11 = Reserved</u>
<u>N_layer</u>	<u>2 bits</u>	<u>Number of coding/modulation layers</u> <u>00 = 1 layer</u> <u>01 = 2 layers</u> <u>10-11 = Reserved</u>
<u>}</u>		

----- End of Text Change -----

[Modify Table 302a in page 353, section 8.4.5.4.15 as following]

----- Start of Text Change -----

Table 302a. CQICH Enhanced allocation IE format

Syntax	Size (bits)	Notes
CQICH_Enhanced_Alloc_IE() {		

Extended UIUC <u>2</u>	4	0x0 <u>90</u>
Length	<u>48</u>	Length in bytes of following fields
CQICH_ID	variable	Index to uniquely identify the CQICH resource assigned to the MSS
Period (=p)	<u>3</u>	A CQI feedback is transmitted on the CQICH every 2^p frames
Frame offset	3	The MSS starts reporting at the frame of which the number has the same 3 LSB as the specified frame offset. If the current frame is specified, the MSS should start reporting in 8 frames
Duration (=d)	3	A CQI feedback is transmitted on the CQI channels indexed by the CQICH_ID for 10×2^d frames. If $d=0$, the CQICH is de-allocated. If $d=111$, the MSS should report until the BS command for the MSS to stop.
CQICH_Num	4	Number of CQICHs assigned to this CQICH_ID is (CQICH_Num +1)
for (i=0;i<CQICH_Num+ <u>1</u> ;i++) {		
Feedback_type	<u>3</u>	0b000 = Fast DL measurement/Default Feedback with antenna grouping 0b001 = Fast DL measurement/Default Feedback with antenna selection 0b010 = Fast DL measurement/Default Feedback with reduced code book 0b011 = Quantized precoding weight feedback 0b100 = Index to precoding matrix in code book 0b101 = Channel Matrix Information 0b1 <u>010</u> = Per stream power control 0b110 —0b111 = Reserved
Allocation index	6	Index to the fast feedback channel region marked by UIUC=0
CQICH Type	3	0b <u>000</u> = 6-bit CQI, 0b <u>001</u> = DIUC-CQI, 0b <u>010</u> = 3-bit CQI (even), 0b <u>011</u> = 3-bit CQI(odd) 0b100 = 6 bit CQI (primary) 0b101 = 4 bit CQI (secondary) 0b110-0b111 = reserved A DIUC-CQI is a CQI channel that uses a modulation and coding level derived from the DIUC.
STTD indication	1	When CQICH type=000, 0 = reserved 1 = use STTD in PUSC only (see Figure 249)
}		
Band_AMC_Precoding_Mode	1	0 = One common precoder for all bands. 1 = Distinct precoders for the bands with the highest S/N values, up to the number of short term precoders fed back as specified by Nr_Precoders_feedback
If (Band_AMC_Precoding_Mode =1) { Nr_Precoders_feedback (=N) }	3	Nr of precoders feedback = N.
Padding	variable	The padding bits are used to ensure the IE size is integer number of bytes.
}		

----- **End of Text Change** -----

References

- [1] IEEE P802.16e/D7 Air Interface for Fixed and Mobile Broadband Wireless Access Systems – Amendment for Physical and Medium Access Control Layers for Combined Fixed and Mobile Operation in Licensed Bands
- [2] IEEE C802.16e-05/038r1 “Normal MAP Extension for MIMO H-ARQ”, accepted at 35th 802.16 Meeting in Jan. 2005