

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178A SC 178A.1.9.3 P830 L37 # 1

Shakiba, Hossein

Huawei Technologies Canada

Comment Type TR Comment Status R (bucket) (E)

Based on this paragraph, calculation of the noise PDF starts with a Dirac delta function and moves on to include the non-Gaussian crosstalk and dual-Dirac jitter noises in the following two paragraphs. Then, the third following paragraph adds the remaining Gaussian noise terms. However, this process of calculating noise PDF misses the ISI noise.

#### SuggestedRemedy

Add a description to include the ISI noise PDF and its calculation using reference to the procedure defined in 93A.1.7.3. This can be done by either adding another convolution step or starting with ISI noise PDF instead of a Dirac delta function.

Response Response Status W

REJECT.

The draft is correct as written.

The preceding paragraph states that "DELTA is defined in 178A.1.7.6 with the exception that the Gaussian approximation of the probability density function of the noise amplitude  $p_{ga}(y)$  is replaced with the probability density function of the noise amplitude  $p_n(y)$  defined below." The definition of DELTA in 178A.1.7.6 is based on the convolution of the probability distribution function of the noiseless signal amplitude prior to quantization  $p_s(n)$  and the Gaussian approximation of the probability density function of the noise amplitude prior to quantization  $p_{ga}(y)$ . Substitution of  $p_n(y)$  for  $p_{ga}(y)$  means that  $p_n(y)$  will be convolved with  $p_s(y)$  to generate the probability distribution function for signal and noise amplitude prior to quantization  $p_{sn}(y)$  that is used to determine the quantization step DELTA. Since  $p_s(y)$  is defined in 178A.1.7.6 to include the signal and inter-symbol interference, all of the appropriate terms are being included.

CI 176D SC 176D.6.4 P790 L47 # 3

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (E)

Editor's note expire's after Draft 2.1.

#### SuggestedRemedy

Delete editor's note.

Response Response Status C

ACCEPT.

CI 176D SC 176D.6.4 P791 L39 # 4

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (E)

Editor's note expire's after Draft 2.1.

#### SuggestedRemedy

Delete editor's note.

Response Response Status C

ACCEPT.

CI 176D SC 176D.6.5 P792 L5 # 5

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (E)

Editor's note expire's after Draft 2.1.

#### SuggestedRemedy

Delete editor's note.

Response Response Status C

ACCEPT.

CI 175 SC 175.7 P295 L3 # 6

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (L)

Editor's note expire's after Draft 2.1.

#### SuggestedRemedy

Delete editor's note.

Response Response Status C

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 175 SC 175.9.4.4 P300 L31 # 7

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) (CG)

The management PICS do not align well with the specifications. The management variables are defined at the end of the clause. The subclause specifies management variables, not management objects. It specifies an "alternate" not "equivalent" mechanism if MDIO is not implemented. The "alternate" method is mandatory, not optional, if MDIO is not implemented.

#### SuggestedRemedy

Move 179.9.4.4 "Management", to the end of 179.9.4.

In M1, change feature to "Alternate access to PCS management variables is provided" and change status to "MD:M".

For Clause 176 through Clause 187, Annex 176C, and Annex 176D, align the PICS with the updated 179.9.4.4 and including \*MD in the "Major capabilities/options" subclause.

Response Response Status C

ACCEPT IN PRINCIPLE.

Note that the suggested remedy refers to 179.9.4.4 and 179.9.4, but those references should be to 175.9.4.4 and 175.9.4.

Implement the suggested remedy with editorial license and with consideration of the resolution of comment #376 which suggests removing most of the PICS content.

[Editor's note: CC 176, 177, 178, 179, 180, 181, 182, 183, 184, 185, 186, 187, 176C, 176D]

CI 175 SC 175.9.4.2 P299 L11 # 8

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) (L)

The PCS lane number is captured to a management variable, which would then be mapped to MDIO or alternate register as defined in 175.8.

#### SuggestedRemedy

For RF2, change the Feature to "PCS lane number is captured to a management variable" and in the Status column change "MD:M" to "M".

Response Response Status C

ACCEPT.

CI 178B SC 178B.3 P836 L14 # 10

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The span labelled "Physical Layer implementation" is intended to convey simply that this portion of the diagram is representative of the entire Physical Layer not an implementation; otherwise PHY and xMII Extender should be labelled as implementations as well.

#### SuggestedRemedy

Change "Physical Layer implementation" to "Physical Layer".

Response Response Status C

ACCEPT.

CI 178B SC 178B.4 P836 L42 # 11

Brown, Matt

Alphawave Semi

Comment Type E Comment Status R Interfaces (CI)

Nomenclature is inconsistent. This is the only part of this Annex that uses "AUI-C2C" and "AUI-C2M". 178B.3 defines xAUI-n; this should be used instead. The references to Annex 176C and Annex 176D are limiting assuming future AUI also use Annex 178B; so these should be examples of references.

#### SuggestedRemedy

Change (twice in this paragraph) "AUI-C2M (Annex 176D)" to "xAUI-n C2M (e.g., see Annex 176D)".

Change (twice in this paragraph) "AUI-C2C (Annex 176C)" to "xAUI-n C2C (e.g., see Annex 176C)".

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.4 P836 L48 # 12

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

It sounds like you have both a per-interface function and one per-lane function on each lane. Clarify text.

**SuggestedRemedy**

Change "is composed of one per-interface function and one per-lane function for each lane associated with the interface"

Change "is composed of one per-interface function for the entire interface and one per-lane function for each lane associated with the interface"

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement suggested remedy with editorial license.

CI 178B SC 178B.4 P837 L19 # 13

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

In Figure 178B-2, it would be helpful to point out that the DLi and SLi are attaching to the medium or AUI channel.

**SuggestedRemedy**

Add a label to the right "Medium or AUI Channel"

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement suggested remedy with editorial license.

CI 178B SC 178B.5 P837 L47 # 14

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

local\_rts, remote\_rts, and remote\_rx\_ready are defined as Boolean variable thus should be given values true and false, not 0 and 1.

**SuggestedRemedy**

Change "1" to "true" on ...

page 837 line 47

page 838 lines 7, 13, 16, 18

Change "0" to "false" on ...

page 838 line 16

Apply similarly elsewhere as necessary.

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement suggested remedy with editorial license.

CI 178B SC 178B.5.1.1 P838 L26 # 16

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

Training frames are always based on a local clock regardless of the other interface state.

**SuggestedRemedy**

Delete "In this case".

Response Response Status C

ACCEPT.

CI 178B SC 178B.5.1.1 P838 L28 # 17

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

It would be good to be clear about where the recovered clock is coming from.

**SuggestedRemedy**

Change "recovered clock" to "recovered clock from the receiver on the other interface" or similar.

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement suggested remedy with editorial license.

CI 178B SC 178B.5.1.1 P838 L32 # 18

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

Misused comma.

**SuggestedRemedy**

Delete comma between "PCS clock and such".

Response Response Status C

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.5.2.2 P841 L1 # 20

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

The sentence "Each interface using ILT shall identify which format is relevant for it." does not make sense. How is an interface to identify a preferred format. Perhaps that clause or annex that specifies the interface should identify the format, given that is the case.

#### SuggestedRemedy

Change sentence to "The training frame format is specified by the clause specifying the AUI component or PMD."

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement the suggested remedy with editorial license.

CI 178B SC 178B.5.2.3 P841 L17 # 21

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

The setting to one value or another is mandatory, not just permitted.

#### SuggestedRemedy

Change "precoding may be enabled or disabled" to "precoding is either enabled or disabled".

Response Response Status C

ACCEPT.

CI 178B SC 178B.5.2.3 P841 L28 # 22

Brown, Matt Alphawave Semi

Comment Type E Comment Status R (bucket) (CI)

In Figure 178B-5, what does the box "x3" do?

#### SuggestedRemedy

Provide description of the "x3" block.

Response Response Status C

REJECT.  
This function is described in 178B.5.2.4 second paragraph.

CI 178B SC 178B.5.3 P845 L26 # 23

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The Figure title should like be a level 4 Annex subclause heading, 178B.5.3.1.

#### SuggestedRemedy

Change heading paragraph appropriately.

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

CI 178B SC 178B.5 P849 L28 # 24

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

Paragraph begins with an incomplete sentence/thought. The same is conveyed more clearly in the first sentence of 178B.5.7 "Equalization control is only available for the E1 format."

#### SuggestedRemedy

Change "Only applies for E1 format" to "The initial condition request only applies for the E1 format."

Make similar updates in 178B.5.3.4, 178B.5.3.5, 178B.5.4.5, 178B.5.4.7, 178B.5.4.8.  
Align text in 178B.5.7.

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

CI 178B SC 178B.5.3.5 P846 L4 # 25

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

This paragraph defines how a coefficient not just give permission to do so.

#### SuggestedRemedy

Change "may be changed" to "is changed".

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

CI 178B SC 178B.5.4 P846 L53 # 26

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

In Table 178B-4 footnote a three values are described as being undefined. Why are they not just listed along with the others and mark as either "undefined" or "reserved" as is done for other fields.

#### SuggestedRemedy

For coefficient select echo add values "010, 011, and 100 and indicate they are "= reserved" or "= undefined".

Response Response Status C

ACCEPT IN PRINCIPLE.

For coefficient select echo add values "010, 011, and 100 and indicate they are "= undefined". Remove footnote "a".

CI 178B SC 178B.5.4.2 P847 L39 # 27

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The variable local\_tp\_mode is used in state diagram in Figure 178B-10 so should be defined in 178B.7.3.1

#### SuggestedRemedy

Move definition to 178B.7.3.1.

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #475.

CI 178B SC 178B.5.4.3 P847 L39 # 28

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The variable local\_mc\_mode is used in state diagram in Figure 178B-10 so should be defined in 178B.7.3.1

#### SuggestedRemedy

Move definition to 178B.7.3.1.

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #475.

CI 178B SC 178B.5.4.2 P847 L43 # 29

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

This variable is set by state diagram which take precedence. It would be helpful to state explicit that the action is handled by the state diagram as is done for training\_failure.

#### SuggestedRemedy

For the definitions for local\_tp\_mode, local\_mc\_mode, tx\_disable, tx\_mode, lane\_training\_status, training, and training\_failure add the following sentence "The value of <variable name>

is set by the state diagram in Figure 178B-10."

For the definitions for tf\_offset, local\_tf\_lock, new\_marker, and slip\_done add the following sentence "The value of <variable name>

is set by the state diagram in Figure 178B-11."

For the definitions for coef\_sts, ic\_req, ic\_sts, and k add the following sentence "The value of <variable name> is set by the state diagram in Figure 178B-12."

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement suggested remedy for: local\_tp\_mode, local\_mc\_mode, lane\_training\_status and training.

The definitions of tx\_disable, tx\_mode and training\_failure already include the proposed reference to the state diagram.

Implement suggested remedy for: tf\_offset, local\_tf\_lock and new\_marker.

The definition of slip\_done already includes the proposed reference to the state diagram.

Implement suggested remedy for: ic\_req, ic\_sts, and k

The definition of coef\_sts already includes the proposed reference to the state diagram.

Implement with editorial license.

CI 178B SC 178B.5.4.2 P847 L38 # 30

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

The sentence is rather ambiguous; not clear if the variable reflect the state of the status bits or vice versa. Since local\_tp\_mode is set by the state machine it seems the status bits are set based on local\_tp\_mode.

#### SuggestedRemedy

Change "The training pattern status bits encode the value of local\_tp\_mode." to "The training status bits are encoded to convey the value of local\_tp\_mode."

Update 178B.5.4.3 similarly.

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement suggested remedy with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.5.4.2 P847 L42 # 31

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

It is required not just permitted to set the variable to one of the listed values.

#### SuggestedRemedy

Change "may be assigned" to "is assigned".  
Update 178B.5.4.3 similarly.

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

CI 178B SC 178B.5.4.4 P848 L4 # 32

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

Typically, lock is defined by identifying the mark position not the infinite set of equally spaced positions. Is there some special meaning to this?

#### SuggestedRemedy

Change "positions" to "position".

Response Response Status C

ACCEPT IN PRINCIPLE.  
Change: "When the receiver frame lock bit is set to 1, the receiver is indicating that it has identified training frame marker positions"  
To: "The receiver frame lock bit is set to 1 when the receiver has identified the training frame marker position"  
Implement with editorial license.

CI 178B SC 178B.5.4.4 P848 L4 # 33

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The first sentence describes the bit as a status bit to be read while the second sentence describes it as a status bit to be a set to one value or another. The second sentence is correct.

#### SuggestedRemedy

Change "When the receiver frame lock bit is set to 1, the receiver is indicating that it has identified"  
To "The receiver frame lock bit is set to 1 when the receiver has identified"

Response Response Status C

ACCEPT IN PRINCIPLE.  
Resolve using the response to comment #32.

CI 178B SC 178B.5.5 P848 L37 # 34

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

Training frame lock is not achieved by "looking" but rather by "detecting".

#### SuggestedRemedy

Change "by looking for the frame marker or the inverted frame marker in" to "by detecting either the frame marker or the inverted frame marker in".

Response Response Status C

ACCEPT.

CI 178B SC 178B.5.7.4 P851 L19 # 35

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The defining for variable ck\_stp could be improved. The description implies that the variable is something that can be set or queried. But rather the variable is representative of the step size used by the implementation but is nevertheless within the specified bounds.

#### SuggestedRemedy

Change the definition to "Variable that represents the magnitude of the change in c(k) for one step up or one step down from its current value. The value is implementation dependent but within the range specified by the clause or annex that defines the PMD or AUI component.

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

CI 178B SC 178B.5.7.4 P851 L22 # 36

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The set of indices are not defined by the AUI component or PMD but rather by the clause or annex that specifies them.

#### SuggestedRemedy

Change "defined by" to "specified for".

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.5.9 P851 L44 # 37

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

Although the changes are permitted to occur during this time span they are to not occur outside of this time span.

#### SuggestedRemedy

Change "training pattern may occur at" to "training pattern occurs at" or "training pattern shall occur at".

Response Response Status C

ACCEPT IN PRINCIPLE.  
Change: "training pattern may occur at any"  
To: "training pattern occurs at any"  
Implement with editorial license.

CI 178B SC 178B.6 P852 L27 # 38

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

The word "can" is deprecated in the sense of giving permission. It is not clear if this is giving permission or stating the possibility of occurrence.

#### SuggestedRemedy

Assuming the intent is to give permission, change the sentence to "The path may include ISLs that do not use a training protocol."

Response Response Status C

ACCEPT IN PRINCIPLE.  
Change: "The path can include ISLs that do not use a training protocol."  
To: "The path may include ISLs that do not use a training protocol."  
Also change: "that can include AUI components and PMDs" in the previous sentence to: "that may include AUI components and PMDs"  
Implement with editorial license.

CI 178B SC 178B.6 P852 L37 # 39

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

What is meant by "a remote AUI component or PMD"? Is this the peer interface as defined for this annex?

#### SuggestedRemedy

Change "a remote AUI component or PMD" to "the peer interface".

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

CI 178B SC 178B.6 P852 L51 # 40

Brown, Matt Alphawave Semi

Comment Type TR Comment Status A (bucket) (CI)

Behaviors defined in the second bullet are loosely defined as being included in the ILT umbrella, not outside. Each of the descriptions should have a qualifier as to when they apply, not delegate that to an informational note; language from 178B.5.1 can be leveraged. These bullets are not methods but rather they are means. Finally, the second bullet is insufficiently defined; should it not also include the sending of local pattern?

#### SuggestedRemedy

Change the opening sentence and two dashed bullets to the following:  
Ready to send (RTS) propagates over ISLs using one of the following means:  
-- If training is enabled, the continue training bit in the control field of the training frames (see 178B.5.3.1)  
-- If training is disabled or not supported, the transmit disable function to send and signal detect function to detect

Response Response Status W

ACCEPT IN PRINCIPLE.  
Implement the suggested change with editorial license.

CI 178B SC 178B.7.2.1 P853 L53 # 42

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

Use of word may with means "is permitted to". Describing a possible occurrence here not giving permission to "not work".

#### SuggestedRemedy

Change "may" to "might".

Response Response Status C

ACCEPT.

CI 178B SC 178B.7.2.1 P854 L12 # 44

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

The variable is required, not just permitted, to be set to one these values.

#### SuggestedRemedy

Change "This variable may be assigned one of the following values:"  
To "This variable may is assigned one of the following values:"

Response Response Status C

ACCEPT IN PRINCIPLE.  
Change: "This variable may be assigned one of the following values"  
To: "This variable is assigned one of the following values"

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.7.2.1 P854 L23 # 46

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

It would be helpful to direct the reader to some background on the use of recovered clock.

#### SuggestedRemedy

Change "a clock recovered by another interface"

To "a clock recovered by another interface (see 178B.5.1.1)"

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement the suggested change with editorial license.

CI 178B SC 178B.7.2.4 P855 L18 # 47

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

The inclusion of adjacent\_remote\_rts in the transition is redundant or unnecessary since if it is false then the state would transition to the "START" state.

#### SuggestedRemedy

In the transition from "WAIT\_ADJACENT" to "SWITCH\_CLOCK" delete "\*\* adjacent\_remote\_rts"

Response Response Status C

ACCEPT.

CI 178B SC 178B.7.3 P856 L8 # 48

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

Use of word may with means "is permitted to". In this case, assignment to one of these is mandatory.

#### SuggestedRemedy

Change "may be" to "is".

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement the suggested change with editorial license.

CI 178B SC 178B.7.3 P856 L19 # 49

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

Use of word may with means "is permitted to". In this case, assignment to one of these is mandatory.

#### SuggestedRemedy

Change "may be" to "is assigned".

Update the definitions for coef\_sts, ic\_req, ic\_sel, ic\_sts, lane\_training\_status, remote\_tp\_mode, similarly.

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement suggested remedy with editorial license..

CI 178B SC 178B.7.3 P856 L5 # 50

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The definition of remote\_mc\_mode is not introduced. It is also only used here and could be replaced with a reference to the received status.

#### SuggestedRemedy

Add the following to the end of the paragraph: "The variable remote\_mc\_mode is defined as follows:"

Also, consider deleting this variable and instead of pointing to the state of the received status "Modulation and precoding status" field.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change: "is entered with remote\_mc\_mode set to "PAM4 with precoding""

To: "is entered with the modulation and coding status of the status field of the received training frames set to "PAM4 with precoding""

Delete the remote\_mc\_mode variable and its definition. Remove the remote\_mc\_mode row from Table 178B-7.

Implement with editorial license.

CI 178B SC 178B.3 P856 L12 # 51

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

Add cross-reference to state diagram figure.

#### SuggestedRemedy

After "state diagram" insert "(see Figure 178B-12)"

Response Response Status C

ACCEPT.



## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.7.3.1 P857 L38 # 52

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CI)

The variable remote\_tp\_mode is never used by or set by any state diagram and is never referenced elsewhere.

*SuggestedRemedy*

Delete the entry for remote\_tp\_mode.

Response Response Status C

ACCEPT.

CI 178B SC 178B.7.3.5 P860 L45 # 53

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) (CI)

In Figure 178B-10 operator symbol "#" is used but likely it was intended to be no-equal-to symbol.

*SuggestedRemedy*

Change "#" to not-equal-to symbol.

Response Response Status C

ACCEPT.

CI 1 SC 1.4.24aa P55 L # 54

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CG)

1.4.24aa is not the correct subclause number. Instead it should be immediately before 1.4.101a "200GBASE-CR2" as inserted by IEEE Std 802.3ck-2022.

*SuggestedRemedy*

Change the subclause number per comment with editorial license.

Response Response Status C

ACCEPT.

CI 174A SC 174A.8.7 P722 L3 # 55

Brown, Matt

Alphawave Semi

Comment Type E Comment Status A (bucket) (CG)

"AUI component" is a new term introduced in 802.3dj.

*SuggestedRemedy*

Add a nomenclature subclause in Annex 174A and provide a definition for AUI component using the definition from 178B.3. Implement with editorial license.

Response Response Status C

ACCEPT.

CI 178 SC 178.1 P367 L15 # 58

Brown, Matt

Alphawave Semi

Comment Type TR Comment Status A (bucket) (E)

The word "device" has two meaning in Clause 178. On Page 367 line 15 "device" is packaged part (e.g., die plus the package). On the other hand, on page 373 line 41 the device is something that sits on the package (e.g., die) and the package is separate from the device. The term "device" in the latter context is well embedded so the former context should be given a different term. Subclause 179.11.7.1 uses the term "packaged device".

*SuggestedRemedy*

When referring to a packaged part, use the term "packaged device". Another unique term would be acceptable.

Update 179, 176C, 176D similarly, as necessary.

Response Response Status W

ACCEPT IN PRINCIPLE.

In 178.1, change "Devices conform to" to "PMD transmitters and PMD receivers conform to".

Change "between two devices" to "between two PMDs" and similarly in the rest of the sentence.

Elsewhere, change "device" to "PMD" when it refers to a PMD rather than the die inside the package.

Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 175 SC 175.8 P295 L17 # 59

Brown, Matt

Alphawave Semi

Comment Type T Comment Status R (withdrawn)

The MDIO interface and register addressing is obsolete. In devices of this complexity that structure does not suffice and proprietary register maps and APIs are provided. For new clauses in 802.3dj the various management variables are defined within the clause and listed in management variable tables. References to optional MDIO registers and references in Clause 45 are provided.

#### SuggestedRemedy

Delete all references to register mappings and descriptions in Clause 45 and, where necessary, include necessary heuristics in the clause that uses the management variables. Alternately, define a new management variable clause that defines the variable heuristics, e.g., number of bits, R/W, clear-on-read, without specific addressing or assumed register sizes (i.e., define by name, not address). Applies to clauses 45, 178 through 183, and annexes 176C and 176D.

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 178B SC 178B.7.3 P855 L51 # 60

Brown, Matt

Alphawave Semi

Comment Type TR Comment Status A (bucket) (CI)

For PMD types defined in Clause 182 and Clause 183, the adjacent sublayer that provides or reverses precoding is the Inner FEC defined in Clause 177 rather than a PMA as defined in Clause 176.

#### SuggestedRemedy

Change "the AUI component or PMD shall cause the adjacent PMA to transmit all subsequent data on the corresponding lane with precoding (see 176.7.1.2) and otherwise cause the adjacent PMA to transmit all subsequent data on the corresponding lane without precoding."

To: "the AUI component or PMD shall cause the adjacent PMA or Inner FEC to transmit all subsequent data on the corresponding lane with precoding (see 176.7.1.2) and otherwise cause the adjacent PMA or Inner FEC to transmit all subsequent data on the corresponding lane without precoding."

Change: "the AUI component or PMD shall inform the adjacent PMA that all subsequently received data on the corresponding lane includes precoding (see 176.7.1.2) and otherwise inform the adjacent PMA that all subsequently received data on the corresponding lane does not include precoding."

To: "the AUI component or PMD shall inform the adjacent PMA or Inner FEC that all subsequently received data on the corresponding lane includes precoding (see 176.7.1.2) and otherwise inform the adjacent PMA or Inner FEC that all subsequently received data on the corresponding lane does not include precoding."

Response Response Status W

ACCEPT IN PRINCIPLE.

Change: "the AUI component or PMD shall cause the adjacent PMA to transmit all subsequent data on the corresponding lane with precoding (see 176.7.1.2) and otherwise cause the adjacent PMA to transmit all subsequent data on the corresponding lane without precoding."

To: "the AUI component or PMD shall cause the PMA or Inner FEC to transmit all subsequent data on the corresponding lane with precoding (see 176.7.1.2) and otherwise cause the PMA or Inner FEC to transmit all subsequent data on the corresponding lane without precoding."

Change: "the AUI component or PMD shall inform the adjacent PMA that all subsequently received data on the corresponding lane includes precoding (see 176.7.1.2) and otherwise inform the adjacent PMA that all subsequently received data on the corresponding lane does not include precoding."

To: "the AUI component or PMD shall inform the PMA or Inner FEC that all subsequently received data on the corresponding lane includes precoding (see 176.7.1.2) and otherwise inform the PMA or Inner FEC that all subsequently received data on the corresponding lane does not include precoding."

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 00 SC 0 P0 L0 # 63

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) PICS (CG)

The PICS subclauses may not be in alignment with the specification in each clause. Grant editorial license to update as needed.

#### SuggestedRemedy

With editorial license, update the PICS subclause in each clause/annex as necessary to align with specifications within the clause/annex.

Response Response Status C

ACCEPT IN PRINCIPLE.

Note that comment #376 proposes to reduce the content in the PICS subclauses.

For any clauses with a PICS subclause, implement the suggested remedy with consideration of the adopted response to comment #376 with editorial license.

[Editor's note: CC: many clauses]

CI 176 SC 176.12 P337 L3 # 64

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A (bucket) PICS (L)

Per editor's note, the PICS is incomplete.

#### SuggestedRemedy

Complete the PICS with editorial license and delete editor's note.

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement the suggested remedy with consideration of the resolution to comment #376 which suggests removing most of the PICS content.

CI 00 SC 0 P8 L34 # 67

Lusted, Kent

Synopsys

Comment Type E Comment Status A (bucket) (CG)

Missing the list of members in the balloting committee

#### SuggestedRemedy

Add the list of members in the balloting committee

Response Response Status C

ACCEPT.

CI 1 SC 1.4 P59 L19 # 68

Lusted, Kent

Synopsys

Comment Type T Comment Status A (bucket) (CG)

In the base specification IEEE Std. 802.3-2022 page 204, the definition of "Channel Operating Margin (COM)" points to Clause 93A.1). There needs to be a reference to the COM in Annex 178A

#### SuggestedRemedy

Bring 1.4.237 Channel Operating Margin (COM): into the draft and add a reference to Annex 178A

Response Response Status C

ACCEPT.

CI 1 SC 1.5 P59 L50 # 69

Lusted, Kent

Synopsys

Comment Type T Comment Status A (bucket) (CG)

SCMR is used 12 times throughout the draft as an abbreviation for Signal to AC common-mode noise ratio. It is not listed in the abbreviations in CI 1.5

#### SuggestedRemedy

Add abbreviation for SCMR as follows:

SCMR Signal to AC common-mode noise ratio

Response Response Status C

ACCEPT.

CI 175 SC 175.2.5.5 P288 L32 # 71

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

Boolean variables are not "deasserted", they are set to "false".

#### SuggestedRemedy

Change: It is deasserted when rx\_am\_sf<1> is deasserted

To: It is set to false when rx\_am\_sf<1> is deasserted

Response Response Status C

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 175 SC 175.2.5.5 P288 L37 # 72

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

Boolean variables are not "deasserted", they are set to "false".

#### SuggestedRemedy

Change: It is deasserted when rx\_am\_sf<2> is deasserted

To: It is set to false when rx\_am\_sf<2> is deasserted

Response Response Status C

ACCEPT.

CI 175 SC 175.2.6.2.2 P290 L8 # 73

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

In 175.2.5.7, add to the end of the definition of amps\_lock<x>:

"The value of amps\_lock<x> is set by the alignment marker lock state diagram (see Figure 119-12)."

Implement with editorial license.

CI 175 SC 175.2.6.2.2 P290 L42 # 74

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Modify the definition of the reset variable by adding: ", and is false otherwise." to end of the last sentence.

Implement with editorial license.

CI 176 SC 176.4.4.2.1 P320 L54 # 75

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Update the definition of reset to keep it consistent with comments #74 - reset is a special case.

Modify the definition of the reset variable by adding: ", and is false otherwise." to end of the last sentence.

Implement with editorial license.

CI 176 SC 176.4.4.2.1 P321 L7 # 76

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Update the definition of the align\_status\_mux variable from:

"Boolean variable that is set to true when PCS lane synchronization is complete. It indicates that all\_locked\_mux is true and deskew is complete."

To:

"Boolean variable that indicates the alignment marker lock and deskew processes are complete. Its value is set by the PMA multiplex synchronization state diagram (see Figure 176-10)."

Implement with editorial license.

CI 176 SC 176.4.4.2.1 P321 L21 # 77

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Update the definition of the pcs\_lanes\_identified\_mux variable from:

"Boolean variable that is set to true if each input lane is locked to a unique alignment marker sequence identified using the alignment markers in Table 119–1 for 200GBASE-R, Table 119–2 for 400GBASE-R, Table 172–2 and Table 172–3 for 800GBASE-R, or Table 175–2 for 1.6TBASE-R PMAs."

To:

"Boolean variable that is set to true if each input PCS lane is locked to a unique alignment marker sequence identified using the alignment markers in Table 119–1 for 200GBASE-R, Table 119–2 for 400GBASE-R, Table 172–2 and Table 172–3 for 800GBASE-R, or Table 175–2 for 1.6TBASE-R PMAs. It is set to false upon entering the LOSS\_OF\_ALIGNMENT state in the PMA multiplex synchronization state diagram (see Figure 176-10)."

Implement with editorial license.

CI 176 SC 176.4.4.2.1 P321 L42 # 78

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of all\_locked\_demux from:

"Boolean variable that is set to true when pma\_locked\_demux<y> is true for all y. For y = 0 to (n-1)."

To:

"Boolean variable is set to true when pma\_locked\_demux<y> is true for all y, where y = 0 to (n-1), which indicates all PCS lanes within all PMA lanes have achieved alignment marker lock. Otherwise, this variable is set to false."

Implement with editorial license.

CI 176 SC 176.4.4.2.1 P321 L48 # 79

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of pcs\_lanes\_identified\_demux

From:

"Boolean variable that is set to true if all demultiplexed PCS lanes are locked to a unique alignment marker sequence identified using the alignment markers in Table 119–1 for 200GBASE-R, Table 119–2 for 400GBASE-R, Table 172–2 and Table 172–3 for 800GBASE-R, or Table 175–2 for 1.6TBASE-R PMAs."

To:

"Boolean variable that is set to true if all demultiplexed PCS lanes are locked to a unique alignment marker sequence identified using the alignment markers in Table 119–1 for 200GBASE-R, Table 119–2 for 400GBASE-R, Table 172–2 and Table 172–3 for 800GBASE-R, or Table 175–2 for 1.6TBASE-R PMAs. It is set to false upon entering the LOSS\_OF\_SYMBOL\_LOCK state in the PMA demultiplex symbol lock state diagram (see Figure 176-11)."

CI 176 SC 176.4.4.2.1 P321 L52 # 80

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of pma\_locked\_demux<y>

From:

"Boolean variable that is set to true when amps\_lock<x> is true, as defined in 119.2.6.2.2, for all PCSs within the single input lane in the demultiplexing direction. For y = 0 to (n-1)"

To:

"Boolean variable that is set to true when amps\_lock<x> is true, as defined in 119.2.6.2.2, for all PCSs within the single input PMA lane y in the demultiplexing direction, and is set to false otherwise. For y = 0 to (n-1)."

Implement with editorial license.

CI 176 SC 176.4.4.2.1 P322 L5 # 81

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

This variable definition actually explains how the restart\_lock variable in Fig. 119-12 gets replaced by the restart\_lock\_demux<y> variable for use in the CL 176 data flow. This is already explained in 176.4.3.2.3.

Remove restart\_lock from the state diagram variable definitions in 176.4.4.2.1.

Remove similar redundant definition of restart\_lock in the multiplexing direction in 176.4.4.2.1 and add a description of restart\_lock for the multiplexing direction in 176.4.2.2 similar to the description in 176.4.3.2.3.

Implement with editorial license.

CI 176 SC 176.4.4.2.1 P322 L10 # 82

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of restart\_lock\_demux<y>

From:

"Boolean variable that is set to true in the SYMBOL\_LOCK\_RESTART and SLIP\_CONTROL states to restart the alignment marker lock processes for the PCSLs within a single input lane in the demultiplexing direction. For y = 0 to (n-1)."

To:

"Boolean variable that is used to restart the alignment marker lock processes for the PCSLs within the single input lane y in the demultiplexing direction, where y = 0 to (n-1). Its value is set by the PMA demultiplex symbol lock state diagram (see Figure 176-11)."

Implement with editorial license.

CI 176 SC 176.4.4.2.1 P322 L17 # 83

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to true or false. There is just a description of the use.

#### SuggestedRemedy

Change: For y = 0 to (n-1).

To: It is set to true for y = 0 to (n-1). Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of symbol\_lock\_counter\_demux<y>

From:

"Boolean variable that indicates that the symbol\_lock\_counter\_demux<y> has reached its terminal count. For y = 0 to (n-1).",

To:

"Boolean variable that is set to true when the counter symbol\_lock\_counter\_demux<y> has reached its terminal count, and is set to false when starting the counter (see figure 176-11). For y = 0 to (n-1)."

Implement with editorial license.

CI 177 SC 177.7.2.1 P355 L9 # 84

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to true or false. There is just a description of the use.

#### SuggestedRemedy

Change: Boolean variable that indicates that fas\_cnt has reached its terminal count.

To: Boolean variable that is set to true when fas\_cnt has reached its terminal count.

Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of fas\_cnt\_done

From:

"Boolean variable that indicates that fas\_cnt has reached its terminal count."

To:

"Boolean variable that is set to true when the counter fas\_cnt has reached its terminal count and is set to false when starting the counter (see Figure 177-13)."

Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 177 SC 177.7.2.1 P355 L13 # 85

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change definition of fas\_lock

From:

"A Boolean variable that is set to true when the receiver has detected the location of the frame alignment sequence within the pad codewords."

To:

"A Boolean variable that indicates the receiver has detected the location of the frame alignment sequence within the pad codewords. Its value is set by the Inner FEC pad detection state diagram (see Figure 177-13)."

Implement with editorial license.

CI 177 SC 177.7.2.1 P355 L20 # 86

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Add to the end of definition of fas\_valid:

"Otherwise, this variable is set to false."

Implement with editorial license.

CI 177 SC 177.7.2.1 P355 L29 # 87

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Update the definition of reset to keep it consistent with comments #74 - reset is a special case.

Modify the definition of the reset variable by adding: ", and is false otherwise." to end of the last sentence.

Implement with editorial license.

CI 177 SC 177.7.2.1 P355 L33 # 88

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to true or false. There is just a description that says what processes set it.

#### SuggestedRemedy

Add a description of when it is set to true and when it is set to false. There isn't enough information in the spec to provide a suggestion.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of restart\_inner\_fec\_sync

From:

"A Boolean variable that is set by the Inner FEC synchronization process or the Inner FEC pad detection process."

To:

"A Boolean variable that is used to restart all eight self-synchronization processes as well as the pad detection process associated with an input lane in the receive direction. Its value can be set to true in either the Inner FEC self-synchronization state diagram (see Figure 177-12) or the Inner FEC pad detection state diagram (see Figure 177-13). Its value is set to false upon entering the FAS\_LOCK\_INIT state of the Inner FEC pad detection state diagram."

Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 177 SC 177.7.2.1 P355 L41 # 89

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of slip\_done

From:

"A Boolean variable that is set to true when the SLIP requested by the Inner FEC synchronization state diagram has been completed indicating that the next candidate 128-bit block position can be tested."

To:

"A Boolean variable that indicates the next candidate 128-bit block position can be tested by the Inner FEC self-synchronization process. It is set to true when the SLIP function completes and is set to false upon entering the GET\_BLOCK state of the Inner FEC self-synchronization state diagram (see Figure 177-12).  
Implement with editorial license.

CI 177 SC 177.7.2.1 P355 L45 # 90

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable sync\_cflow<x>

From:

"A Boolean variable that is set to true after the Inner FEC codeword boundary is found for an Inner FEC flow, where x = 0 to 7, and represents an Inner FEC flow ID before identifying the actual Inner FEC flow numbering."

To:

"A Boolean variable that indicates the Inner FEC codeword boundary is found for an Inner FEC flow, where x = 0 to 7, and x represents an Inner FEC flow ID before identifying the actual Inner FEC flow numbering. The value of sync\_flow<x> is set by the Inner FEC self-synchronization state diagram (see Figure 177-12).  
Implement with editorial license.

CI 184 SC 184.7.2.2 P584 L33 # 91

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of dsp\_lock<x>

From:

"A Boolean variable that is set to true when the receiver has detected the location of the PS for a given polarization symbol stream on the 800GBASE-LR1 PMD service interface, where x = 0:1."

To:

"A Boolean variable that indicates the receiver has detected the location of the PS for a given polarization symbol stream on the 800GBASE-LR1 PMD service interface, where x = 0 or 1. Its value is set by the DSP lock state diagram (see Figure 184-9).  
Implement with editorial license.

CI 184 SC 184.7.2.2 P584 L42 # 92

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Update the definition of reset to keep it consistent with comments #74 - reset is a special case.

Modify the definition of the reset variable by adding: ", and is false otherwise." to end of the last sentence.

Implement with editorial license.



CI 184 SC 184.7.2.2 P584 L47 # 93

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable restart\_lock

From:

"A Boolean variable that is set by the DSP frame lock process to reset the synchronization process on each polarization symbol stream. It is set to true when M PS symbols in a row fail to match (M\_BAD state) on a given polarization symbol stream."

To:

"A Boolean variable that is used to restart the synchronization process for both polarization symbol streams when M PS symbols in a row fail to match within either polarization symbol stream. Its value is set by the DSP lock state diagram (see Figure 184-9).

Implement with editorial license.

CI 184 SC 184.7.2.2 P584 L54 # 94

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to true or false. There is just a description of the use.

#### SuggestedRemedy

Change: Boolean variable that indicates that sym\_counter has reached its terminal count.

To: Boolean variable that is set to true when sym\_counter has reached its terminal count.

Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable sym\_counter\_done

From:

"A Boolean variable that indicates that sym\_counter has reached its terminal count."

To:

"A Boolean variable that is set to true when the counter sym\_counter has reached its terminal count. It is set to false when the counter is started (see figure 184-9).

Implement with editorial license.

CI 184 SC 184.7.2.2 P585 L3 # 95

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable sym\_slip\_done

From:

"A Boolean variable that is set to true when the SYM\_SLIP requested by the DSP frame lock state diagram has been completed indicating that the next candidate PS position is available for testing."

To:

"A Boolean variable that indicates the next candidate PS position is available for testing. Is it set to true when the SYM\_SLIP function completes and is set to false upon entering the GET\_SYMBOL state of the DSP lock state diagram (see Figure 184-9)."

Implement with editorial license.

CI 184 SC 184.7.2.2 P585 L7 # 96

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of sym\_valid

From:

"A Boolean variable that is set to true if the received symbol is a valid PS symbol according to the state of the pilot sequences generator (see 184.4.9) for the value of the current\_ps\_id variable."

To:

"A Boolean variable that is set to true if the received symbol is a valid PS symbol according to the state of the pilot sequences generator (see 184.4.9) for the value of the current\_ps\_id variable. Otherwise, this variable is set to false."

Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 186 SC 186.4.2.1 P648 L40 # 97

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

**Response** Response Status C

ACCEPT IN PRINCIPLE.

The intent is that this variable is set to false when the next state is entered (in this case, RAML\_CNT\_0 or RAML\_CNT\_INC), but the assignment to false is missing.

Change the definition of the block\_rx variable

From:

"Boolean variable that is set to true when the next non-stuff 257b block is demapped by the GMP demapper function."

To:

"Boolean variable that is set to true when the next non-stuff 257b block is demapped by the GMP demapper function. It is set to false upon entering the RAML\_CNT\_0 or RAML\_CNT\_INC states in the 800GBASE-ER1 FEC sublayer alignment marker location state diagram (see Figure 186-21)."

Update figure 186-21 to assign the value false to variable block\_rx in states RAML\_CNT\_0 and RAML\_CNT\_INC.

Implement with editorial license.

CI 186 SC 186.4.2.1 P649 L11 # 98

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to true or false. There is just a description of the use.

**SuggestedRemedy**

Change: Boolean variable that indicates that amp\_counter has reached its terminal count.

To: Boolean variable that is set to true when amp\_counter has reached its terminal count. Otherwise, this variable is set to false.

**Response** Response Status C

ACCEPT IN PRINCIPLE.

In addition to not defining the true/false conditions, the text also refers to "amp\_counter" rather than "fam\_counter".

Change the definition of the variable fam\_counter\_done

From:

"A Boolean variable that indicates that amp\_counter has reached its terminal count."

To:

"A Boolean variable that is set to true when the counter fam\_counter has reached its terminal count. It is set to false when the counter is started (see figure 186-19). Implement with editorial license."

CI 186 SC 186.4.2.1 P649 L14 # 99

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to true or false. It just says it holds the output of the function FAM\_COMPARE.

**SuggestedRemedy**

Add a description of when it is set to true and when it is set to false. There isn't enough information in the spec to provide a suggestion.

**Response** Response Status C

ACCEPT IN PRINCIPLE.

The variable fam\_compare holds the result of the FAM\_COMPARE function. The definition of the function indicates what it returns, and there is no value in repeating that information in the definition of the variable. The specification methodology is consistent with clause 119 and 172. However, in 186.4.2.2, the FAM\_COMPARE function does not specify when it is set to false.

Add to the end of the definition of function FAM\_COMPARE in 186.4.2.2: ", otherwise it is set to false."

Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 186 SC 186.4.2.1 P649 L18 # 100

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable fam\_slip\_done

From:

"A Boolean variable that is set to true when the FAM\_SLIP requested by the FAM field lock state diagram has been completed and the next candidate 480-bit block position is available to be tested."

To:

"A Boolean variable that indicates the next candidate 480-bit block position is available to be tested. Is it set to true when the FAM\_SLIP function completes and is set to false upon entering the GET\_BLOCK state of the 800GBASE-ER1 FEC sublayer FAM field lock state diagram (see Figure 186-19)."

Implement with editorial license.

CI 186 SC 186.4.2.1 P649 L23 # 101

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement the suggested remedy to update the fam\_valid definition with editorial license.

CI 186 SC 186.4.2.1 P649 L28 # 102

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable fam\_lock<x>

From:

"A Boolean variable that is set to true when the receiver has detected the location of the FAM field among the stream of 257-bit blocks on an 800GBASE-ER1 FEC sublayer tributary FEC flow, where x = 0 to 7."

To:

"A Boolean variable that indicates the receiver has detected the location of the FAM field among the stream of 257-bit blocks on an 800GBASE-ER1 FEC sublayer tributary FEC flow, where x = 0 to 7. The value of fam\_lock<x> is set by the 800GBASE-ER1 FEC sublayer FAM field lock state diagram (see Figure 186-19)."

Implement with editorial license.

CI 186 SC 186.4.2.1 P649 L30 # 103

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to true or false. There is just a description of the use.

#### SuggestedRemedy

Change: Boolean variable that indicates that faw\_counter has reached its terminal count.

To: Boolean variable that is set to true when faw\_counter has reached its terminal count.

Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable faw\_counter\_done

From:

"A Boolean variable that indicates that faw\_counter has reached its terminal count."

To:

"A Boolean variable that is set to true when the counter faw\_counter has reached its terminal count. It is set to false when the counter is started (see figure 186-17).

Implement with editorial license.

[Editor's note: changed line from 11]

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 186 SC 186.4.2.1 P649 L14 # 104

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to true or false. It just says it holds the output of the function FAW\_COMPARE.

**SuggestedRemedy**

Add a description of when it is set to true and when it is set to false. There isn't enough information in the spec to provide a suggestion.

**Response** Response Status C

ACCEPT IN PRINCIPLE.

The variable faw\_match holds the result of the FAW\_COMPARE function. The definition of the function indicates what it returns, and there is no value in repeating that information in the definition of the variable. The specification methodology is consistent with clause 119 and 172. However, in 186.4.2.2, the FAW\_COMPARE function does not specify when it is set to false.

Add to the end of the definition of function FAW\_COMPARE in 186.4.2.2: ", otherwise it is set to false."

Implement with editorial license.

CI 186 SC 186.4.2.1 P649 L45 # 105

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

**Response** Response Status C

ACCEPT IN PRINCIPLE.

Implement the suggested remedy to update the faw\_valid definition with editorial license.

CI 186 SC 186.4.2.1 P649 L50 # 106

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

**Response** Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable faws\_lock<x>

From:

"A Boolean variable that is set to true when the receiver has detected the location of the FAW field for a given polarization symbol stream on the 800GBASE-ER1 PMD service interface, where x = 0:1."

To:

"A Boolean variable that indicates the receiver has detected the location of the FAW field for a given polarization symbol stream on the 800GBASE-ER1 PMD service interface, where x = 0 or 1. The value of faws\_lock<x> is set by the 800GBASE-ER1 PMA FAW field lock state diagram (see Figure 186-17)."

Implement with editorial license.

CI 186 SC 186.4.2.1 P650 L25 # 107

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

**Response** Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable mfas\_lock<x>

From:

"A Boolean variable that is set to true when the receiver has detected a valid MFAS sequence on an 800GBASE-ER1 FEC sublayer tributary FEC flow, where x = 0 to 7."

To:

"A Boolean variable that indicates the receiver has detected a valid MFAS sequence on an 800GBASE-ER1 FEC sublayer tributary FEC flow, where x = 0 to 7. The value of mfas\_lock<x> is set by the 800GBASE-ER1 FEC sublayer multi-frame alignment state diagram (see Figure 186-20)."

Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 186 SC 186.4.2.1 P650 L29 # 108

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement the suggested remedy to update the mfas\_valid definition with editorial license.

CI 186 SC 186.4.2.1 P650 L40 # 109

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable fec\_restart\_lock

From:

"A Boolean variable that is set by the FAM field lock process to reset the synchronization process. It is set to true when 5 consecutive FEC frame alignment mechanism patterns fail to match (5\_BAD state) on a given 800GBASE-ER1 tributary FEC flow."

To:

"Boolean variable that is used to restart the FAM field lock process when 5 consecutive FEC frame alignment patterns fail to match on a given tributary FEC flow. The value of fec\_restart\_lock is set by the 800GBASE-ER1 FEC sublayer FAM field lock state diagram (see Figure 186-19)."

Implement with editorial license.

CI 186 SC 186.4.2.1 P650 L45 # 110

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable fec\_mfas\_restart\_lock

From:

"A Boolean variable that is set by the MFAS field lock process to reset the synchronization process. It is set to true when 5 consecutive MFAS values do not match the expected value (5\_BAD state) on a given 800GBASE-ER1 FEC sublayer tributary FEC flow."

To:

"A Boolean variable that is used to restart the MFAS field lock process when 5 consecutive MFAS values do not match the expected value on a given FEC sublayer tributary FEC flow. The value of fec\_mfas\_restart\_lock is set by the 800GBASE-ER1 FEC sublayer multi-frame alignment state diagram (see Figure 186-20).

Implement with editorial license.

CI 186 SC 186.4.2.1 P651 L26 # 111

Wienckowski, Natalie

IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

#### SuggestedRemedy

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change the definition of the variable pma\_restart\_lock

From:

"A Boolean variable that is set by the FAW field lock process to reset the synchronization process on 800GBASE-ER1 PMA polarization symbol streams. It is set to true when 15 consecutive frame alignment word sequences to match (15\_BAD state) on a given 800GBASE-ER1 PMA polarization symbol stream."

To:

"A Boolean variable that is used to restart the FAW field lock process on both PMA polarization symbol streams when 15 consecutive frame alignment word sequences fail to match on either PMA polarization symbol stream. The value of pma\_restart\_lock is set by the 800GBASE-ER1 PMA FAW field lock state diagram (see Figure 186-17)."

Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 186 SC 186.4.2.1 P651 L37 # 112

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

**Response** Response Status C

ACCEPT IN PRINCIPLE.  
Change the definition of the variable raml\_align  
From:  
"Boolean variable that is set to true if the raml\_counter needs to be aligned to a new value"  
To:  
"Boolean variable that indicates when the 800GBASE-R PCS alignment markers insertion location needs to be aligned to the received AML overhead. The value of raml\_align is set by the 800GBASE-ER1 FEC sublayer alignment marker location state diagram (see Figure 186-21)."  
Implement with editorial license.

CI 186 SC 186.4.2.1 P651 L42 # 113

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status R (bucket) (L)

This Boolean variable is never set to true or false. There is just a description of the use.

**SuggestedRemedy**

Change: Boolean variable that indicates if the received information in the AML field is valid..  
To: Boolean variable that is set to true if the received information in the AML field is valid.  
Otherwise, this variable is set to false.

**Response** Response Status C

REJECT.  
The variable raml\_valid is set based on the results of the RAML\_CHECK function. The definition of that function indicates how the variable is set.

CI 186 SC 186.4.2.1 P651 L47 # 114

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

**Response** Response Status C

ACCEPT IN PRINCIPLE.  
Update the definition of reset\_fec to keep it consistent with comment #74 - reset is a special case.  
Modify the definition of the reset\_fec variable by adding: ", and is false otherwise." to end of the last sentence.  
Implement with editorial license.

CI 186 SC 186.4.2.1 P651 L50 # 115

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

**Response** Response Status C

ACCEPT IN PRINCIPLE.  
Update the definition of reset\_pma to keep it consistent with comment #74 - reset is a special case.  
Modify the definition of the reset\_pma variable by adding: ", and is false otherwise." to end of the last sentence.  
Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 186 SC 186.4.2.1 P652 L11 # 116

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

The rx\_local\_degraded variable is not used (or set) in any state diagram and therefore does not belong in the state machine variable definitions list.

Delete the variable definition of rx\_local\_degraded.

Implement with editorial license.

CI 186 SC 186.4.2.1 P652 L17 # 117

Wienckowski, Natalie IVN Solutions LLC

Comment Type T Comment Status A (bucket) (L)

This Boolean variable is never set to false.

**SuggestedRemedy**

Add at the end of the description: Otherwise, this variable is set to false.

Response Response Status C

ACCEPT IN PRINCIPLE.

The rx\_rm\_degraded variable is not used (or set) in any state diagram and therefore does not belong in the state machine variable definitions list.

Delete the variable definition of rx\_rm\_degraded.

Implement with editorial license.

CI 180 SC 180.7.1 P454 L26 # 124

Landry, Gary Texas Instruments

Comment Type E Comment Status R (bucket) (O)

The text was changed from referencing "Table 180-8" to "180-9." This sentence refers to the Tx specs and should have remained "Table 180-8"

**SuggestedRemedy**

Change reference back to Table 180-8

Response Response Status C

REJECT.

The D2.1 clean version correctly has the cross reference as Table 180-8

CI 181 SC 181.7.1 P484 L21 # 125

Landry, Gary Texas Instruments

Comment Type E Comment Status R (bucket) (O)

The variable OMAouter (min) is now shown as "max(TECQ, TDECQ)." While strictly correct, it would be better to explicitly show the offset for parallelism to other clauses

**SuggestedRemedy**

Change "max(TECQ, TDECQ)" to "0 + max(TECQ, TDECQ)"

Response Response Status C

REJECT.

While the intention of the comment is understandable, it is unnecessary to add 0 when the value has an explicit expression, i.e., max(TECQ, TDECQ).

CI 185A SC 185A.2.4.1 P914 L50 # 129

Zimmerman, George ADI,APLgp,Cisco,Marvell,OnSemi,Sony

Comment Type TR Comment Status A (bucket) ENOB (O)

while the final ENOB number is the average of "the individual points" - what are the points being averaged - are they "effective bits", are they "SNR" in dB (both log scales, so this is a geometric mean), or are they a linear average of signal power and noise power from which effective bits is then computed (more accurate). The text doesn't say. I have an old version of IEEE Std 1241 (2011), but I believe you want to average the NAD term, according to equation 67 there (COherent sampling test method for SINAD in the frequency domain).

**SuggestedRemedy**

Change "The final ENOB number is then the average of the individual points." to "The final ENOB number is computed from the linearly averaging the noise and distortion terms and then computing ENOB of that average according to IEEE Std 1241-2023."

Response Response Status W

ACCEPT IN PRINCIPLE.

In 185A.2.4.1 replace "The final ENOB number is then the average of the individual points." with "The final ENOB number is computed from linearly averaging the noise and distortion terms and then computing ENOB of that average according to IEEE Std 1241-2023."

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 185A SC 185A.2.5.3 P917 L35 # 130

Zimmerman, George ADI,APLgp,Cisco,Marvell,OnSemi,Sony

Comment Type T Comment Status R (bucket) shall statements (O)

I think this is the key requirement for ETCC - the stepwise calculation. Unfortunately, you can't actually specify the steps - that's a requirement on the user - but you can specify the steps or their equivalent.

*SuggestedRemedy*

Replace "ETCC is calculated using the following steps." with "ETCC shall be calculated using the following steps, or methods which produce the same result."

Response Response Status C

REJECT.

The normative statement is in clauses 185 and 187 that use the annex. In both clauses the parameter definition is "The ETCC shall be within the limit given in Table 185-5 if measured using the methods specified in 185.9" where 185.9 points to the annex and provides the specific parameter values to use the annex.

To meet ETCC requirement the value must be measured per the steps in the annex, adding "or methods which produce the same result" removes this requirement.

CI 180 SC 180.7.3 P456 L35 # 133

Ghiasi, Ali Ghiasi Qunatum/Marvell

Comment Type TR Comment Status R (withdrawn)

In D2.0 1T DFE was added to the TDECQ equalizer which reduces TDECQ by 0.5-1.0 dB. Given the TDECQ reduction, assuming 3.0 dB is the value WG accepts then power budget can be adjusted down.

*SuggestedRemedy*

In Table 180-9 make following changes

- Power budget (for Max TDECQ) reduced from 6.7 to 6.3 dB
- Allocation for penalties (for Max TDECQ) reduced from 3.7 to 3.3 dB

see ghiasi\_3dj\_02\_2509

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 180 SC 180.7.3 P456 L35 # 136

Ghiasi, Ali Ghiasi Qunatum/Marvell

Comment Type TR Comment Status R (withdrawn)

In D2.0 1T DFE was added to the TDECQ equalizer which reduces TDECQ by 0.5-1.0 dB. Given the TDECQ reduction, assuming 3.0 dB is the value WG accepts then power budget is reduced by 0.4 dB.

*SuggestedRemedy*

Given the 0.4 dB power budget reduction in Table 180-9 suggest to split the difference between TX and RX PMDs, and make following adjustments to the OMA:

- Table 180-7 Outer OMA change 4.2 to 4.0 dBm
- Table 180-8 Receiver Power Outer OMA (max) change 4.2 to 4.0 dBm

see ghiasi\_3dj\_02\_2509

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 181 SC 181.7.3 P487 L35 # 137

Ghiasi, Ali Ghiasi Qunatum/Marvell

Comment Type TR Comment Status R (withdrawn)

In D2.0 1T DFE was added to the TDECQ equalizer which reduces TDECQ by 0.5-1.0 dB. Given the TDECQ reduction, assuming 3.0 dB is the value WG accepts then power budget is reduced by 0.4 dB.

*SuggestedRemedy*

Given the 0.4 dB power budget reduction in Table 181-7 suggest to split the difference between TX and RX PMDs, and make following adjustments to the OMA:

- Table 181-5 Outer OMA change 4.8 to 4.6 dBm
- Table 181-6 Receiver Power Outer OMA (max) change 4.8 to 4.6 dBm

see ghiasi\_3dj\_02\_2509

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.



## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 180 SC 180.9.5 P462 L8 # 144

Ghiasi, Ali Ghiasi Qunatum/Marvell

Comment Type TR Comment Status R TDECQ method (CO)

TDECQ mission mode test definition should be made more clear

#### SuggestedRemedy

Proposed text

TDECQ is defined with all receive xAUI-n lanes when instantiated in operation using test pattern 3 or 5 (see Table 180–13). xAUI-n lanes operate with receiver jitter tolerance condition defined by applicable instantiated xAUI-n.

The received test patterns shall be asynchronous to the pattern used to test the transmitter, and shall

have power levels as specified in Table 180–8 for the aggressor lanes in the stressed receiver sensitivity test.

Response Response Status U

REJECT.

There was not sufficient consensus to adopt the proposed changes.

Straw poll TF-4 (directional)

I support adopting the suggested remedy with or without some caveats for clauses 180 through 183.

Yes: 10

No: 11

NMI: 3

Abstain: 13

CI 180 SC 180.7.1 P453 L47 # 157

Ghiasi, Ali Ghiasi Qunatum/Marvell

Comment Type TR Comment Status R (withdrawn)

In D2.0 1T DFE was added to the TDECQ equalizer which reduces TDECQ by 0.5-1.0 dB. If TDECQ/TECQ are kept at 3.4 dB given the new TDECQ equalizer will add 1+ dB of penalty to the receiver.

#### SuggestedRemedy

Propose to split the gain from 1T DFE between TX and RX PMDs:

- Reduce TDECQ from 3.4 dB to 3.0

- Reduce TECQ from 3.4 dB to 3.0

- Reduce |TDECQ-TECQ| from 2.5 dB to 2.2 dB

- Reduce TDECQ range from 3.4 dB to 3.0 under Outer OMA parameter

Based on the resolution also adjust Figure 180-3, SECQ in table 180-8, Figure 180-4, and Figure 180-5, see ghiasi\_3dj\_01\_2509

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 181 SC 181.7.1 P484 L24 # 158

Ghiasi, Ali Ghiasi Qunatum/Marvell

Comment Type TR Comment Status R (withdrawn)

In D2.0 1T DFE was added to the TDECQ equalizer which reduces TDECQ by 0.5-1.0 dB. If TDECQ/TECQ are kept at 3.4 dB given the new TDECQ equalizer will add 1+ dB of penalty to the receiver.

#### SuggestedRemedy

Propose to split the gain from 1T DFE between TX and RX PMDs:

- Reduce TDECQ from 3.4 dB to 3.0

- Reduce TECQ from 3.4 dB to 3.0

- Reduce |TDECQ-TECQ| from 2.5 dB to 2.2 dB

- Reduce TDECQ range from 3.4 dB to 3.0 under Outer OMA parameter

Based on the resolution also adjust Figure 180-3, SECQ in table 180-8, Figure 180-4, and Figure 180-5, see ghiasi\_3dj\_01\_2509

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 180 SC 180.7.3 P456 L35 # 166

Ghiasi, Ali Ghiasi Qunatum/Marvell

Comment Type TR Comment Status R (withdrawn)

In D2.0 1T DFE was added to the TDECQ equalizer which reduces TDECQ by 0.5-1.0 dB. Given the TDECQ reduction, assuming 3.0 dB is the value WG accepts then power budget can be adjusted down.

#### SuggestedRemedy

In Table 180-9 make following changes  
 - Power budget (for Max TDECQ) reduced from 6.7 to 6.3 dB  
 - Allocation for penalties (for Max TDECQ) reduced from 3.7 to 3.3 dB  
 see ghiasi\_3dj\_02\_2509

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 181 SC 181.7.3 P487 L35 # 167

Ghiasi, Ali Ghiasi Qunatum/Marvell

Comment Type TR Comment Status R (withdrawn)

In D2.0 1T DFE was added to the TDECQ equalizer which reduces TDECQ by 0.5-1.0 dB. Given the TDECQ reduction, assuming 3.0 dB is the value WG accepts then power budget can be adjusted down.

#### SuggestedRemedy

In Table 181-9 make following changes  
 - Power budget (for Max TDECQ) reduced from 7.5 to 7.1 dB  
 - Allocation for penalties (for Max TDECQ) reduced from 4.0 to 3.6 dB  
 see ghiasi\_3dj\_02\_2509

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 180 SC 180.9.5 P447 L1 # 179

El-Chayeb, Ahmad Keysight Technologies (ahmad.el-chayeb@keysight.c

Comment Type TR Comment Status A TDECQ (CO)

The current TDECQ calculated at a pre-FEC target SER is intended to correlate to receiver sensitivity, not link performance

#### SuggestedRemedy

Add a new CER TDECQ metric that estimates the power penalty at a target CER (codeword error ratio) to have better correlation with link performance. The definition for this CER TDECQ and suggested wording will be provided in a supporting presentation.

Response Response Status C

ACCEPT IN PRINCIPLE.

The following contribution was reviewed by the CRG:  
[https://www.ieee802.org/3/dj/public/25\\_09/chayeb\\_3dj\\_01b\\_2509.pdf](https://www.ieee802.org/3/dj/public/25_09/chayeb_3dj_01b_2509.pdf)

According straw poll TF-3 there is sufficient consensus for the proposal in chayeb\_3dj\_01b\_2509.

Implement the proposal on slides 12 to 19 of chayeb\_3dj\_01b\_2509 in Clause 180, 181, 182, and 183.

Clarify on slide 15 that "center of the target histogram" refers to the horizontal center.

Straw poll TF-3 (directional)

I support adopting the proposal on slides 12 to 19 of  
[https://www.ieee802.org/3/dj/public/25\\_09/chayeb\\_3dj\\_01b\\_2509.pdf](https://www.ieee802.org/3/dj/public/25_09/chayeb_3dj_01b_2509.pdf)

Yes: 22

No: 10

NMI: 8

Abstain: 12

CI 177 SC 177.1.1 P339 L12 # 189

Bruckman, Leon Nvidia

Comment Type E Comment Status A (bucket) (L)

Text can be simplified. As an example see similar text in 176.1.1

#### SuggestedRemedy

Change: "When necessary for disambiguation, to differentiate the Inner FEC defined in this clause"

To: "When necessary to differentiate the Inner FEC defined in this clause"

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #504

CI 177 SC 177.4.7.2 P348 L48 # 190

Bruckman, Leon

Nvidia

Comment Type TR Comment Status A (bucket) (L)

It will be beneficial to refer to the PRBS13 pattern generator figure in the base standard.

#### SuggestedRemedy

Change: "using a self-synchronizing PRBS13 scrambler using the same polynomial as Equation (94-3)."

To: "using a self-synchronizing PRBS13 scrambler as shown in Figure 94-6 and using the polynomial defined in Equation (94-3)."

Response Response Status W

ACCEPT.

CI 177 SC 177.5.2 P350 L36 # 191

Bruckman, Leon

Nvidia

Comment Type T Comment Status A (bucket) (L)

Pad identification and removal is described in the next section. It will be useful to refer to it.

#### SuggestedRemedy

Change: "removed before the received data is processed further."

To: "removed before the received data is processed further (see 177.5.3)."

Response Response Status C

ACCEPT.

CI 186 SC 186.2.1 P620 L8 # 192

Bruckman, Leon

Nvidia

Comment Type TR Comment Status A (bucket) (L)

The indicated rate is nominal. See page 620 line 53.

#### SuggestedRemedy

Change: "a rate of 26.5625 Gb/s." To: "a nominal rate of 26.5625 Gb/s."

Response Response Status W

ACCEPT.

CI 186 SC 186.2.2 P621 L6 # 193

Bruckman, Leon

Nvidia

Comment Type TR Comment Status A (bucket) (L)

According to Figure 186-3, FEC:IS\_SIGNAL.indication is also influenced by PMA:IS\_SIGNAL.indication from the PMA.

#### SuggestedRemedy

Change: "The SIGNAL\_OK parameter is set to OK when fec\_all\_mfas\_locked (see 186.4.2.1) is true and is set to FAIL when fec\_all\_mfas\_locked is false."

To: "The SIGNAL\_OK parameter is set to OK when fec\_all\_mfas\_locked (see 186.4.2.1) is true and the PMA:IS\_SIGNAL.indication(SIGNAL\_OK) is set to OK, and is set to FAIL otherwise."

Response Response Status W

ACCEPT.

CI 73A SC 73A.1a P696 L36 # 194

Bruckman, Leon

Nvidia

Comment Type T Comment Status A (bucket) (L)

Host class is not negotiated, but it is part of an autonegotiation page. This may create confusion

#### SuggestedRemedy

Add footnote to Table 73A-1b: Host class is only reported, no negotiation is required."

Response Response Status C

ACCEPT.

CI 178B SC 178B.1 P835 L12 # 196

Bruckman, Leon

Nvidia

Comment Type T Comment Status A (bucket) (CI)

This is an annex not a clause

#### SuggestedRemedy

Change: "This clause defines" to: "This annex defines"

Response Response Status C

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.8 P863 L16 # 197  
 Bruckman, Leon Nvidia  
 Comment Type T Comment Status A (bucket) (CI)  
 Wrong reference for mr\_restart, mr\_training\_enable and training\_status  
 SuggestedRemedy  
 In Table 178B-6 change the references of mr\_restart, mr\_training\_enable and training\_status to point to clause 45 and not clause 42.  
 Response Response Status C  
 ACCEPT.

CI 73 SC 73 P136 L3 # 199  
 Bruckman, Leon Nvidia  
 Comment Type TR Comment Status A (bucket) (L)  
 After adding the Host class to Autonegotiation, the base standard introduction to AN in 73.1 needs to be updated.  
 SuggestedRemedy  
 In 73.1  
 Change: "The Auto-Negotiation function allows an Ethernet device to advertise modes of operation it possesses to another device at the remote end of a Backplane Ethernet link and to detect corresponding operational modes the other device may be advertising."  
 To: "The Auto-Negotiation function allows an Ethernet device to advertise modes of operation it possesses and its characteristics to another device at the remote end of a Backplane Ethernet link and to detect corresponding operational modes and characteristics the other device may be advertising."  
 Response Response Status W  
 ACCEPT IN PRINCIPLE.

Change the text to:  
 "The Auto-Negotiation function allows an Ethernet device to advertise characteristics and modes of operation it possesses to another device at the remote end of a Backplane Ethernet link and to detect corresponding operational modes and characteristics that the other device may be advertising".

CI 73 SC 73.9.1.1 P147 L44 # 200  
 Bruckman, Leon Nvidia  
 Comment Type E Comment Status A (bucket) (L)  
 Missing word  
 SuggestedRemedy  
 Change: "one of values" to: "one of three values"  
 Response Response Status C  
 ACCEPT.

CI 116 SC 116.3.3.3.1 P171 L34 # 201  
 Bruckman, Leon Nvidia  
 Comment Type T Comment Status A management intervention (CG)  
 For the values of SIGNAL\_OK = READY or IN\_PROGRESS, it is specified that "Management intervention is not required".  
 When SIGNAL\_OK = FAIL, management intervention may be required, but this is not indicated.  
 SuggestedRemedy  
 Add the following text to the end of definition of the FAIL value of SIGNAL\_OK: "Management intervention may be required".  
 Also in the second paragraph in page 172, at the end of the paragraph that starts: "A value of FAIL indicates..." add the following text: "and management intervention may be required."  
 Response Response Status C  
 ACCEPT IN PRINCIPLE.  
 Resolve using the responses to comment #335 and #336.

CI 178 SC 178.10.6 P390 L35 # 204  
 Brown, Matt Alphawave Semi  
 Comment Type T Comment Status R (withdrawn)  
 The following paragraph is informative since it gives information that is not normative or building upon normative content.  
 "Systems with no AC-coupling within the channel are considered engineered links. It is the system integrator's responsibility to verify that the transmitter and the receiver are compatible with the common-mode voltage differences that may exist in this configuration."  
 SuggestedRemedy  
 Change the paragraph to an informative note, starting with "NOTE--"  
 Response Response Status Z  
 REJECT.  
 This comment was WITHDRAWN by the commenter.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 179 SC 179.9.4.1.2 P411 L32 # 205

Brown, Matt

Alphawave Semi

Comment Type T Comment Status R (withdrawn)

The following paragraph is informative since it gives information that is not normative or building upon normative content. In fact, it is talking about a system that violates the normative specifications in this clause.

"Systems with transmitters having steady-state voltage higher than the maximum specified in Table 179–7 are considered engineered links. It is the system integrator's responsibility to verify that the transmitter, receiver, and channel are compatible."

Note that this text was correctly implemented per the adopted response to Draft 2.1 comment #668.

#### SuggestedRemedy

Change the paragraph to an informative note, starting with "NOTE--"

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 179 SC 179.9.4.1.5 P413 L1 # 206

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A cket) Standards language (E)

A note (preceded with "NOTE--") is an informative statement. The word "may" is normative interpreted as "is permitted to" per the style guide. If this is intended to describe the possibility given the normative specifications, then we can change "may" to "can" (interpreted as "is able to"). If we want to give permission, then it should not be an informative note. The style manual helps us with the latter suggest that the sentence be prefixed with "Note that".

#### SuggestedRemedy

Two solutions are suggested:

#1 Change "may" to "can". (preferred)

#2 Change "Note--Any" to "Note that any"

Response Response Status C

ACCEPT IN PRINCIPLE.

Change "may" to "can".

CI 179 SC 179.9.4.6 P414 L40 # 207

Brown, Matt

Alphawave Semi

Comment Type T Comment Status A cket) Standards language (E)

The second sentence of the informative note is making a recommendation, which is normative, not informative, as it could mean the test is not properly done otherwise. The style manual helps us out suggesting that instead we use "Note that" if it is normative.

#### SuggestedRemedy

Change "NOTE--Outputs" to "Note that outputs".

Response Response Status C

ACCEPT IN PRINCIPLE.

The recommendation in the second sentence ("Other circuitry in lanes not under test should be kept active during the measurement") can affect the measurement result and is not just explanatory.

Move the second sentence from the NOTE to the paragraph above it, with editorial license.

CI 179 SC 179.9.5.2 P419 L11 # 208

Brown, Matt

Alphawave Semi

Comment Type T Comment Status R (withdrawn) (bucketp)

Two concerns with this note. First, the statements are extra information relating to the normative requirements and is worded somewhat normatively; so this should not be an informative note. Secondly, the first sentence is ambiguous as it is the measurement of steady-state voltage as specified in 179.9.4.1.2 that is defined with the transmitter set to preset 1.

#### SuggestedRemedy

Change "NOTE—Steady-state voltage is defined with preset 1. It is not initially generated by a transmitter, due to the initialize setting in Table 179–8."

To "Note that the measurement of steady-state voltage as defined in 179.9.4.1.2 with transmit equalizer set to preset 1 (no equalization), which is not initially generated by a transmitter per initialize setting in Table 179–8 ."

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 179 SC 179.9.5.3.4 P421 L30 # 209

Brown, Matt Alphawave Semi

Comment Type T Comment Status R (withdrawn)

This informative note is providing clarification of a normative specification and thus is not really informative.

SuggestedRemedy

Change "Note--The" to "Note that the".

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

CI 174A SC 174A.12 P726 L4 # 211

Brown, Matt Alphawave Semi

Comment Type E Comment Status A (bucket) (CG)

In Figure 174A-6, the spans labelled "Physical Layer implementation" were meant to illustrate the portion of this block diagram that is within the Physical Layer, similar to the spans for PHY and xMII extender.

SuggestedRemedy

In Figure 174A-6, change "Physical Layer implementation" to "Physical Layer" in two places.

Response Response Status C

ACCEPT.

CI 174A SC 174A.12 P729 L48 # 212

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CG)

BER specified for xAUI-n C2C in Table 174A-3 (0.1E-4) is larger than that specified in the preceding tables for PHYs. For the latter, the numbers provided are the limits for the xAUI-n defined in Annex 176C and Annex 176D which were chosen to leave sufficient BER allocation for the PMD. For the the xMII Extender however there is room for excess BER on the C2C. The value 0.1E-4 is thus used allowing use of 50 Gb/s per lane (Annex 120D) and 100 Gb/s per lane xAUI-n (Annex 120F) xAUI-n C2C which are specified to 0.1E-4. A note for the reader to explain this would be helpful as it is not obvious.

SuggestedRemedy

In Table 174A-3, add a table note related to the C2C "A value of 0.1E-4 rather than 0.08E-4 is allocated to an xAUI-n C2C in an xMII Extender since there significant BER margin and this allows the use of an xAUI-n defined in Annex 120D or Annex 120F to be used without reducing the specified BER limit."

Response Response Status C

ACCEPT.

CI 174A SC 174A.12 P729 L48 # 213

Brown, Matt Alphawave Semi

Comment Type T Comment Status A (bucket) (CG)

BER for the XS-to-XS path is 2.21E-4. However, the total allocation to the two ISLs withing an XS-to-XS path (xMII extender) is 0.34. So there is significant margin. The allocation to the XS-to-XS path is based on the FLR allocated to the XS-to-XS path capability of the RS-FEC. The allocation to the xAUI-n is based on the specified limits for permitted xAUI-n, the sum of which is much lower than necessary to meet the FLR target. A note for the reader to explain this would be helpful as it is not obvious.

SuggestedRemedy

In Table 174A-3, add a table note related to the XS-to-XS path BER allocation as follows: "The BER allocation for the XS-to-XS path is based on the FLR target and the capability of the RS-FEC while the BER per ISL is based on the specified limits for permitted xAUI-n C2C and C2M, which were constrained by their respective specifications. This results in a significant BER margin for the XS-to-XS and PCS-to-FEC paths."

Response Response Status C

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.1 P835 L12 # 217

D'Ambrosia, John Futurewei, U.S. Subsidiary of Huawei

Comment Type E Comment Status A (bucket) (CI)

Opening states - "This clause..."  
this is an annex

SuggestedRemedy  
Replace "clause" with "annex"

Response Response Status C

ACCEPT.

CI 180A SC 180A.4.2 P905 L34 # 218

D'Ambrosia, John Futurewei, U.S. Subsidiary of Huawei

Comment Type ER Comment Status A (bucket) (O)

There are two instances of 1.6TBASE-DR8 in the note.

SuggestedRemedy  
The second instance of 1.6TBASE-DR8 should be replaced with "1.6TBASE-DR8-2."

Response Response Status W

ACCEPT.

CI 178B SC 178B.7.3.5 P860 L52 # 231

Mi, Guangcan Huawei Technologies Co., Ltd

Comment Type T Comment Status A (bucket) (CI)

there is a variable isl\_ready and a state ISL\_READY. The variable isl\_ready is used in the RTS state diagram. But not appearing in the control state diagram. By definition

SuggestedRemedy  
change the local\_rx\_ready and remote\_rx\_ready after the ISL\_READY state to isl\_ready

Response Response Status C

ACCEPT.

CI 180 SC 180.9.7 P464 L31 # 233

Mi, Guangcan Huawei Technologies Co., Ltd

Comment Type E Comment Status A (bucket) (O)

p=1, where p should be italian

SuggestedRemedy  
make p italian

Response Response Status C

ACCEPT IN PRINCIPLE.  
Change the format of p into italics.

CI 178B SC 178B.5.3 P845 L26 # 236

Mi, Guangcan Huawei Technologies Co., Ltd

Comment Type ER Comment Status A (bucket) (CI)

the caption of the figure, "Figure 178B-7—Initial condition request", is misplaced or the figure is missing.

SuggestedRemedy  
Delete the caption, or add the figure.

Response Response Status W

ACCEPT IN PRINCIPLE.  
Resolve using the response to comment #23.

CI 184 SC 184.4.7 P575 L45 # 239

He, Xiang Huawei

Comment Type ER Comment Status A (bucket) (L)

The terminology "DP-QAM16" is not used in the standard. Instead, "DP-16QAM" is used.

SuggestedRemedy  
Change "DP-QAM16" to "DP-16QAM"

Response Response Status W

ACCEPT.

CI 174A SC 174A.6 P717 L43 # 240

He, Xiang Huawei

Comment Type T Comment Status A (bucket) (CG)

Is it really necessary to specify CRC error ratio to three digits?

**SuggestedRemedy**

Consider to keep only two digits like all other error ratios.

**Response** Response Status C

ACCEPT IN PRINCIPLE.  
The extra two digits will have insignificant impact on the the FLR which is specified with 2 significant figures.  
Change "5.706E-11" to "5.7E-11".

CI 174A SC 174A.8.2 P720 L8 # 241

He, Xiang Huawei

Comment Type TR Comment Status A (bucket) (CG)

The number of physical lanes is p, so the index i should be in the range" 0 through p-1", instead of "0 through p".

**SuggestedRemedy**

Change "p" to "p-1"

**Response** Response Status W

ACCEPT.

CI 174A SC 174A.8.2 P720 L9 # 242

He, Xiang Huawei

Comment Type TR Comment Status A (bucket) (CG)

"test\_block\_error\_bin\_i\_k" is used in other clause, instead of "test\_block\_error\_count\_i\_k".  
Change "count" to "bin".  
Do the same for "test\_block\_error\_count\_i\_16p".

**SuggestedRemedy**

Change "count" to "bin" for "test\_block\_error\_bin\_i\_k" and "test\_block\_error\_count\_i\_16p".

**Response** Response Status W

ACCEPT IN PRINCIPLE.  
Change "test\_block\_error\_count\_i\_k"  
To "test\_block\_error\_bin\_i\_k"  
Change "test\_block\_error\_count\_i\_16p"  
To: "test\_block\_error\_bin\_i\_16p"  
Implement with editorial license.

CI 174A SC 174A.8.3 P720 L39 # 243

He, Xiang Huawei

Comment Type TR Comment Status A (bucket) (CG)

In Equation 174A-1 and 174A-2, "test\_block\_error\_count\_i\_k" should be "test\_block\_error\_bin\_i\_k".

**SuggestedRemedy**

Change "test\_block\_error\_count\_i\_k" to "test\_block\_error\_bin\_i\_k" in Equation 174A-1 and 174A-2.

**Response** Response Status W

ACCEPT IN PRINCIPLE.  
Note that comment #242 proposed to rename the counters where they are defined in 174A.8.2.  
Implement the suggested remedy with editorial license.

CI 174A SC 174A.8.4 P720 L52 # 244

He, Xiang Huawei

Comment Type TR Comment Status R (bucket) (CG)

#Definition of k#  
Are we defining the variables at the first appearance and use this definition across this Annex? Or the definition varies from subclause to subclause?  
For example, if k is defined in 174A.8.2, where it says k is "in the range 0 through 15" (line 9) and again in 174A.8.3 as "k<16" (line 19), but in 174A.8.4 it has "k = 16" (line 52)? If this is a different k, we need to define it locally in this subclause (and in each subclause it is used). Otherwise we should stick to "0 through 15" as the range for "k".

**SuggestedRemedy**

Define the range of k clearly in the beginning, adding something like "k in the range 0 through 15 in Annex 174A", if this is the same k across this Annex. Do not redefine it, or at least use the same definition whenever it is used.

**Response** Response Status W

REJECT.  
This location as well as page 720 line 19 are not defining k, but rather defining the counts or histograms differently for different subranges of k. The indexing of the counters is unfortunately complicate because we named the 17th counter differently then the rest so is not conveniently indexed (see page 720 line 9).  
The definitions of k are otherwise consistent and correct. The proposed remedy does not improve the clarity.



## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 174A SC 174A.8.5 P721 L29 # 245

He, Xiang Huawei

Comment Type **TR** Comment Status **R** (bucket) (CG)

#Definition of k#  
"for all k>0" meaning "0<k<16" or "0<k<n"? Is 16 included?

*SuggestedRemedy*  
Define the range of k clearly in the beginning, adding something like "k in the range 0 through 15 in Annex 174A", if this is the same k across this Annex. Do not redefine it, or at least use the same definition whenever it is used.

Response Response Status **W**

REJECT.  
Resolve using the response to comment #244.

CI 174A SC 174A.10.4 P725 L8 # 246

He, Xiang Huawei

Comment Type **TR** Comment Status **A** (bucket) (CG)

The range for "i" is not clearly defined. While reading this I was confused whether this is only for the test channel or should this include the possible AUI's in the PHY receiver under test. If it is only PMD, then total lane number is p - we should clearly state that, and remove "or AUI component" in step b). If it includes the possible AUIs in the PHY receiver, the total number of lanes would be p + N\*n, where N is the number of AUIs?

*SuggestedRemedy*  
Specify the total number of lanes to be considered, i.e. range of "i" in this subclause.

Response Response Status **W**

ACCEPT IN PRINCIPLE.  
The method defined in 174A.10.4 is for the entire PHY receive path as measured at the PMD inputs and is not relevant to the AUI or AUI components.  
Change "the PMD or AUI component" to "the PMD".  
Change "For each lane i" to "For each PMD input lane i"

CI 178B SC 178B.4 P836 L40 # 247

He, Xiang Huawei

Comment Type **ER** Comment Status **R** (bucket) (CI)

The sentence "A physically instantiated interface is either a PMD or an AUI component." is repeated too many times in this Annex.

*SuggestedRemedy*  
Consider to define this once in front (in fact it has been defined in 178B.3 which is the perfect place), and remove all other repetitions in the following text.

Response Response Status **W**

REJECT.  
This wording is used only in this paragraph and it adds clarity to the text.

CI 178B SC 178B.6 P852 L41 # 248

He, Xiang Huawei

Comment Type **E** Comment Status **A** (bucket) (CI)

The sentence does not read right with the first "both" because it says "an AUI component \*or\* PMD" before it.

*SuggestedRemedy*  
Remove the first "both" in the sentence.

Response Response Status **C**

ACCEPT.

CI 178B SC 178B.7.3.5 P860 L45 # 249

He, Xiang Huawei

Comment Type **ER** Comment Status **A** (bucket) (CI)

the "not equals" sign should be "≠" instead of "#".

*SuggestedRemedy*  
Change "#" to "≠"

Response Response Status **W**

ACCEPT IN PRINCIPLE.  
According to Table 21–1—State diagram operators, not equal sign is ≠. Replace # with ≠.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178 SC 178.1 P384 L47 # 251  
 Mellitz, Richard Samtec  
 Comment Type TR Comment Status A (bucket) (E)  
 table 178–11 missing reference for SCMR\_CH  
 SuggestedRemedy  
 Add 179.11.8 as the reference  
 Response Response Status W  
 ACCEPT.

CI 178 SC 178.9.2.6 P378 L47 # 252  
 Mellitz, Richard Samtec  
 Comment Type TR Comment Status A (bucket) SCMR (E)  
 Comment 48 in  
[https://www.ieee802.org/3/dj/comments/D2p0/8023dj\\_D2p0\\_comments\\_final\\_clause.pdf](https://www.ieee802.org/3/dj/comments/D2p0/8023dj_D2p0_comments_final_clause.pdf)  
 Not implemented.  
 SuggestedRemedy  
 Either change equation 178-1  
 To  
 $SCMR = 10 \cdot \log_{10}(P_{\text{signal}} / VCM_{\text{FB}}^2)$   
 Or  
 $SCMR = 20 \cdot \log_{10}(\sqrt{P_{\text{signal}}} / VCM_{\text{FB}})$   
 Response Response Status W  
 ACCEPT IN PRINCIPLE.  
 Change equation (178-1) to  $SCMR = 10 \cdot \log_{10}(P_{\text{signal}} / VCM_{\text{FB}}^2)$ .

CI 176D SC 176D.7.1 P794 L25 # 275  
 Kutscher, Noam Marvell  
 Comment Type T Comment Status R (bucket) Figure labels (E)  
 The point in the center is not well defined. What is it? cage? HCB?  
 SuggestedRemedy  
 Add an explanation of the location to which the arrows point.  
 Response Response Status C  
 REJECT.  
 The NOTE at the bottom of the figure states "For loss budgeting purposes, the connector is considered part of the host". The arrows representing the channels indicate that; the connector (labeled) is within the host channel.  
 As noted in the subclause text, these losses are not expected to be measurable.  
 It is not clear whether additional explanation is necessary, and what it should be.  
 The suggested remedy does not provide sufficient detail to implement.

CI 178 SC 178.9.2 P376 L11 # 278  
 Kutscher, Noam Marvell  
 Comment Type T Comment Status R (bucket) TX jitter (E)  
 A difference of 0.002 is not a resolution that the Scope can provide.  
 SuggestedRemedy  
 Change the Tx package Class A value to be '0.12' instead of '0.118'.  
 Response Response Status C  
 REJECT.  
 Jitter specifications to 3 significant digits is consistent with previous clauses (e.g. 162, 163) and with the other electrical clauses in this draft.  
 No evidence has been presented that scopes cannot provide this resolution.

CI 174A SC 174A.12 P729 L30 # 279  
 Kutscher, Noam Marvell  
 Comment Type T Comment Status R (bucket) (CG)  
 Line 30 & 33 are the same line –'xAUI-n C2Cb'  
 SuggestedRemedy  
 Delete one of them.  
 Response Response Status C  
 REJECT.  
 Each row in Table 174A-2 represents one ISL in a PCS-to-PCS path. There is one xAUI-n C2C link at one end, a PMD link in the middle, and another xAUI-n C2C link at the other end. The sum of allocations to these links is equal to the net allocation to the PCS-to-PCS path. The table is correct as is. A similar approach is taken in Table 174A-1.

CI 1 SC 1.2.3 P54 L28 # 281  
 Huber, Thomas Nokia  
 Comment Type T Comment Status A (bucket) (CG)  
 Since this amendment is introducing "1.6TBASE-R", clause 1.2.3 needs to be updated to include "T" meaning Tb/s.  
 SuggestedRemedy  
 Change the first sentence of the last paragraph of 1.2.3 from  
 The data rate, if only a number, is in Mb/s, and if suffixed by a "G", is in Gb/s.  
 To  
 The data rate, if only a number, is in Mb/s, if suffixed by a "G", is in Gb/s, and if suffixed by a "T", is in Tb/s.  
 Response Response Status C  
 ACCEPT IN PRINCIPLE.  
 Implement suggested remedy with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 45 SC 45.2.1.258 P110 L29 # 282

Huber, Thomas

Nokia

Comment Type E Comment Status A (bucket) (L)

The registers in this subclause are used by both the "Inner FEC" and the "ER1 FEC", but the Name field is "Inner FEC", and Description is "Inner\_FEC\_..." Since the ER1 FEC is not an "inner FEC", the description should be generalized. This issue exists in subclauses 45.2.1.259, 45.2.1.260, and 45.2.1.261 also.

#### SuggestedRemedy

Change the Name column from "Inner FEC..." to "Inner FEC or ER1 FEC..."  
Change the Description column from "Inner\_FEC\_..." to "FEC\_..."

Response Response Status C

ACCEPT.

CI 176 SC 176.4.2 P311 L10 # 283

Huber, Thomas

Nokia

Comment Type T Comment Status A (bucket) (L)

The AMs provide both the RS FEC symbol boundary and the RS FEC codeword boundary

#### SuggestedRemedy

Change the beginning of the 3rd sentence from:  
"This also identifies the RS-FEC symbol boundary and allows the PCSs to then be deskewed and aligned to a multiple-symbol or codeword boundary..."  
to  
"This also identifies the RS-FEC symbol boundary and RS-FEC codeword boundary and allows the PCSs to then be deskewed and aligned to a multiple-symbol or codeword boundary..."

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement the suggested remedy with editorial license.

CI 177 SC 177.1.4 P340 L28 # 285

Huber, Thomas

Nokia

Comment Type ER Comment Status A (bucket) (L)

No need to describe the pad as "8x128b" in Figure 177-2. The details of how the pad is constructed are in 177.4.7, which is titled "Pad insertion and format".

#### SuggestedRemedy

Change the label from "8x128b pad insertion" to "Pad insertion" Make the same change in figure 177A-1.

Response Response Status W

ACCEPT.

CI 177 SC 177.10 P360 L29 # 286

Huber, Thomas

Nokia

Comment Type E Comment Status A (bucket) (L)

The variables for counting corrected codewords, uncorrected codewords, total bits, and corrected bits (rows 3-TBD) are shared with the ER1 FEC, so they should have more general names.

#### SuggestedRemedy

Change "Inner\_FEC\_..." to "FEC\_..." (see related comment on 45.2.1.258)

Response Response Status C

ACCEPT.

CI 177 SC 177.10 P363 L29 # 287

Huber, Thomas

Nokia

Comment Type E Comment Status A (bucket) (L)

In table 177-8, all of the variables that start with "Inner\_FEC\_delay..." are not aligned with the description in clauses 45.2.1.177a and 45.2.1.177b (or 45.2.1.175 for the ability registers)

#### SuggestedRemedy

Change "Inner\_FEC\_delay..." to "FEC\_delay..." in the last 12 rows of the table

Response Response Status C

ACCEPT.

CI 185 SC 185.12.4.1 P614 L32 # 288

Huber, Thomas

Nokia

Comment Type ER Comment Status A (bucket) (O)

Item F1 refers to an 800GBASE-LR1 PCS and PMA, but there are no such sublayers. Since LR1 requires an inner FEC it should be included in the PICS.

#### SuggestedRemedy

Change the feature column of item F1 to say "Compatible with 800GBASE-R PCS and PMA and 800GBASE-LR1 Inner FEC"

Response Response Status W

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 186 SC 186.2.1 P619 L30 # 289

Huber, Thomas Nokia

Comment Type T Comment Status A (bucket) (L)

The location of the test pattern insertion points should be shown in the overview figure

*SuggestedRemedy*

Add an arrow indicating PRBS31 insertion occurs above the GMP mapping function.

Response Response Status C

ACCEPT IN PRINCIPLE.

Modify figure 186-3 as proposed.

CI 186 SC 186.2.3.5.9 P626 L52 # 290

Huber, Thomas Nokia

Comment Type TR Comment Status A (bucket) (L)

The sum of C(sub)nD is encoded in bits D1-D5 rather than D1-D7.

*SuggestedRemedy*

Change "...is encoded in bits D1-D7 of JC4 and JC5..." to "...is encoded in bits D1-D5 of JC4 and JC5..."

Response Response Status W

ACCEPT.

CI 186 SC 186.2.3.12 P631 L33 # 291

Huber, Thomas Nokia

Comment Type T Comment Status A (bucket) (L)

The text regarding where the test pattern is inserted should be more clear.

*SuggestedRemedy*

Change "... is generated by the 800GBASE-ER1 FEC sublayer into each of the eight 800GBASE-ER1 tributary frames..." to "... is generated by the 800GBASE-ER1 FEB sublayer into each of the eight 800GBASE-ER1 tributary frames, before the GMP mapping process (see Figure 186-3)..."

Response Response Status C

ACCEPT IN PRINCIPLE.

Change "... is generated by the 800GBASE-ER1 FEC sublayer into each of the eight 800GBASE-ER1 tributary frames..." to "... is generated by the 800GBASE-ER1 FEC sublayer into each of the eight 800GBASE-ER1 tributary frames, before the GMP mapping process (see Figure 186-3)..."

CI 186 SC 186.7.2 P662 L6 # 292

Huber, Thomas Nokia

Comment Type E Comment Status A (bucket) (L)

The first 4 rows in the table are sharing registers with the clause 177 inner FEC, but they have different names than what is used in clause 177 and in clause 45

*SuggestedRemedy*

Change "FEC\_erc1fec\_..." to "FEC\_..."

Response Response Status C

ACCEPT IN PRINCIPLE.

CI 187 SC 187.6.1 P677 L34 # 293

Huber, Thomas Nokia

Comment Type TR Comment Status A (bucket) (O)

The ETCC row doesn't indicate min or max, which implies that the specified value of 2.5 is required. However, this is a maximum value.

*SuggestedRemedy*

Change the Description from "ETCC" to "ETCC (max)"

Response Response Status W

ACCEPT.

CI 187 SC 187.12.4.1 P689 L32 # 295

Huber, Thomas Nokia

Comment Type ER Comment Status A (bucket) (O)

Item F1 in the PICS refers to the 800GBASE-ER1 PCS. With the change to a FEC sublayer, this should refer to 800GBASE-R PCS, 800GBASE-ER1 FEC, and 800GBASE-ER1 PMA

*SuggestedRemedy*

Change the feature column of item F1 to say "Compatible with 800GBASE-R PCS, 800GBASE-ER1 FEC, and 800GBASE-ER1 PMA.

Response Response Status W

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 185A SC 185A.2.5 P916 L2 # 296

Huber, Thomas

Nokia

Comment Type ER Comment Status A (bucket) (O)

The text here was not updated to reflect the change in modeling of 800GBASE-ER1 as a FEC sublayer rather than a standalone PCS.

**SuggestedRemedy**

Change "... the input to the PCS for 800GBASE-ER1 and 800GBASE-ER1-20." to "... the input to the ER1 FEC for 800GBASE-ER1 and 800GBASE-ER1-20."

Response Response Status W

ACCEPT.

CI 176C SC 176C.6.4.6 P776 L33 # 306

Healey, Adam

Broadcom, Inc.

Comment Type TR Comment Status A (bucket) RX JTOL (E)

The jitter tolerance test procedure defined in Annex 176C is not consistent with the test procedure defined in Clause 178. There is no obvious reason why the test procedures should differ.

**SuggestedRemedy**

Align the jitter tolerance test procedure defined in 176C.6.4.6 with the jitter tolerance test procedure defined in 178.9.3.5.

Response Response Status W

ACCEPT IN PRINCIPLE.

The addition of additive broad-band noise to calibrate COM in the jitter tolerance test (comment #496 against D2.0, see <[https://www.ieee802.org/3/dj/comments/D2p0/8023dj\\_D2p0\\_comments\\_final\\_id.pdf#page=129](https://www.ieee802.org/3/dj/comments/D2p0/8023dj_D2p0_comments_final_id.pdf#page=129)>) was implemented in clause 178 but not in the other clauses, although that was obviously the intent.

Apply changes corresponding to the resolution of comment #496 in clause 179, annex 176C, and annex 176D.  
Implement with editorial license.

CI 176D SC 176D.8.13.2 P805 L23 # 307

Healey, Adam

Broadcom, Inc.

Comment Type TR Comment Status A (bucket) ITOL/JTOL (E)

The first sentence of the note below Table 176D-10 states the following. "For a module input test, ADD and sigmaRJ calculated from pattern generator measurements using Equation (179-14) and Equation (179-15) can be higher than the values in Table 176D-7. In this case, a suitable channel should be chosen in order to meet the COM requirement with these higher values." This suggests that a receiver is permitted to be tested with a transmitter that is far outside the limits imposed on compliant transmitters. It also relies on the Channel Operating Margin (COM) calculation being able to correctly evaluate the penalty caused by transmitters with high jitter. The COM calculation uses a first-order approximation of the noise due to transmitter jitter and the accuracy of this approximation can be expected to degrade for higher levels of jitter. Therefore, it seems likely trade-offs between channel loss/noise and jitter may not be evaluated accurately. The test transmitter, including the added sinusoidal jitter, should be required to meet the JRMS and Jnu03 specifications or the degree to which the test transmitter is allowed to exceed the specifications should be limited.

**SuggestedRemedy**

Remove the first sentence of the note. The requirements of 176D.8.12.2 (referred to by 176D.8.13.2) item d) are then expected to apply.

Response Response Status W

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #308.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 179 SC 179.9.5.4.2 P423 L23 # 308

Healey, Adam Broadcom, Inc.

Comment Type TR Comment Status A (bucket) ITOL/JTOL (E)

The note below Table 179-13 states the following. "The ADD (Equation (179-14)) and sigmaRJ (Equation (179-15)) calculated from transmitter measurements in this test may be higher than the values in Table 179-19. A suitable channel should be chosen in order to meet the COM requirement with these values." This suggests that a receiver is permitted to be tested with a transmitter that is far outside the limits imposed on compliant transmitters. It also relies on the Channel Operating Margin (COM) calculation being able to correctly evaluate the penalty caused by transmitters with high jitter. The COM calculation uses a first-order approximation of the noise due to transmitter jitter and the accuracy of this approximation can be expected to degrade for higher levels of jitter. Therefore, it seems likely trade-offs between channel loss/noise and jitter may not be evaluated accurately. The test transmitter, including the added sinusoidal jitter, should be required to meet the JRMS and Jnu03 specifications or the degree to which the test transmitter is allowed to exceed the specifications should be limited.

#### SuggestedRemedy

Remove the note. The requirements of 179.9.5.3.3 (referred to by 179.9.5.4.2) item c) are then expected to apply.

Response Response Status W

ACCEPT IN PRINCIPLE.

The measured parameters of the pattern generator, J4u\_03 and J\_RMS, need to be within the limits in Table 179-7.

Add a statement in 179.9.5.4.1 that the pattern generator with SJ inspection complies with EOJ03, J4u03, and JRMS in Table 179-7.

Apply similar changes in the JTOL subclauses in Clause 178, Annex 176C, and Annex 176D.

Implement with editorial license.

CI 179 SC 179.8.1 P404 L23 # 309

Healey, Adam Broadcom, Inc.

Comment Type E Comment Status A (bucket) Test points (E)

In Table 179.8.1 the term "die bump" is used in the definition of TP0d and TP5d but it is not defined in IEEE Std 802.3 (or in the IEEE P802.3dj draft). Since TP0d and TP5d are also defined in Clause 178 and Annex 176C, use of similar language seems appropriate. Refer to Figure 178-2 for an example.

#### SuggestedRemedy

Replace "die bump" with "device-to-package interface" in the definitions of TP0d and TP5d.

Response Response Status C

ACCEPT.

CI 176D SC 176D.7.1 P794 L21 # 310

Healey, Adam Broadcom, Inc.

Comment Type E Comment Status A (bucket) Figure labels (E)

The term "die-to-die channels" is used but the term "die" is not in IEEE Std 802.3 (or in the IEEE P802.3dj draft). "Device" has been used instead e.g., in the Channel Operating Margin reference model.

#### SuggestedRemedy

Change "die-to-die channels" to "device-to-device channels". Make the same change in Figure 176D-6.

Response Response Status C

ACCEPT IN PRINCIPLE.

"Device-to-Device channel" has not been used anywhere in 802.3 or in presentations. The editor suspects that this term would be more confusing than "die-to-die". However, the terms "die-to-die" and "end-to-end" that appear in 176D.7 and subclause can be made more specific, using the named test points.

In the first sentence of 176D.7, change from "the channel between the C2M components is not specified from end to end" to "the channel between the C2M components is not specified".

In 176D.7.1, change "The insertion loss of the host, module, and die-to-die channels is not expected to be measurable" to "The insertion losses of the host channel, the module channel, and the TP0d-TP1d and TP4d-TP5d channels are not expected to be measurable". In Figure 176D-6, change the label "Die-to-die" to "TP0d-TP1d and TP4d-TP5d".

Implement with editorial license.

CI 178 SC 178.9.2.6 P378 L47 # 311

Levin, Itamar Altera corp.

Comment Type T Comment Status A (bucket) SCMR (E)

When changing from vpeak to Psignal in this formula going from D2.0 to D2.1, we now have a ratio of power to voltage within the log function, instead of a "unit-less" ratio. Note that in eq 179-8 Psignal is a sum of squares of pulse shapes which is proportional to power indeed (like in its use in eq. 179-9). And yet we have  $20\log \dots$ . If the formula originated from  $10\log(P/V^2)$  then that is still incorrect since this expression corresponds to  $20\log(P^{0.5}/V)$ .

#### SuggestedRemedy

If the intent here is to use Psignal, then in this formula we should take the root of this quantity in order to fix the ratio, or conversely - use  $10\log(P\text{signal}/V\text{cm}^2)$  in order for the quantity within the log function be unit-less.

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #252.

[Editor's note: changed page/line from 415/14]

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178 SC 178.9.2.6 P378 L52 # 312  
Levin, Itamar Altera corp.  
Comment Type E Comment Status R (bucket) (E)  
The accurate clause is not 179.9.4.5 but subclause 179.9.4.5.1  
SuggestedRemedy  
change 179.9.4.5 to 179.9.4.5.1  
Response Response Status C  
REJECT.  
179.9.4.5.1 was the subclause in D2.0 but its content was merged into 179.9.4.5.  
[Editor's note: changed page/line from 415/19]

CI 180 SC 180.9.4 P461 L33 # 316  
Rodes, Roberto Coherent  
Comment Type E Comment Status A (bucket) TDECQ method (O)  
The definitions of OMA, overshoot, transmitter power excursion, extinction ratio, and transition time are misleading. These tests are measured using waveforms at the output of the reference receiver defined in 180.9.5. This wording could give the impression that the same waveform used in 180.9.5 is applied to the test, which is not the case.  
SuggestedRemedy  
Move the definition of the reference receiver from the TDECQ to the TECQ subclause, and specify TDECQ by referencing TECQ with the addition of the fiber, instead of the other way around as it is currently written in the document.  
Response Response Status C  
ACCEPT IN PRINCIPLE.  
Implement the suggested remedy with editorial license.

CI 180 SC 180.9.13 P467 L29 # 319  
Johnson, John Broadcom  
Comment Type E Comment Status A (bucket) (O)  
The Note about the use of linear extrapolation, while syntactically correct, is challenging to parse.  
SuggestedRemedy  
Change From: "NOTE - To reduce test time, a means to provide statistical projection of the measured histograms (see 174A.8.3), if the statistical projection is modeled accurately by a linear fit extrapolation, follows."  
To: "NOTE - If the statistical projection is modeled accurately by a linear fit extrapolation, a means to provide statistical projection of the measured histograms (see 174A.8.3) in order to reduce test time follows."  
The same remedy can be applied to the Notes in clauses 180.9.14, 181.9.13, 181.9.14, 182.9.13, 182.9.14, 183.9.13 and 183.9.14, with editorial license.  
Response Response Status C  
ACCEPT IN PRINCIPLE.  
[Editor's note: changed page/line from 496/35]

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.2 P835 L23 # 320

Mascitto, Marco

Nokia

Comment Type T Comment Status A (bucket) (CI)

In TRAINING mode, locally generated training frames are sent to the peer interface, not data.

#### SuggestedRemedy

Replace:

Initially all ISLs are in TRAINING mode, in which the data sent to the peer is generated locally by each interface.

With:

Initially all ISLs are in TRAINING mode, in which the training frames sent to the peer are generated locally by each interface.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change: "Initially all ISLs are in TRAINING mode, in which the data sent to the peer is generated locally by each interface."

To: "Initially all AUI components and PMDs that have ILT enabled are in TRAINING mode (tx\_mode = training, see 178B.7.3.1), in which the training frames sent to the peer are generated locally by each interface."

In the following paragraph change: "ILT includes a training protocol, used in TRAINING mode,"

To: "ILT defines a training protocol, used in TRAINING mode (tx\_mode = training, see 178B.7.3.1),"

Implement with editorial license.

CI 178B SC 178B.2 P835 L30 # 321

Mascitto, Marco

Nokia

Comment Type E Comment Status A (bucket) (CI)

The last sentence of this paragraph is not clear and may lead to confusion.

#### SuggestedRemedy

Replace:

ILT can also establish communication between interfaces that do not use a training protocol.

With:

ILT ensures that any ISLs in the path that do not make use of the training protocol (e.g., ISLs using 100Gb/s lane technology) signal their readiness for DATA mode so that the end-to-end path start-up process can complete successfully.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change: "ILT can also establish communication between interfaces that do not use a training protocol."

To: "ILT allows ISLs in the path that do not make use of the training protocol to signal their readiness for DATA mode (tx\_mode = data, see 178B.7.3.1) so that the end-to-end path start-up process can complete successfully."

Implement with editorial license.

CI 178B SC 178B.3 P836 L15 # 324

Mascitto, Marco

Nokia

Comment Type T Comment Status A Path (CI)

Update the figure showing the path between RSs, per straw ballot results.

#### SuggestedRemedy

Update the figure showin the path between RSs, per straw ballot results.

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #417.



## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.4 P836 L47 # 325

Mascitto, Marco

Nokia

Comment Type E Comment Status A (bucket) (CI)

Improve clarity.

#### SuggestedRemedy

Replace:

The ILT function in AUI components and PMDs is composed of one per-interface function and one per-lane function for each lane associated with the interface as shown in Figure 178B-2.

With:

The ILT function at an interface is composed as shown in Figure 178B-2, with:

- one per-interface function
- one per-lane function for each lane associated with the interface

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #12.

CI 178B SC 178B.5 P837 L47 # 327

Mascitto, Marco

Nokia

Comment Type E Comment Status R (bucket) (CI)

The "rts" in variables local\_rts and remote\_rts is misleading and caused confusion. When asserted, it means the interface is ready to send (RTS) and receive (CTS) data, not just send data.

#### SuggestedRemedy

Propose changing local\_rts to local\_ifready and remote\_rts to remote\_ifready.

Response Response Status C

REJECT.

The term RTS is well defined. Implementing the proposed change may create confusion with the rx\_ready indication.

CI 178B SC 178B.6 P852 L34 # 328

Mascitto, Marco

Nokia

Comment Type T Comment Status R (bucket) (CI)

This statement conflicts with the variable definition in 178B.7.2.1. local\_rts asserted means that the training of the local interface has completed successfully. The training of the remote interface is still undetermined, so we are not yet in the ISL\_READY state.

#### SuggestedRemedy

Delete:

(it reached the ISL\_Ready state in Figure 178B-10)

Response Response Status C

REJECT.

local\_rts is set only if isl\_ready is set, and that indicates that both sides have completed training.

CI 178 SC 178.9.3.3 P380 L48 # 332

Mascitto, Marco

Nokia

Comment Type T Comment Status R (bucket) ITOL (E)

The receiver's control of the transmitter's equalizer coefficients is an important function that helps that receiver to meet the block error ratio. Recommend making this normative.

#### SuggestedRemedy

Change "The receiver may control" to "The receiver should control".

Response Response Status C

REJECT.

Receiver control of the transmit equalizer coefficients is an implementation choice, and some implementations may not need it to meet the test requirements. It is therefore optional to use the transmitter control in this test.

Note that the ILT function is a normative requirement regardless of this test.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178 SC 178.8.9 P374 L35 # 333

Mascitto, Marco

Nokia

Comment Type E Comment Status A (bucket) (E)

The statement is incomplete (cut-n-paste error).

#### SuggestedRemedy

Replace, "When the variable mr\_training\_enable is true, the ILT function is used to request changes to the peer transmitter state (modulation, training pattern, and precoder state), control the PMD transmitter output on each lane based on requests from the peer interface."

with

"When the variable mr\_training\_enable is true, the ILT function is used to request changes to the peer transmitter state (modulation, training pattern, and precoder state), control the PMD transmitter output on each lane based on requests from the peer, indicate the receiver state, and coordinate the transition of the PMD transmit function to DATA mode."

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #502.

CI 116 SC 116.3.3.3.1 P171 L18 # 334

Mascitto, Marco

Nokia

Comment Type E Comment Status R management intervention (CG)

A value of FAIL will require management intervention. Recommend stating this explicitly.

#### SuggestedRemedy

Add sentence, "Management intervention is required".

Response Response Status C

REJECT.

For this case, the value FAIL may not indicate the need for management intervention since for this case ILT as defined in Annex 178B is not supported. It would therefore not be generally correct. Also, the statement would in a small way affect legacy clauses.

CI 116 SC 116.3.3.3.1 P171 L33 # 335

Mascitto, Marco

Nokia

Comment Type E Comment Status A management intervention (CG)

A value of FAIL will require management intervention. Recommend stating this explicitly.

#### SuggestedRemedy

Add sentence, "Management intervention is required".

Response Response Status C

ACCEPT IN PRINCIPLE.

In the instance, a value of FAIL is likely initiated by the ILT state diagram. Also, since it is stated for "IN\_PROGRESS" and "TRAINING" it is stated "Management intervention is not required." It would to provide complementary guidance for the FAIL value. Also, there is the possibility in some implementations that management intervention is not required.

Add sentence:

"Management intervention might be required."

CI 116 SC 116.3.3.4.1 P172 L8 # 336

Mascitto, Marco

Nokia

Comment Type E Comment Status A management intervention (CG)

A value of FAIL will require management intervention. Recommend stating this explicitly.

#### SuggestedRemedy

Add sentence, "Management intervention is required".

Response Response Status C

ACCEPT IN PRINCIPLE.

The addition statement applies on to the last sentence in this paragraph which implies that ILT is in use. Also, there is the possibility in some implementations that management intervention is not required.

Append the last sentence in the paragraph with "and management intervention might be required."

CI 45 SC 45.2.1.8 P77 L6 # 339

Simms, William

NVIDIA

Comment Type E Comment Status R (bucket) (L)

table 45-12 name vs section header inconsistent with table 45-14 and its section header

#### SuggestedRemedy

change table 45-12 title to Transmit disable register description location

Response Response Status C

REJECT.

The table title "Table 45–12—Transmit disable description location" matches what is in the base standard.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 45 SC 45.2.1.10 P77 L34 # 340  
 Simms, William NVIDIA  
 Comment Type E Comment Status A (bucket) (L)  
 title capitalization difference with table title  
 SuggestedRemedy  
 make 45.2.1.10 "PMA/PMD Extended Ability register" 'or' Table 45-14 "PMA/PMD extended ability register bit definitions"  
 Response Response Status C  
 ACCEPT IN PRINCIPLE.  
 Change table title to be lower case "extended ability".

CI 73 SC 73.11.4.5 P153 L13 # 341  
 Simms, William NVIDIA  
 Comment Type E Comment Status A (bucket) (L)  
 just a sanity check on the wording in quotes in the Value/Comment field of the table  
 SuggestedRemedy  
 should the language in quotes be removed?  
 Response Response Status C  
 ACCEPT IN PRINCIPLE.  
 Remove the text in quotes "Recognized as end of link partner's Next Pages"

CI 118 SC 118.1 P179 L40 # 342  
 Simms, William NVIDIA  
 Comment Type E Comment Status A (bucket) (L)  
 observation that associated clauses are not completely in increasing order  
 SuggestedRemedy  
 note that clause 78 is at bottom of list in table 118-a (and also table 118-b) rather than at top.  
 Response Response Status C  
 ACCEPT IN PRINCIPLE.

Clause 78 was placed at the bottom of Table 118-a and Table 118-b to be consistent with the approach taken in previous projects (Clauses 84, 85, 86, 87, 88, etc). However for the equivalent tables being added in this project, the clauses are now listed in numerical clause order (Clauses 179, 180, 181, 182, etc...) . For consistency it makes sense to reorder Tables 118-a and 118-b in numerical clause order, and do the same for Tables 171-1 and 171-1a.

Reorder Table 118-a and Table 118-b in numerical clause order.

Reorder Table 171-1 and Table 171-1a in numerical clause order.

CI 175 SC 175.2.4.7 P285 L5 # 343  
 Simms, William NVIDIA  
 Comment Type E Comment Status A (bucket) (L)  
 "round robin" instead of "round-robin" used elsewhere in document  
 SuggestedRemedy  
 change "round robin" to "round-robin" also on line 8  
 Response Response Status C  
 ACCEPT.

CI 178 SC 178.9.2.7 P379 L20 # 344

Simms, William NVIDIA

Comment Type E Comment Status A (bucket) (E)

RLcd is defined but RLdc is used for equation and plot

**SuggestedRemedy**

Change RLcd to RLdc in the definition

Response Response Status C

ACCEPT IN PRINCIPLE.  
Change "where RLcd is the differential-mode to common-mode" to "where RLdc is the common-mode to differential-mode"  
Implement in 178.9.2.7 and in 176C.6.3.7, with editorial license.

CI 176c SC 176c.6.3.7 P771 L52 # 346

Simms, William NVIDIA

Comment Type E Comment Status A (bucket) (E)

RLcd is defined but RLdc is used for equation and plot

**SuggestedRemedy**

Change RLcd to RLdc in the definition

Response Response Status C

ACCEPT IN PRINCIPLE.  
Resolve using the response to comment #344

CI 178 SC 178.8.1 P373 L16 # 347

Swenson, Norman Nokia, Point2

Comment Type ER Comment Status A (bucket) (E)

The first sentence starts with "The test points are illustrated..." This implies that these are the only test points. But additional test points are later defined for compliance testing. This can be confusing.

**SuggestedRemedy**

Change "The test points are illustrated..." to "Reference test points are illustrated..." Add a sentence after the first sentence that says "Additional test points for compliance measurement are defined in Section 178.9."

Response Response Status W

ACCEPT IN PRINCIPLE.  
Implement the suggested remedy with editorial license.

CI 176 SC 176.2 P306 L29 # 354

Swenson, Norman Nokia, Point2

Comment Type ER Comment Status A (bucket) (L)

"When the client sublayer is an xAUI-n"... An AUI has never (to my knowledge) been defined as a sublayer, but rather a physical instantiation of a service interface. If we are going to treat it as a sublayer now, we need to formally state that.

**SuggestedRemedy**

Clarify whether we are treating xAUI-n as a sublayer.

Response Response Status W

ACCEPT IN PRINCIPLE.  
The comment correctly points out that the AUI is not defined as a sublayer.  
Change from:  
"When the client sublayer is an xAUI-n, each instance of tx\_symbol and rx\_symbol takes on one of four values..."  
To:  
"When there is an xAUI-n above the PMA, each instance of tx\_symbol and rx\_symbol takes on one of four values..."

Additionally, there are other instances in Clause 176 where an AUI is referred to as a sublayer.  
- 176.3, Page 307, Line 38  
- Fig 176-2, footnotes c and d.

Make changes to all instances in Clause 176 where an AUI is referred to as a sublayer.  
Implement with editorial license.

CI 1 SC 1.3 P54 L44 # 361

Kocsis, Sam Amphenol

Comment Type ER Comment Status A (bucket) (CG)

Reference to OSFP is Revision 5.1, September 12, 2024 is outdated

**SuggestedRemedy**

Update reference to Revision 5.22, August 9, 2025

Response Response Status W

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

---

CI 1 SC 1.3 P54 L51 # 362

Kocsis, Sam Amphenol

Comment Type E Comment Status A (bucket) (CG)

The reference to REF-TA-1011 is normative, but the document itself is informative. There are no direct references to REF-TA-1011 in 802.3dj, and any of the relevant information would be covered in SFF-8665 or SFF-TA-1027, or 1031.

*SuggestedRemedy*

Remove the reference to "REF-TA-1011 Rev 1.1.7, July 11, 2025, Cross Reference to Select SFF Connectors and Modules."

Response Response Status C

ACCEPT.

---

CI 179B SC 179B.4.2 P875 L33 # 366

Kocsis, Sam Amphenol

Comment Type E Comment Status A ket) Test fixture reference (E)

Equation 179B-5, as plotted in Figure 179B-2 provides a reference insertion loss for the mated test fixture, without any context.

*SuggestedRemedy*

Add text, or a note that specifies that Equation 179B-5 is the sum of Equations 179B-1 and 179B-2.

Response Response Status C

ACCEPT IN PRINCIPLE.

Add the following NOTE after the parameter list that follows equation 179B-5:  
NOTE---ILDD\_MTFref is equal to the sum of ILdd\_tref in Equation (179B-1) and ILdd\_catref in Equation (179B-2).

---

CI 179 SC 179.1 P397 L15 # 370

Kocsis, Sam Amphenol

Comment Type E Comment Status A (bucket) Wording (E)

The sentence "Annex 179B specifies test fixtures" implies that the normative annex contains normative requirements for the test fixtures. However, the normative requirements are for the mated test fixtures only, not independent requirements.

*SuggestedRemedy*

Update the sentence to say "Annex 179B specifies the normative requirements for mated test fixtures."

Response Response Status C

ACCEPT IN PRINCIPLE.

179B.1 states that the test fixture are specified, and the parameters measured in mated state create implied specifications for each fixture.

Change "Annex 179B specifies test fixtures" to "Annex 179B includes specifications and reference insertion loss for test fixtures".

---

CI 1 SC 1.1.3.2 P54 L17 # 371

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (CG)

"The 1.6TmII is a logical interconnection intended for use as an intra-chip interface"  
To me "interface" is formal and "interconnection" is practical/implementation.

(Other items that include this statement can be handled in maintenance)

*SuggestedRemedy*

Change to  
"The 1.6TmII is a logical interface intended for intra-chip interconnection".

Response Response Status C

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

---

**Cl 45**      **SC 45**      **P71**      **L**      # **372**

Ran, Adee      Cisco Systems

**Comment Type**    **T**      **Comment Status**    **R**      (withdrawn)

The MDIO interface registers are practically irrelevant in implementations of the PHYs and sublayers defined in this amendment. Configuration is done using software management interfaces that do not necessarily use the same register addresses, and possibly do not use a register map at all.

The functionality required by management is defined by the management variable list in each clause; the mapping to register addresses in clause 45 has no added value.

Maintaining clause 45 is an extremely tedious task and is a waste of editors' and reviewers' time. Eventually, it is likely not read by any user of the standard.

**SuggestedRemedy**

Remove clause 45 and all references to it, including register addresses, from this amendment.

**Response**      **Response Status**    **Z**

REJECT.

This comment was WITHDRAWN by the commenter.

---

**Cl 73**      **SC 73.6.1.1**      **P139**      **L2**      # **373**

Ran, Adee      Cisco Systems

**Comment Type**    **E**      **Comment Status**    **A**      (bucket) (L)

The text of this clause includes "will" twice, and in both cases it seems like a normative requirement (so should be "shall").

There are several other instances of "will" in the document; they should be checked for compliance with the SA style manual ("will is only used in statements of fact") and changed if necessary. The suggested remedy lists some instances, and excludes instances for which I checked that "will" is appropriate.

**SuggestedRemedy**

Change "will" to "shall" twice in this subclause.

Check (and correct if necessary, e.g. to "is" or variants) other instances of "will" in clauses 73, and in 177.4.6, 177.5.2, 180.10.4, 184.4.9, 185.10.4, 186.2.3.3, 186.2.3.5.9, 186.2.3.8, 186.2.4.7.5, 187.10.4, 174A.10.

**Response**      **Response Status**    **C**

ACCEPT IN PRINCIPLE.

The style manual states the following: "The word will is deprecated and shall not be used when stating mandatory requirements; will is only used in statements of fact."

The two "will"s mentioned in 73.6.1.1 along with the one in 73.6.1.2 are in the base standard and so should be left as is.

The "will"s in 177.4.6, 177.5.2, 186.2.3.3 are statements of fact, so should remain.

The "will"s in 186.2.3.5.9 and 186.2.3.8 have been reviewed and are considered to be correct as written.

In 174A.10 the "will"s are consequences and should remain.

In 186.2.4.7.5 change "will need" to "are".

In 180.10.4, 185.10.4, and 187.10.4 change "will be met" to "are met".

The "will"s in in 184.4.9 delete the word "will".

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 119 SC 119.3.4a P187 L4 # 374

Ran, Adeo Cisco Systems

Comment Type T Comment Status A (bucket) (L)

The new counter is optional. The text says "The following optional counter may be implemented for these PHY types" followed by a list of PHYs - but obviously it is permitted ("may equals is permitted to") to implement the counter in any PCS; the same PCS can be part of different PHYs (e.g. depending on the module type). So the restricted list does not make sense.

Removing the restriction would make the counter simply optional. Adding an optional feature to an existing specification is not a violation of scope - it has been done before (e.g., EEE, TimeSync) and we are doing similar things in this project (e.g. adding optional stateless encoder and decoder).

Similarly for 119.3.4b FEC\_codeword\_error\_bin\_i

#### SuggestedRemedy

Change "The following optional counter may be implemented for these PHY types:" to "The following counter is optional".

Implement similar change in 119.3.4b.

Response Response Status C

ACCEPT.

CI 175 SC 175.3 P293 L40 # 377

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (L)

"FEC degrade detection is specified in 175.2.5.3. FEC degrade detection is optional." 175.2.5.3 does not specify FEC degrade detection; it only changes the definition of the counters (and thus modifies the criteria for detection). This subclause is the specification of the Reed-Solomon decoder, and it refers to the original specification in 119.2.5.3 - that is where FEC degrade is actually defined. A direct reference would be friendly for the reader.

#### SuggestedRemedy

Change to "FEC degrade detection is specified in 119.2.5.3 with the exception listed in 175.2.5.3. FEC degrade detection is optional."

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement the suggested remedy with editorial license.

[Editor's note: changed page from 287 to 293]

CI 175 SC 175.3 P293 L34 # 378

Ran, Adeo Cisco Systems

Comment Type E Comment Status R (bucket) (L)

FEC degrade is part of the PCS functionality. It should be under 175.2 PCS functions. Similarly for Loopback in 175.4.

#### SuggestedRemedy

Move 175.3 and 175.4 to become subclauses of 175.2.

Response Response Status C

REJECT.

The whole clause is the definition of the PCS functionality. Subclause 175.2 describes the PCS top-level interfaces and TX and RX data manipulations mainly for "normal flow" of data.". Loopback functionality does not fall into this category for 175.2 and should remain as a separate subclause at the same level as 175.2 (as is also done in other PCS clauses such as 119 and 172). FEC degrade has a portion that is performed in the TX path and a portion that is performed in the RX path, and these are described in 172.2.2 (TX functionality) and 172.2.3 (RX functionality). Subclause 175.3 is used at this level to tie the two parts of the FEC degrade feature together and act as an anchor for other clauses to reference.

CI 178 SC 178.8.1 P373 L33 # 379

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (E)

"ILT" is a very general term. The block diagram in Figure 178-2 shows the ILT function, part of the PMD functional specification. It would better be labeled "ILT function", to match the other PMD blocks (receive and transmit).

Also in 179.8.1, Figure 179-2.

#### SuggestedRemedy

Change "ILT" to "ILT function", twice, in Figure 178-2 and Figure 179-2.

Response Response Status C

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178 SC 178.9.2 P375 L15 # 381

Ran, Adeo Cisco Systems

Comment Type T Comment Status A est equipment impedance (E)

Slide 12 of [https://www.ieee802.org/3/dj/public/25\\_07/ran\\_3dj\\_01c\\_2507.pdf](https://www.ieee802.org/3/dj/public/25_07/ran_3dj_01c_2507.pdf) (used for resolution of several comments against D2.0) says "Specify that transmitter time-domain measurements are made with a 50  $\Omega$  single-ended load".  
This is not stated explicitly in Clause 178, nor in Annex 178C. It is especially important now that the reference impedance is changed.  
The text about transmitter measurement should be unified.

#### SuggestedRemedy

In 178.9.2, change the second paragraph to  
"Unless specified otherwise, transmitter signal measurements are made for each lane separately using a fourth-order Bessel-Thomson low-pass response with a 3 dB bandwidth of 60 GHz, with AC-coupled connection from TP0v to 50  $\Omega$  single-ended loads in the test equipment."

In 176C.6.3, replace the existing two paragraphs with the three paragraph in 178.9.2, including the change above.

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement the suggested remedy with editorial license.

CI 178 SC 178.9.3.3 P380 L44 # 382

Ran, Adeo Cisco Systems

Comment Type T Comment Status A t) RX amplitude tolerance (E)

In D2.1 the receiver amplitude tolerance text has been expanded in clause 179, and now the text in clause 178 and Annex 176C does not match it.  
The requirement is essentially the same so the text should be similar (with perhaps different references).

#### SuggestedRemedy

Change the text in 178.9.3.3 and in 176C.6.4.2 to match the text in 179.9.5.2.

Response Response Status C

ACCEPT.

CI 178 SC 178.9.3.4.2 P381 L52 # 383

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) ITOL (E)

in "J4u03" the "u" should not be in subscript.

#### SuggestedRemedy

Change to normal text.

Response Response Status C

ACCEPT.

CI 178 SC 178.10. P384 L28 # 387

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (E)

"the channel is bound by TP0 and TP5"

"bound" does not seem natural here.

Also in 176C.7.

#### SuggestedRemedy

Change to "The channel is defined between TP0 and TP5" or alternatively "The channel is delimited by TP0 and TP5".  
Apply a similar change in 176C.7.

Response Response Status C

ACCEPT IN PRINCIPLE.  
Change to "The channel is defined between TP0 and TP5".  
Also, apply to 176C.7.

CI 178 SC 178.10. P384 L36 # 388

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (E)

"Tp0d to Tp5d" - P should be uppercase

#### SuggestedRemedy

Change to "TP0d to TP5d"

Response Response Status C

ACCEPT.



## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178 SC 178.10. P384 L45 # 389

Ran, Adeo Cisco Systems

Comment Type TR Comment Status A (bucket) (E)

In Table 178–11, maximum AC coupling frequency of 100 kHz does not match the value in referenced subclause, which was changed to 250 kHz.

In Table 176C-6, the value is 50 kHz, not matching the reference either.

#### SuggestedRemedy

Change to 250 kHz in Table 178–11 and in Table 176C–6.

Response Response Status W

ACCEPT.

CI 178 SC 178.10. P384 L47 # 390

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (E)

Missing reference for SCMR\_CH.

#### SuggestedRemedy

Add a reference to 179.11.8 (or another place if the location of the definition changes).

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #251.

CI 178 SC 178.10.1 P386 L6 # 391

Ran, Adeo Cisco Systems

Comment Type TR Comment Status A (et) Reference Impedance (E)

In Table 178-12, R0 should be 46.25 Ohm (Slide 12 of [https://www.ieee802.org/3/dj/public/25\\_07/ran\\_3dj\\_01c\\_2507.pdf](https://www.ieee802.org/3/dj/public/25_07/ran_3dj_01c_2507.pdf)).  
Also in Table 176C–7.

#### SuggestedRemedy

Change per comment (2 places).

Response Response Status W

ACCEPT.

CI 179 SC 179.8.1 P405 L21 # 394

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (E)

In Figure 179-2, the demarcation lines of PMD, Cable assembly, and PMD should be at the bottom of the diagram (below the newly-introduced "ILT" blocks).

#### SuggestedRemedy

Change the diagram per the comment.

Response Response Status C

ACCEPT.

CI 179 SC 179.9.4 P408 L8 # 395

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (E)

Article mismatch in "to a 50  $\Omega$  single-ended loads".

#### SuggestedRemedy

Delete "a".

Response Response Status C

ACCEPT.

CI 179 SC 179.11.8 P433 L40 # 396

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (cket) Document structure (E)

The new SCMR\_CH specification is relevant for all electrical channels, not just to cable assemblies. Its location under 179.11 is not ideal, and it is possible that other electrical channel specifications will also include this parameters.  
Annex 178A, titled "Specification methods for 200 Gb/s per lane electrical channels", is a more appropriate place.

#### SuggestedRemedy

Move the content of 179.11.8 to a new subclause 178A.2.  
Update the existing reference in Table 179–14 accordingly.

Response Response Status C

ACCEPT IN PRINCIPLE.

CI 180 SC 180.7.1 P453 L31 # 399

Ran, Adeo Cisco Systems

Comment Type TR Comment Status A Jitter for optical interface (CO)

Clock jitter, especially at low frequencies, is not captured adequately by existing optical PMD transmitter specifications, and should be limited by separate specifications to avoid correlated errors in receivers that would degrade link performance.

Methods for jitter measurements are available in oscilloscopes and are used successfully in electrical transmitters. The same methods can be used for optical transmitters.

Note that jitter measurement is faster than a "functional receiver" test, and is more reliable, because the CRU bandwidth in oscilloscopes scope is tightly controlled.

A presentation with measured data in a controlled experiment, demonstrating that high jitter levels significantly degrade FEC performance while having an insignificant effect on TDECQ, will be provided.

This specification should apply to transmitters in all IM-DD PMDs.

#### SuggestedRemedy

In Table 180-7, add an "Output jitter" row with parameters and units as in Table 176D-3 (module output specifications at TP4). For maximum values, use the values in 176D-3 except that J4u03 is increased by 10% (relaxed) to account for higher measurement noise.

In Table 180-14, add a new test pattern 8, PRBS9Q, defined in 176.7.4.4.

In Table 180-14, add an "Output jitter" row with pattern 4, 6, or 8, and reference to 180.9.14 (new subclause).

Add a new subclause 180.9.14 for Output jitter. The content is to be taken from 176D.8.9, with additional exceptions:

- transmit equalizer is fixed
- when the PHY includes an xAUI-n, the clock source for the test pattern is derived from the clock recovered from the xAUI-n input signal.

Implement similarly in clauses 181, 182, and 183, as appropriate.

Response Response Status C

ACCEPT IN PRINCIPLE.

The following contribution was reviewed by the task force:  
[https://www.ieee802.org/3/dj/public/25\\_09/ran\\_3dj\\_04\\_2509.pdf](https://www.ieee802.org/3/dj/public/25_09/ran_3dj_04_2509.pdf)

Based on the results of straw poll TF-2 there is sufficient consensus make the proposed changes.

Implement the suggested remedy with editorial license.

Straw poll TF-1 (directional)

I support adopting the suggested remedy in comment #399.

Yes: 22

No: 6

NMI: 14

Abstain: 19

Straw poll TF-2 (decision)

I support closing comment #399 adopting the suggested remedy in comment #399.

Yes: 22

No: 17

Abstain: 20

CI 184 SC 184.1.2 P568 L31 # 403

Ran, Adeo Cisco Systems

Comment Type T Comment Status R (bucket) (L)

Figure 184-1 shows the Inner FEC sublayer directly below the PCS. However, Figure 184-2 indicates that the sublayer above can also be a PMA (two specific types). While theoretically the PCS can be connected directly, as in Figure 184-1, it is likely not the implementation most people have in mind.

#### SuggestedRemedy

In Figure 184-1 add a box for the PMA, with a footnote that it is optional and limited to the 800GBASE-R 8:32 PMA or 800GBASE-R 4:32 PMA (to match Figure 184-2).

Response Response Status C

REJECT.

The only time a PMA is above the Inner FEC is when an AUI C2M is present. That will probably be the case for most implementations of 800GBASE-LR1. But it's the same case for all implementations of IMDD PHYs, and we have historically not included AUIs in these introductory figures. This figure is consistent with similar PHY types defined in the base standard.

CI 184 SC 184.1.3 P569 L11 # 404

Ran, Adeo Cisco Systems

Comment Type TR Comment Status R (withdrawn)

Following up on comments #418 and #419 against D2.0.

The inner FEC sublayer should have a way to relay the "RTS" status from the PMA above it to the link partner and vice versa. This could be achieved by enabling/disabling the coherent transmitter output, but alternative methods that keep the transmitter active may be preferable.

#### SuggestedRemedy

A presentation with a detailed proposal will be provided.

Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

---

**CI 184**      **SC 184.2**                      **P570**      **L6**                      # **405**

Ran, Adee                                      Cisco Systems

**Comment Type**    **TR**                      **Comment Status**    **R**                                      (withdrawn)

The service interface in Figure 184–2 does not include an IS\_SIGNAL.request primitive, although the PCS and PMA can generate this primitive to the service interface below them. This primitive is required if ILT is to be included; until then, it can be included with a statement that it has no effect.

**SuggestedRemedy**

Add a FEC:IS\_SIGNAL.request primitive in Figure 184–2 and add text as necessary in 184.2 and 184.3 (examples can be taken from clause 177).  
Implement with editorial license.

**Response**                                      **Response Status**    **Z**

REJECT.

This comment was WITHDRAWN by the commenter.

---

**CI 186**      **SC 186,2,1**                      **P619**      **L4**                      # **406**

Ran, Adee                                      Cisco Systems

**Comment Type**    **TR**                      **Comment Status**    **R**                                      (withdrawn)

The service interface in Figure 186–3 does not include an IS\_SIGNAL.request primitive, although the PCS and PMA above the FEC can generate this primitive to the service interface below them.  
This primitive is required if ILT is to be included; until then, it can be included with a statement that it has no effect.

**SuggestedRemedy**

Add a FEC:IS\_SIGNAL.request primitive in Figure 186–3 and add text as necessary in 186.2.2 (examples can be taken from clause 177).  
Implement with editorial license.

**Response**                                      **Response Status**    **Z**

REJECT.

This comment was WITHDRAWN by the commenter.

---

**CI 186**      **SC 186.1.2**                      **P617**      **L31**                      # **408**

Ran, Adee                                      Cisco Systems

**Comment Type**    **T**                                      **Comment Status**    **R**                                      (bucket) (L)

Figure 186–1 shows the FEC sublayer directly below the PCS. However, Figure 186–2 and Figure 186–3 indicate that the sublayer above can also be a PMA (two specific types). While theoretically the PCS can be connected directly, as in Figure 186–1, it is likely not the implementation most people have in mind.

**SuggestedRemedy**

Figure 186–1 add a box for the PMA, with a footnote that it is optional and limited to the 800GBASE-R 8:32 PMA or 800GBASE-R 4:32 PMA (to match Figure 186–2).

**Response**                                      **Response Status**    **C**

REJECT.

The only time a PMA is above the Inner FEC is when an AUI C2M is present. That will probably be the case for most implementations of 800GBASE-ER1 and 800GBASE-ER1-20. But it's the same case for all implementations of IMDD PHYs, and we have historically not included AUIs in these introductory figures. This figure is consistent with similar PHY types defined in the base standard.

---

**CI 186**      **SC 186.2.1**                      **P618**      **L48**                      # **409**

Ran, Adee                                      Cisco Systems

**Comment Type**    **TR**                      **Comment Status**    **R**                                      (withdrawn)

The 800GBASE-ER1 FEC sublayer should have a way to relay the "RTS" status from the PCS/PMA above it to the link partner and vice versa. This could be achieved by enabling/disabling the coherent transmitter output, but alternative methods that keep the transmitter active may be preferable.

**SuggestedRemedy**

A presentation with a detailed proposal will be provided.

**Response**                                      **Response Status**    **Z**

REJECT.

This comment was WITHDRAWN by the commenter.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 174A SC 174A.8.3 P720 L16 # 410

Ran, Adeo Cisco Systems

Comment Type T Comment Status A (bucket) (CG)

174A includes many instances of "histogram". This term is potentially misleading for readers because its typical meaning uses counts, not probabilities.  
To avoid going into more precise but less common mathematical terms, I suggest (based on <https://www.itl.nist.gov/div898/handbook/eda/section3/histogra.htm>) using the term "Relative histogram". To minimize disruption to the text, the existing term can be retained, but a clarification should be provided.

#### SuggestedRemedy

Add the following informative NOTE after the first paragraph of 174A.8.3:  
NOTE--Within this annex, the term "histogram" denotes an array that holds values normalized such that the sum of the values is one. This is sometimes referred to as a relative histogram.

Response Response Status C

ACCEPT.

CI 176C SC 176C.7.3 P781 L1 # 412

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (E)

Stray space in "an d"

#### SuggestedRemedy

Change to "and".

Response Response Status C

ACCEPT.

CI 176C SC 176C.7 P781 L17 # 413

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (E)

The references for RLcd and for maximum AC-coupling frequency point to 176C.7.4 and 176C.7.5, which in turn point to subclauses of clause 178 with no modification.  
There are other references pointing directly to clause 178. The chain of references can be eliminated here too.  
(ILdd and ERL are exceptions; these specifications have different values or parameters).

#### SuggestedRemedy

Replace the references in these rows to point directly at the specifications in clause 178, and delete the subclauses in this annex.

Response Response Status C

ACCEPT.

CI 178B SC 178B.2 P835 L22 # 414

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (CI)

"Through this communication, ILT creates a well-defined path start-up process for paths that include one or more ISLs"  
The path start-up protocol in 178B.6 should be referenced.

#### SuggestedRemedy

Add "(see 176B.6)" in this sentence and reword if necessary with editorial license.

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement suggested remedy with editorial license.

CI 178B SC 178B.2 P835 L23 # 415

Ran, Adeo Cisco Systems

Comment Type E Comment Status A (bucket) (CI)

"Initially all ISLs are in TRAINING mode"  
It is the AUIs or AUI components that are in TRAINING mode.

#### SuggestedRemedy

Reword as necessary with editorial license.

Response Response Status C

ACCEPT IN PRINCIPLE.  
Resolve using the response to comment #320.

CI 178B SC 178B.5.1.2 P839 L38 # 417

Ran, Adeo Cisco Systems

Comment Type TR Comment Status A Path (CI)

Based on straw poll results and discussion in the Annex 178B ad hoc, there is consensus that the path start-up protocol should span the path that includes the two Physical Layer implementations (MAC to MAC), including extenders. For this purpose, the exchange of information (e.g., RTS) between PHY XS and the PCS across the xMII should be defined.

#### SuggestedRemedy

A presentation with a detailed proposal will be provided.

Response Response Status C

ACCEPT IN PRINCIPLE.

The following contribution was reviewed by the CRG:  
[https://www.ieee802.org/3/dj/public/25\\_09/ran\\_3dj\\_03\\_2509.pdf](https://www.ieee802.org/3/dj/public/25_09/ran_3dj_03_2509.pdf)

Implement the proposal on slides 11 to 13 in ran\_3dj\_03\_2509 with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 175 SC 175.2.5.7 P288 L53 # 423

Nicholl, Shawn

AMD

Comment Type T Comment Status A (bucket) (L)

Currently, there is a note (in 175.2.4.3) for mapping to OTN. But no corresponding note for demapping from OTN.

#### SuggestedRemedy

At the end of "175.2.5.7 Block collection", add "Note -- The stream of 257-bit blocks generated by this process is used as the reference signal for de-mapping from OTN."

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement the suggested remedy with editorial license.

CI 180 SC 180.1 P443 L38 # 433

Nicholl, Gary

Cisco Systems

Comment Type TR Comment Status A (bucket) AUI (O)

In Table180-1, footnote c also applies to 200GAUI-2 C2C and 200GAUI-2 C2M. When implemented in a 200GBASE-DR1 PHY the signalling rate of these AUIs must also be constrained as defined in 120.1.4 (i.e. to 50ppm).

Same comment for Table 180-2..

#### SuggestedRemedy

Update Table 180-1 and Table 180-2 , to add footnote c to 200GAUI-2 C2C and 200GAUI-2 C2M (Table 180-1) and 400GAUI-4 C2C and 400GAUI-4 C2M (Tabe 180-2).

Response Response Status W

ACCEPT IN PRINCIPLE.

CI 182 SC 182.1 P505 L39 # 434

Nicholl, Gary

Cisco Systems

Comment Type TR Comment Status A (bucket) AUI (O)

In Table 182-1, footnote c also applies to 200GAUI-2 C2C and 200GAUI-2 C2M. When implemented in a 200GBASE-DR1-2 PHY the signalling rate of these AUIs must also be constrained as defined in 120.1.4 (i.e. to 50ppm).

Same comment for Table 182-2.

#### SuggestedRemedy

Update Table 182-1 and Table 182-2 , to add footnote c to 200GAUI-2 C2C and 200GAUI-2 C2M (Table 182-1) and 400GAUI-4 C2C and 400GAUI-4 C2M (Tabe 182-2).

Response Response Status W

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #433.

CI 180 SC 180.5.2 P450 L48 # 435

Nicholl, Gary Cisco Systems

Comment Type T Comment Status A ILT (CI)

With respect to the sentence "When operating in TRAINING mode, the PAM4 symbol stream on each lane is taken from the output of the training pattern generator in the PMD control function (see Figure 178B.4)" It is not clear what "lane" is referring to in this sentence. Is it the .PMD:IS\_UNITDATA\_i.request input lane from the service interface, or does it mean the SLi lane at the output of the PMD transmit function? Also the sentence refers to a "training pattern generator in the PMD control function (See Figure 178B.4)". There is no "PMD control function" shown in either Figure 180-2 or in Figure 178B-2? The term "PMD control function" does appear anywhere else in clause 180 or in 178B. Is the "training pattern generator" assumed to part of the "PMD transmit Function" block in Figure 180-2 or the "per-lane ILT function block" in Figure 178B-2

It sounds like in training mode a PAM4 signal from a training pattern generator (located somewhere) is converted to an optical signal and delivered to the MDI?

#### SuggestedRemedy

Change from:

"When operating in TRAINING mode, the PAM4 symbol stream on each lane is taken from the output of the training pattern generator in the PMD control function (see Figure 178B.4)." to:

"When operating in TRAINING mode, each source lane of the MDI (SLi) is replaced with a PAM4 optical symbol stream derived from a training pattern generator (add a reference here)"

An alternative approach would be to simplify both paragraphs along the lines of:  
"When operating in DATA mode, the PMD Transmit Function converts a symbol stream from PMD:IS\_UNITDATA\_i to a corresponding optical signal on source lane SLi on the MDI."

When operating in TRAINING mode, the PMD Transmit Function converts a PAM4 symbol stream from a training pattern generator (add reference here) to a corresponding optical signal on each source lane SLi on the MDI"

Make similar and appropriate changes to 181.5.2, 182-2.5.2, 183.5.2.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change "PMD control function" to "ISL training function" to match the subclause title (178B.5).

Update the reference from "Figure 178B.4" to "(see 178B.5 and Figure 178B-5)".

Apply in other PMD and AUI clauses where appropriate.

Implement with editorial license.

CI 180 SC 180.6 P452 L43 # 436

Nicholl, Gary Cisco Systems

Comment Type T Comment Status R (bucket) MDI (O)

This is more of a question for clarification. I wanted to clarify that this subclause is only assigning optical lanes at the MDI. It is not attempting to place any restriction on the mapping between electrical lanes (on the AUI-n) and optical lanes at the MDI?

The whole point of the MLD based PCS is to allow both host and module implementors flexibility in the routing and mapping of both electrical and optical lanes.

#### SuggestedRemedy

Clarify that we are not placing any restrictions on the mapping between electrical lanes from the AUI-n to optical lanes on the MDI.

Response Response Status C

REJECT.

There could be a gearbox between the AUI and the optical PMD, therefore, it is not necessarily a one-to-one relation. However, the suggested remedy does not provide sufficient detail to implement.

CI 179B SC 179B.3.1 P874 L19 # 442

Dudek, Mike Marvell

Comment Type T Comment Status A (bucket) Test points (E)

The cable assembly test fixture includes the connector, vias, etc.

#### SuggestedRemedy

Delete "PCB" from "test fixture PCB reference"

Response Response Status C

ACCEPT IN PRINCIPLE.

The comment identifies an inconsistency in the nomenclature. However, the text fixture should be referenced correctly.

Change "test fixture PCB reference" to "cable assembly test fixture reference".

Update the details of the structures included in the cable assembly test fixture in the text of 179B.3.1.

Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI **179B** SC **179B.3.1** P**874** L**15** # **443**  
Dudek, Mike Marvell  
Comment Type **TR** Comment Status **A** (ket) Test fixture reference (E)  
Equation 179B-2 leads to -34.26dB at 53GHz. An obvious problem as the value per figure 179A-1 should be 5.95dB  
SuggestedRemedy  
Change the 0.841f to 0.0841f  
Response Response Status **W**  
ACCEPT IN PRINCIPLE.  
The comment identifies an editorial error in translating the equation for D2P1. There are technical implications with the error, but the suggested remedy provides the right corrective action.  
Implement the suggested remedy.

CI **FM** SC **Front Matter** P**13** L**12** # **447**  
Dudek, Mike Marvell  
Comment Type **T** Comment Status **A** (bucket) (CG)  
The clause # is not included.  
SuggestedRemedy  
Make it Clause 168.  
Response Response Status **C**  
ACCEPT.

CI **180** SC **180.9.7** P**464** L**31** # **449**  
Dudek, Mike Marvell  
Comment Type **T** Comment Status **A** (bucket) (O)  
Confusion between codeword and test block. The test is performed with PRBS31Q so codeword is not appropriate.  
SuggestedRemedy  
Change "single codeword" to "single test block".  
Response Response Status **C**  
ACCEPT.

CI **174A** SC **174A.12** P**727** L**34** # **451**  
Dudek, Mike Marvell  
Comment Type **T** Comment Status **A** (bucket) (CG)  
The PMD link BER is wrong in figures , 174A-9. and a74A-10. The BERs do not add correctly to the PCS-to-PCS path allocation. It is stated correctly as 2.28e-4 in Table 174A-1.  
SuggestedRemedy  
Change "2.76e-4" to "2.24e-4" in these two figures.  
Response Response Status **C**  
ACCEPT IN PRINCIPLE.  
Table 174A-1 specifies BER of 2.28E-4 for the PMD link.  
In Figure 174A-9 and Figure 174A-10 change the PMD link BER allocation to 2.28E-4.  
[Editor's note: Changed line from 14 to 34]

CI **178B** SC **178B.5** P**837** L**41** # **452**  
Slavick, Jeff Broadcom  
Comment Type **TR** Comment Status **A** ILT (CI)  
The bullets describing the path start-up process is too wordy and confusing.  
SuggestedRemedy  
Update 178B.5.1 to read as follows:  
ILT on each interface operates with the following behavior:  
- Each lane of ISL begin in TRAINING mode or by sending a local data pattern (when TRAINING is not supported or disabled).  
- Each lane of the ISL independently achieve local\_rx\_ready indicating that lane has completed its adaptation processes and is ready to move to DATA mode.  
- Each ISL achieves local\_rts indicating all lanes of the AUI/PMD are ready to move to DATA mode.  
- Each ISL achieves remote\_rts indicating adjacent AUI/PMDs are ready to move to DATA mode.  
- When local\_rts and remote\_rts are both true it means all ISLs in the Path are ready to move to DATA mode.  
- When all ISLs have switched to DATA mode then communication on the Path is established.  
Response Response Status **C**  
ACCEPT IN PRINCIPLE.  
It would be good to make this description more concise.  
Update the description based on the suggested remedy with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 119 SC 119.2.5.3 P185 L11 # 455

Slavick, Jeff

Broadcom

Comment Type TR Comment Status A (bucket) (L)

Error marking needs to be more explicit about corrupting which 66b blocks following an uncorrected codeword are the ones from the same decoder. In 800G and 1.6T those could be later in the flow of 66-bit blocks at the MII interface and not the ones directly after 66-bit blocks from the uncorrectable block.

*SuggestedRemedy*

Change:  
then the first four 66-bit blocks following the uncorrected codewords shall also be set to an error block.

To:  
then the first four 66-bit blocks of the following set of two associated codewords processed by the Reed-Solomon decoder shall also be set to an error block.

Response Response Status W

ACCEPT IN PRINCIPLE.

Change:  
"... then the first four 66-bit blocks following the uncorrected codewords shall also be set to an error block."

To:  
"... then the first four 66-bit blocks from the next two associated codewords processed by the Reed-Solomon decoder shall also be set to an error block to account for the possible error propagation by the descrambler."

Implement with editorial license.

CI 174A SC 174A.8.2 P720 L6 # 456

Slavick, Jeff

Broadcom

Comment Type TR Comment Status R (bucket) (CG)

optical clauses are using block error ratio methods in the "receiver functional test". In 174A8.2 we talk about splitting the data based "p physical lanes". But for example in FR4 there's only one physical lane (fiber) but you have the data flowing over multiple lanes (wavelengths) in that single physical lane.

*SuggestedRemedy*

remove the word physical

change physical to input/output

Response Response Status W

REJECT.  
For WDM duplex PMD types, each wavelength is a physical lane.  
As an example, the overview in 183.1 says that for 800GBASE-FR4 and 800GBASE-LR4 "The PMDs provide point-to-point 800 Gb/s Ethernet links over four wavelength division multiplexing (WDM) lanes on single-mode fiber". It never refers to the fiber as being a lane.

CI 45 SC 45.2.1 P71 L48 # 457

Slavick, Jeff

Broadcom

Comment Type TR Comment Status A (bucket) (L)

Time Sync Inner FEC or ER1 is not the sub clause title

*SuggestedRemedy*

Remove "TimeSync Inner FEC or ER1" from the two rows in Table 45-3 at lines 48 and 49

Response Response Status W

ACCEPT IN PRINCIPLE.  
Replace "TimeSync Inner FEC or ER1 FEC" with "TimeSync FEC"

CI 45 SC 45.2.1.175 P97 L42 # 458

Slavick, Jeff

Broadcom

Comment Type TR Comment Status A (bucket) (L)

This clause now includes Inner FEC/ER1 FEC.

*SuggestedRemedy*

Update PMA/PMD to FEC/PMA/PMD in the sub-clause title and text and references to this sub-clause (e.g. Table 45-3)

Response Response Status W

ACCEPT.



## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

---

CI 30 SC 30.5.1.1.4 P64 L0 # 460  
Slavick, Jeff Broadcom  
Comment Type TR Comment Status A (bucket) (L)  
The data rates 800G & 1.6T needs to be added to the behavior.  
SuggestedRemedy  
Add 800Gb/s and 1.6Tb/s to the seventh paragraph for the behavior of aMediaAvailable.  
Response Response Status W  
ACCEPT.

---

CI 30 SC 30.5.1.1.12 P64 L0 # 461  
Slavick, Jeff Broadcom  
Comment Type TR Comment Status A (bucket) (L)  
The data rates 800G & 1.6T needs to be added to the behavior.  
SuggestedRemedy  
Add 800Gb/s and 1.6Tb/s to the behavior of aLaneMapping  
Response Response Status W  
ACCEPT.

---

CI 30 SC 30.5.1.1.17 P64 L0 # 462  
Slavick, Jeff Broadcom  
Comment Type TR Comment Status A (bucket) (L)  
The data rates 800G & 1.6T needs to be added to the behavior. Also to 30.5.1.1.18  
SuggestedRemedy  
Add 800Gb/s and 1.6Tb/s to the behavior of aFECCorrectedBlocks and aFECUncorrectedBlocks  
  
In the SYNTAX sections the increment rate for 800Gb/s would be 160 000 000 and 320 000 000 for 1.6T/s  
In the BEHAVIOR sections add 800 to list of xxxGBASE-R PHYs and in 1.6TBASER PHYs to the list as well.  
Response Response Status W  
ACCEPT.

---

CI 178B SC 178B.2 P835 L23 # 464  
Slavick, Jeff Broadcom  
Comment Type TR Comment Status A (bucket) (CI)  
When you use local pattern you don't enter "TRAINING mode".  
SuggestedRemedy  
Change "TRAINING mode," to "a tx mode (see 178B.5)"  
Response Response Status W  
ACCEPT IN PRINCIPLE.  
Resolve using the response to comment #320.

---

CI 178B SC 178B.2 P835 L27 # 465  
Slavick, Jeff Broadcom  
Comment Type T Comment Status A (bucket) (CI)  
ILT defines the training protocol not really includes.  
SuggestedRemedy  
Change "includes" to "defines"  
Response Response Status C  
ACCEPT IN PRINCIPLE.  
Resolve using the response to comment #320.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 116 SC 116.3.3.4.1 P172 L5 # 466

Slavick, Jeff Broadcom

Comment Type T Comment Status A (bucket) service interface (CG)

FAIL status is the state presented if none of the other states apply. The text states that FAIL is when communication is not established. But the states of IN\_PROGRESS and READY would meet that FAIL criteria too as they have yet to establish communication.

#### SuggestedRemedy

Change "or has not established communication"  
To "or is unable to establish communication"

Response Response Status C

ACCEPT IN PRINCIPLE.

In contrary to the comment, "READY" is defined indicating "that communication with the next higher sublayer is established but communication with an upper ISL has not completed".

"IN\_PROGRESS" is defined as indicating "that the sublayer is establishing communication with the next higher sublayer" and thus communication is not established. So there is some ambiguity here.

The distinction is that the attempt to establish communication was unsuccessful.

On page 172 line 5...

Change "or has not established communication"  
To "or is unable to establish communication"

CI 178B SC 178B.5.1.1 P838 L32 # 469

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (CI)

The transmit clock functional mode may not be based upon the PCS clock. It may based on DTE XS or PHY XS or not ever change.

#### SuggestedRemedy

Change:

As shown in the RTS control state diagram (Figure 178B-9) local\_rts is set to true only after the transmit clock is derived from the PCS clock, such that the transition between clock sources occurs while sending local\_rts = false.

To:

As shown in the RTS control state diagram (Figure 178B-9) local\_rts is set to true only after the transmit clock is derived from its mission mode source (local\_rts is false when a transition between clock sources occurs).

Response Response Status W

ACCEPT IN PRINCIPLE.

Change: "local\_rts is set to true only after the transmit clock is derived from the PCS clock"  
To: "local\_rts is set to true only after the transmit clock is derived from the clock recovered by the other interface receiver"

CI 178B SC 178B.5.1.2 P839 L38 # 470

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (CI)

Which same process? The Retimer process?

#### SuggestedRemedy

Remove 178B.5.1.2 there is no need to call out anything special here.

Response Response Status W

ACCEPT IN PRINCIPLE.

Remove the colon after "process" to make clear to which process the text refers.

CI 178B SC 178B.3 P836 L30 # 471

Slavick, Jeff Broadcom

Comment Type TR Comment Status A Path (CI)

Add "path" to the drawing, which per 1.4 is defined as "The sequence of segments and repeaters providing the connectivity between two DTEs in a single collision domain. In CSMA/CD networks there is one and only one path between any two DTEs."

#### SuggestedRemedy

Insert a "| <----->|" at the bottom of Figure 178B-1 which begins at the left edge of the DTE XS and ends at the right edge of the rightmost PCS box. With the word "path" below the line.

Response Response Status C

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #417.

CI 178B SC 178B.5.2.2 P841 L1 # 472

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (CI)

Only interfaces that use training mode need to specify which training format they use.

#### SuggestedRemedy

Change:

Each interface using ILT shall identify which format is relevant for it.

To:

Each interface using ILT that supports TRAINING mode shall specify which format it uses.

Response Response Status W

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #20.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.5.2.3 P841 L14 # 473  
 Slavick, Jeff Broadcom  
 Comment Type T Comment Status A (bucket) (CI)  
 The "(see Figure 178B-5)" is not needed at the end of the 3rd paragraph  
 SuggestedRemedy  
 Remove "(see Figure 178B-5)" from the end of the 3rd paragraph  
 Response Response Status C  
 ACCEPT.

CI 178B SC 178B.5.3 P845 L28 # 474  
 Slavick, Jeff Broadcom  
 Comment Type TR Comment Status A (bucket) (CI)  
 Lost the heading for "Initial condition request".  
 SuggestedRemedy  
 Restore the heading for "Initial condition request". It's been converted to a Figure title.  
 Response Response Status W  
 ACCEPT IN PRINCIPLE.  
 Resolve using the response to comment #23.

CI 178B SC 178B.5.4.2 P847 L40 # 475  
 Slavick, Jeff Broadcom  
 Comment Type TR Comment Status A (bucket) (CI)  
 local\_tp\_mode was moved from the State variables definition even though it's used in Figure 178B-8. But others that are also encoded in the status frame did not have their variable definitions move the status frame bit descriptions (like cf\_sts or coef\_sel).  
 SuggestedRemedy  
 Move the definitions of local\_tp\_mode and local\_mc\_mode back to 178B.7.3.1 and add "(see 178B.7.3.1)" to the end of the sentence in 178B.5.4.2 and 178B.5.4.3  
 Response Response Status W  
 ACCEPT IN PRINCIPLE.  
 Implement suggested remedy with editorial license.

CI 178B SC 178B.5.4.7 P848 L25 # 476  
 Slavick, Jeff Broadcom  
 Comment Type TR Comment Status A (bucket) (CI)  
 Add a reference to coef\_sel in the coef\_select\_echo description.  
 SuggestedRemedy  
 Add this sentence to end of 178B.5.4.7 "The coefficient select echo bits reflect the value of the k variable generated by the coefficient update state diagram (Figure 178B-12)."  
 Response Response Status W  
 ACCEPT IN PRINCIPLE.  
 Implement suggested remedy with editorial license.

CI 178B SC 178B.5.7.1 P849 L28 # 477  
 Slavick, Jeff Broadcom  
 Comment Type TR Comment Status R (bucket) (CI)  
 There are two possible coef status values for a ic\_req.  
 SuggestedRemedy  
 Add the following to the end of step b)  
 or "coefficient not supported"  
 Response Response Status W  
 REJECT.  
 Coefficient is not being selected at this stage, so it can not be unsupported.

CI 178B SC 178B.2 P835 L25 # 479  
 Slavick, Jeff Broadcom  
 Comment Type TR Comment Status A (bucket) (CI)  
 The coordinated transition is the start-up protocol portion of ILT, give a reference from here to it.  
 SuggestedRemedy  
 Add "(see 178B.6)" after DATA mode  
 Response Response Status W  
 ACCEPT IN PRINCIPLE.  
 Change: "The ILT function provides coordinated transition of all ISLs to DATA mode,"  
 To: "The ILT function provides coordinated transition of all ISLs to DATA mode (tx\_mode = data, see 178B.7.3.1)."  
 Implement with editorial license.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178B SC 178B.7.2.1 P854 L23 # 482

Slavick, Jeff Broadcom

Comment Type T Comment Status A (bucket) (CI)

We've often used "DATA mode" to indicate state rather than tx\_mode = data, which is only used as an assignment in the state machine.

#### SuggestedRemedy

Change "tx\_mode = data" to "DATA mode" in the definition of uses\_recovered\_clock

Response Response Status C

ACCEPT IN PRINCIPLE.

Change: "to drive its output when tx\_mode = data."

To: "to drive its output in DATA mode (tx\_mode = data, see 178B.7.3.1)."

Implement with editorial license.

CI 178B SC 178B.7.3 P855 L50 # 483

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (CI)

When we enter PATH\_READY the state of local\_mc\_mode should apply to the given interface that it's set on, not any other interface. As we sometimes use adjacent to mean "the other PMA" versus the PMA that is providing the data for this interface.

#### SuggestedRemedy

Remove the word adjacent from the 2nd and 3rd paragraphs in four places.

Response Response Status W

ACCEPT IN PRINCIPLE.

Resolve using the response to comment #60.

CI 178B SC 178B.7.3 P856 L11 # 484

Slavick, Jeff Broadcom

Comment Type E Comment Status R (bucket) (CI)

The last paragraph of 178B.7.3 is describing which state machines are used which is related to the first paragraph of this section. The paragraphs between the first and last describe some specific cases related to precoding operations. So it'd be better if the first and last were next to each other.

#### SuggestedRemedy

Move the last paragraph that begins with "Interfaces using the E1 format" to be the second paragraph of this sub-clause.

Response Response Status C

REJECT.

This paragraph moved to this location according to the resolution of comment #499 against D2.0

CI 178B SC 178B.7.3.1 P858 L15 # 487

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (CI)

In Data mode we're transmitting the data from the other sub-layer, not really the AUI component or PMD those have digitized the data, but it's then processed by a PMA/PCS/XS/Inner FEC before being transmitted again.

#### SuggestedRemedy

Change the definition of data to be "transmit data from the PMA"

Response Response Status W

ACCEPT IN PRINCIPLE.

Implement suggested remedy with editorial license..

CI 178B SC 178B.7.3.1 P858 L12 # 488

Slavick, Jeff Broadcom

Comment Type T Comment Status A (bucket) (CI)

Training frames could use a reference

#### SuggestedRemedy

Add "(see 178B.5.2)" to the end of the definition of the training enumeration.

Response Response Status C

ACCEPT IN PRINCIPLE.

Implement suggested remedy with editorial license..

CI 30 SC 30.6.1.1.7 P65 L0 # 489

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (L)

Clause 73 uses more than just the base page to indicate which technologies are available.

#### SuggestedRemedy

aAutoNegReceivedTechnologyAbility behavior needs to update this sentence:  
For Clause 73 Auto-Negotiation, this attribute maps to bits D10-D13 and D21-D47 of the last received link codeword Base Page (see 73.6).

To:

For Clause 73 Auto-Negotiation, this attribute maps to bits of the last received link codeword Base Page and/or Message code 2 Next Page (see 73.6).

Response Response Status W

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

---

CI 30 SC 30.5.1.1.2 P64 L48 # 490

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (L)

Need to add new speeds into the Behavior description.

*SuggestedRemedy*

Add 800GBASE-R and 1.6.TBASE-R to the laundry list of enumerations used when PMD type is unknown in the last paragraph of BEHAVIOR DEFINED AS: for aMAUType

Response Response Status W

ACCEPT.

---

CI 45 SC 45.2.1.272 P118 L15 # 491

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (L)

Title of this section does not need the word "duplication" as this is not a duplicate of another set of registers with the same information. It is a distinct set of registers that have the same function as other defined registers but for a different instance.

*SuggestedRemedy*

Remove "Duplication of" from the name of 45.2.1.272

Response Response Status W

ACCEPT.

---

CI 45 SC 45.2.1.272 P118 L19 # 492

Slavick, Jeff Broadcom

Comment Type TR Comment Status A (bucket) (L)

What registers are they duplicates of?

*SuggestedRemedy*

Update the range of the ILT register space copy to be the first 4000 registers and use a 4000 register area of the map.

Update the text of 45.2.1.272 from:

Inter sublayer training requires control registers for the upper and bottom AUI components. The upper AUI component has the same control functionality as the bottom AUI component so the relevant registers are duplicated with an address offset of 4000.

To:

Inter sublayer training requires control registers for the upper and bottom AUI components. Registers 1.4000 through 1.7999 have identical functionality to the register 1.0 through 1.3999 (address offset of 4000). The relevant registers from 1.0 through 1.3999 are used of control and status of the bottom AUI component. The relevant registers from 1.4000 through 1.7999 are used for control and status of the upper AUI component.

Response Response Status W

ACCEPT.

---

CI 116 SC 116.5 P177 L11 # 493

Slavick, Jeff Broadcom

Comment Type TR Comment Status R (bucket) (CG)

Can we move footnote d to the same place as footnote b?

*SuggestedRemedy*

In Table 116-8

Change "(UI)b" to "(UI)b,d"

Remove the words "at this Skew point" from the footnote d definition.

Response Response Status W

REJECT.

The footnote applies only to SP1 through SP6. It does not apply to "at PCS receive" since the extra delay due to the source PMA codeword interleaving has been removed by the destination PMA.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

---

CI 177 SC 177.4.5 P347 L5 # 494

Slavick, Jeff

Broadcom

Comment Type TR Comment Status A (bucket) (L)

I've not heard of an inversion operation for a matrix. I know what the inverse of a matrix is.  
Should also make sure this explanation is relevant just to Eq 177-5

**SuggestedRemedy**

Change "The superscript "-1" denotes a matrix inversion operation."

To:

The superscript "-1" denotes the inverse of the matrix in Eq 177-5.

Or:

The superscript "-1" in Eq 177-5 is the notation for taking the inverse of the matrix.

Or:

delete this sentence entirely since superscript "-1" means "one over the thing" in math notation. So whether this is a number or a matrix it's the same mathematical operation and how can it be mis-interpreted.

**Response**

Response Status W

ACCEPT IN PRINCIPLE.

Change "The superscript "-1" denotes a matrix inversion operation."

To:

The superscript "-1" denotes the inverse of the matrix in Eq 177-5.

---

CI 177 SC 177.4.5 P346 L32 # 495

Slavick, Jeff

Broadcom

Comment Type TR Comment Status A (bucket) (L)

There are two instances of "dot" matrix. Lets make sure both a referred to.

**SuggestedRemedy**

Change "where the "" denotes a matrix dot multiplicaion."

To: "where the "" denotes matrix dot multiplication in the preceding equation and in Eq 177-4"

**Response**

Response Status W

ACCEPT.

---

CI 177 SC 177.4.7.1 P348 L41 # 496

Slavick, Jeff

Broadcom

Comment Type E Comment Status A (bucket) (L)

The description of the FAS could be improved.

**SuggestedRemedy**

Update the section to read as follows: "The Frame Alignment Sequence (FAS) is a fixed pattern that is the first 48-bits transmitted in each pad and enables the receiver to locate the pad. The fixed FAS pattern is as follows with the leftmost bit transmitted first:  
01011001 01010010 01100100 10100110 10101101 10011011"

**Response**

Response Status C

ACCEPT.

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 186 SC 186.2.3.5.10 P627 L7 # 497

Slavick, Jeff

Broadcom

Comment Type E Comment Status A (bucket) (L)

First sentence is very long.

#### SuggestedRemedy

From:

The three bytes of the AML field are used to encode information about the location of 800GBASE-R PCS alignment markers that were removed by the Inverse RS-FEC transmit function (see 186.2.3.1) within the stream of 257-bit blocks that are mapped into the 800GBASE-ER1 tributary multi-frame payload area, such that the 800GBASE-R PCS alignment markers can be re-inserted in the same location by the 800GBASE-ER1 FEC sublayer receive function.

To:

The three bytes of the AML field encodes the location within the stream of 257-bit blocks that the 800GBASE-R PCS alignment markers were removed by the Inverse RS-FEC transmit function (see 186.2.3.1). The AML field is mapped into the 800GBASE-ER1 tributary multi-frame payload area so that the 800GBASE-R PCS alignment markers can be re-inserted in the same location by the 800GBASE-ER1 FEC sublayer receive function.

Response Response Status C

ACCEPT IN PRINCIPLE.

The first sentence is indeed too long and complex, but the suggested remedy is not accurately capturing the meaning.

Replace the first paragraph of 186.2.3.5.10 with this text:

"The three bytes of the AML field (row 3, octets 2 and 3, and row 4, octet 3) in each multi-frame form a single 24-bit field, as shown in Figure 186-6. This field is used to encode information about the location of 800GBASE-R PCS alignment markers that were removed by the Inverse RS-FEC transmit function (see 186.2.3.1). The field encodes the position of the first non-stuff block that is mapped into the payload area relative to the location of the 800GBASE-R PCS alignment markers that were removed. This information allows the 800GBASE-R PCS alignment markers to be re-inserted in the same location by the 800GBASE-ER1 FEC sublayer receive function."

Implement with licence.

CI 119 SC 119.2.1 P184 L7 # 498

Opsasnick, Eugene

Broadcom

Comment Type E Comment Status R (bucket) (L)

The term "data units" should not be hyphenated unless it is functioning as a compound adjective directly before a noun.

Hyphenated example: "The network handles a high volume of data-unit transfers."

Non-hyphenated example: "The network transmits many data units."

Although both forms, hyphenated and non-hyphenated, are used throughout the base standard, the new clauses in 802.3dj as well as updates to previous clauses should use the correct form. Note that "data units" is used 22 times throughout D2.1 of 802.3dj, and 119.2.1 contains the only two occurrence of "data-units". In the base standard 802.3-2022, "data units" is used 51 times and "data-units" is used 34 times (which should also be fixed.). A maintenance request can be submitted to fix the base standard if this comment is accepted.

#### SuggestedRemedy

Change "data-units" to "data units" in the update to the fourth paragraph of 119.2.1. The first sentence should be changed

From:

"Transmit data-units are sent to the service interface via the PMA:IS\_UNITDATA\_i.request primitive."

To:

"Transmit data units are sent to the service interface via the PMA:IS\_UNITDATA\_i.request primitive."

The second sentence should be changed

From:

"The SIGNAL\_OK parameter of the PMA:IS\_SIGNAL.request primitive is set to OK when the transmit data-units are valid and is set to FAIL otherwise."

To:

"The SIGNAL\_OK parameter of the PMA:IS\_SIGNAL.request primitive is set to OK when the transmit data units are valid and is set to FAIL otherwise."

Response Response Status C

REJECT.

The comment correctly points out that in the context of 119.2.1 the correct term is "data units" and not "data-units". However, Clause 119 and the majority of the legacy PCS clauses (49, 82, 97, 126 and 149) use the term "data-units". Note, this issue has been addressed in the recent PCS clauses, where Clauses 172 and 175 correctly use "data units".

However this project is only amending 119.2.1 to add two sentences at the end of the fourth paragraph. The term "data-units" was used for the new text being added for consistency with the other three occurrences of "data-units" in 119.2.1 (in the first sentence

## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

of the fourth paragraph, and in the fifth and sixth paragraphs). In addition it is noted that comment #675 against D2.0 ([https://www.ieee802.org/3/dj/comments/D2p0/8023dj\\_D2p0\\_comments\\_final\\_id\\_v2.pdf](https://www.ieee802.org/3/dj/comments/D2p0/8023dj_D2p0_comments_final_id_v2.pdf)) changed "data units" to "data-units" for the next text being added, for consistency with the other three occurrences of 119.2.1 (that are not being amended).

The suggested remedy would change the first sentence of the fourth paragraph, which is technically out of scope. In addition to changing text that is technically out of scope, the suggested remedy would result in two occurrences of "data units" and two occurrences of "data-units" within 119.2.1, which is likely to attract additional comments (similar to comment #675 against D2.0). It is preferable to use "data-units" for the new sentence being added, for consistency with the three other occurrences of "data-units" in 119.2.1. A maintenance request can be submitted to fix this issue globally for all applicable occurrences of "data-units" in all of the impacted PCS clauses (including Clause 119).

<b>Cl 174</b>	<b>SC 174.2.5</b>	<b>P263</b>	<b>L32</b>	<b># 500</b>
Opsasnick, Eugene		Broadcom		
<b>Comment Type</b>	<b>E</b>	<b>Comment Status</b>	<b>A</b>	<b>(bucket) (CG)</b>

The term "1.6TAUI-n" is used to represent either a 1.6TAUI-8 or a 1.6TAUI-16. "1.6TAUI-n" is usually used a singular noun as in the first sentence of 174.2.5, line 31 that states "A 1.6 Tb/s Attachment Unit Interface (1.6TAUI-n) provides an electrical interface ....". However in the second sentence on line 32, the same term is used as a plural noun which sounds funny. The standard should stick to using "1.6TAUI-n" as a singular noun whenever possible.

**SuggestedRemedy**

Change the second sentence of 174.2.5

From:

"1.6TAUI-n are defined for chip-to-chip (C2C) and chip-to-module (C2M) implementations."

To:

"Two widths, 8-lane and 16-lane, of 1.6TAUI-n are defined for chip-to-chip (C2C) and chip-to-module (C2M) implementations."

Change the last sentence of 174.4.5

From: "1.6TAUI-n are instantiated within a Physical Layer implementation as described in 176B.7"

To:

"Each 1.6TAUI-n is instantiated within a Physical Layer implementation as described in 176B.7".

Similar changes should be made to 169.2.4a for the updates to the summary of the 800GE architecture.

<b>Response</b>	<b>Response Status C</b>
-----------------	--------------------------

ACCEPT IN PRINCIPLE.

Implement the suggested remedy, including the suggested changes to 169.2.4a, with editorial license.

<b>Cl 174</b>	<b>SC 174.2.5</b>	<b>P263</b>	<b>L35</b>	<b># 501</b>
Opsasnick, Eugene		Broadcom		
<b>Comment Type</b>	<b>E</b>	<b>Comment Status</b>	<b>R</b>	<b>(bucket) (CG)</b>

The list of the 4 types of 1.6TAUI-n on lines 35-41 should be presented as a dashed list. This would be consistent with similar lists of AUIs in 118.1.3, and 171.4.

The similar list of 800-GAUI-n in 169.2.4a should also be changed to a dashed list.

**SuggestedRemedy**

Change:

"The 1.6TAUI-16 C2C is specified in Annex 120F.

The 1.6TAUI-16 C2M is specified in Annex 176D.

The 1.6TAUI-8 C2C is specified in Annex 176C.

The 1.6TAUI-8 C2M is specified in Annex 176D."

To:

- " - The 1.6TAUI-16 C2C is specified in Annex 120F.
- The 1.6TAUI-16 C2M is specified in Annex 176D.
- The 1.6TAUI-8 C2C is specified in Annex 176C.
- The 1.6TAUI-8 C2M is specified in Annex 176D."

In 169.2.4a on page 199, starting on line 51, change the four separate paragraphs of 800GAUI-n types to a dashed list.

Change:

"The 800GAUI-8 C2C is specified in Annex 120F.

The 80GAUI-8 C2M is specified in Annex 120G.

The 800GAUI-4 C2C is specified in Annex 176C.

The 800GAUI-4 C2M is specified in Annex 176D"

To:

- " - The 800GAUI-8 C2C is specified in Annex 120F.
- The 80GAUI-8 C2M is specified in Annex 120G.
- The 800GAUI-4 C2C is specified in Annex 176C.
- The 800GAUI-4 C2M is specified in Annex 176D"

<b>Response</b>	<b>Response Status C</b>
-----------------	--------------------------

REJECT.

The proposed changes would make the formatting of 174.2.5 inconsistent with the other subclauses under 174.2. The proposed changes do not improve the clarity or accuracy of the draft.



## 02.3dj D2.1 200 Gb/s, 400 Gb/s, 800 Gb/s, and 1.6 Tb/s Ethernet 1st Working Group recirculation ballot c

CI 178 SC 178.8.9 P374 L37 # 502

Opsasnick, Eugene

Broadcom

Comment Type **TR** Comment Status **A** (bucket) ILT (E)

The statement "When mr\_training\_enable is false and tx\_mode = local\_pattern (see 178B.7.3.1), the PMD transmits PRBS31 encoded by Inner FEC (see 177.6.1.1)." is wrong since these -KR interfaces do not use an inner FEC. Subclause 178.8.9 describes the same functionality for a backplane connection as 179.8.9 does correctly for copper cable interfaces. Many of the 178.8.x subclauses currently refer to the definition of the same function in 179.8.x. This can also be done for 178.8.9

#### SuggestedRemedy

Replace all text in 178.8.9 with:  
"The PMD inter-sublayer link training function specification is identical to that of 179.8.9."

Response Response Status **W**

ACCEPT.

CI 179 SC 179.8.9 P407 L9 # 503

Opsasnick, Eugene

Broadcom

Comment Type **ER** Comment Status **A** (bucket) (E)

The first sentence of 179.8.9 states "A PMD shall provide ...", but this subclause is specifying the behavior of a specific PMD, not all PMDs.

#### SuggestedRemedy

Change "A PMD shall provide ..." to "The PMD shall provide ..."  
This matches the style of the other 179..8.x function definitions.

Response Response Status **W**

ACCEPT.

CI 177 SC 177.1.1 P388 L13 # 504

Opsasnick, Eugene

Broadcom

Comment Type **ER** Comment Status **A** (bucket) (L)

Redundant language should be simplified.

#### SuggestedRemedy

Change:  
"When necessary for disambiguation, to differentiate the Inner FEC defined in this clause from the 800GBASE-LR1 Inner FEC defined in Clause 184, the terms ..."  
To:  
""When necessary to differentiate the Inner FEC defined in this clause from the 800GBASE-LR1 Inner FEC defined in Clause 184, the terms ..."

Response Response Status **W**

ACCEPT.

CI 184 SC 184.1.1 P568 L11 # 505

Opsasnick, Eugene

Broadcom

Comment Type **ER** Comment Status **A** (bucket) (L)

Redundant language should be simplified.

#### SuggestedRemedy

Change:  
"When necessary for disambiguation, to differentiate the Inner FEC defined in this clause from the 800GBASE-R Inner FEC defined in Clause 177, the term 800GBASE-LR1 Inner FEC is used."  
To:  
"When necessary to differentiate the Inner FEC defined in this clause from the 800GBASE-R Inner FEC defined in Clause 177, the term 800GBASE-LR1 Inner FEC is used."

Response Response Status **W**

ACCEPT.

CI 177 SC 177.1.3 P339 L12 # 506

Opsasnick, Eugene

Broadcom

Comment Type **ER** Comment Status **A** (bucket) (L)

Missing comma and article

#### SuggestedRemedy

Change:  
"Per Inner FEC flow binary(128,120) encoding and decoding"  
To:  
"Per Inner FEC flow, a binary(128,120) encoding and decoding"

Response Response Status **W**

ACCEPT.

CI 177 SC 177.2 P341 L24 # 508

Opsasnick, Eugene Broadcom

Comment Type E Comment Status A (bucket) (L)

The cross-referece to Figure 177-2 in this paragraph is out of place, especially since the paragraph prior to it describes at the same client interface which are illustrated in the same figure without a cross-reference.

SuggestedRemedy

Remove "(see Figure 177-2)" from the line 24.

At line 4 of page 341, just prior to "The service interface primitives are summarized as follows:", add a single sentence paragraph that reads:  
"The Inner FEC service interfaces is illustrated in Figure 177-2..

Response Response Status C

ACCEPT IN PRINCIPLE.  
Implement the suggested remedy with editorial license.