

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >
Title	MIB II Integration and MIB II Table
Date Submitted	2006-03-06
Source(s)	Joey Chou [mailto:joey.chou@intel.com] Intel Corporation 5000 W. Chandler Blvd. Chandler, AZ 85226
Re:	
Abstract	This contribution proposed the text for Section 9 of IEEE P802.16i WG draft.
Purpose	Adoption
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.
Patent Policy and Procedures	<p>The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures (Version 1.0) <http://ieee802.org/16/ipr/patents/policy.html>, including the statement "IEEE standards may include the known use of patent(s), including patent applications, if there is technical justification in the opinion of the standards-developing committee and provided the IEEE receives assurance from the patent holder that it will license applicants under reasonable terms and conditions for the purpose of implementing the standard."</p> <p>Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair <mailto:r.b.marks@ieee.org> as early as possible, in written or electronic form, of any patents (granted or under application) that may cover technology that is under consideration by or has been approved by IEEE 802.16. The Chair will disclose this notification via the IEEE 802.16 web site <http://ieee802.org/16/ipr/patents/notices>.</p>

1 *Table of Content*

2 *1.Introduction.....3*

3 *2.MIB-II Integration.....3*

4 *1.Configuration.....3*

5 *3.Mobile MIB Definition.....3*

6

1

2 **1. Introduction**

3 This contribution proposes the text for Section 9 of IEEE P802.16i WG draft.

4 **2. MIB-II Integration**5 wmanIfMib, as defined in IEEE P802.16f standard, is located under MIB-II subtree, and can be accessed
6 through ifType – propBWA2Mp. propBWA2Mp is originally defined for proprietary broadband wireless
7 access for point to multipoint connections, and therefore, it is not sufficient to support a complete suite of
8 applications based on 802.16 standard. This contribution proposes the test for section 9, Configuration.

9

10 Th NetMan WG should submit a request to IANA for the assignment of a new IANAiftype –
11 ieee80216WMAN.12 **1. Configuration**

13

14 *[Replace the subclause 9.3.2.1 with the following:]*15 **9.3.2.1 MIB-II integration**16 wmanIfMib is located under MIB-II subtree. A submission will be sent to the Internet Assigned
17 Numbers Authority (IANA) to assign ieee80216WMAN for wmanIfMib.18 IANAifType ::= TEXTUAL-CONVENTION
19 SYNTAX INTEGER
20 {
21 ieee80216WMAN (???) -- IEEE 802.16 WirelessMAN
22 -- standard to be assigned
23 -- by IANA
24 }

25 Pending on IETF approval, wmanIfMib will be accessed through

26 iso.org.dod.internet.mgmt.mib-2.transmission.ifType
27 (1.3.6.1.2.1.10.???)28 **3. Mobile MIB Definition**29 The mobile MIB is an extension to IEEE 802.16f in adding MIB support for new features and functions
30 included in IEEE 802.16e standard. Therefore, mobile MIB should be a revision of IEEE 802.16f MIB based
31 on the following reasons:32 The revision approach will reduce significantly the amount of IEEE 802.16i work, as opposed to open the complete
33 802.16f MIB for changes.

34 Avoid the duplication of the majority of managed objects that were defined in IEEE 802.16f MIB.

35 IEEE 802.16f MIB structure has been designed to support multiple PHYs (e.g. OFDM-256 OFDMA-2048), and
36 MAC enhancements.

37 Support the backward-compatibility requirement as defined in RFC4181, section 4.9

38 ○ “over the wire” compability of agent and manager implementation that are based on different revisions
39 of the MIB module.

- 1 o “Compilation” conpatibility
- 2 Support the additional enhancements to be proposed by other WGs.

3

4 **[Replace the subclause 9.3.2.2 with the following:]**

5 **9.3.2.2 Usage of MIB-II tables**

6 "Interfaces" group of MIB-II, in RFC2863, has been designed to manage various sub-layers (e.g. MAC and PHY) beneath the internetwork-layer for numerous media-specific interfaces. The implementation of ifTable in SNMP managed BS and SS is mandatory.

7 The implementation of the ifTable for BS must create one row for each BS sector. Each BS sector may support different standards (e.g. IEEE 802.16-2004, IEEE 802.16e). The following recommendations must be applied to each row defining BS sector:

- 12 ifIndex value is implementation specific
- 13 ifType must be set to `ieee80216WMAN`
- 14 ifSpeed must be null
- 15 ifPhysAddress must be set to the MAC Address of the BS sector
- 16 All other columnar objects must be initialized as specified in RFC2863

17

<i>ifTable</i>	<i>ifIndex</i>	<i>ifType (IANA)</i>	<i>ifSpeed</i>	<i>ifPhysAddress</i>	<i>ifAdminStatus</i>	<i>ifOperStatus</i>
BS Sector 1	1	ieee80216WMAN	Null	MAC address of BS sector	Administration Status	Operational Status
BS Sector 2	2	ieee80216WMAN	Null	MAC address of BS sector	Administration Status	Operational Status
BS Sector 3	3	ieee80216WMAN	Null	MAC address of BS sector	Administration Status	Operational Status
BS Sector 4	4	ieee80216WMAN	Null	MAC address of BS sector	Administration Status	Operational Status
Ethernet			Null	MAC address	Administration Status	Operational Status

18 **Table 1 – Example of the Usage of ifTable objects for BS**

19 Table 1 shows an example of the usage of ifTable for BS that supports multiple sectors. Each sector may support one of the following MAC / PHY interfaces:

- 20 IEEE 802.16-2004, OFDM 256
- 21 IEEE 802.16-2004, OFDMA 2048
- 22 IEEE 802.16e, OFDM 128
- 23 IEEE 802.16e, OFDM 512
- 24 IEEE 802.16e, OFDM 1024

25

26 The implementation of the ifTable for SS must create one row for each SS WirelessMAN interface. Additional rows may be necessary to support other network interfaces, such as Ethernet. The following recommendations must be applied to each row:

- 27 IEEE 802.16-2004, OFDM 256
- 28 ifIndex value is implementation specific

1 ifType must be set to `ieee80216WMAN`
 2 ifSpeed must be null
 3 ifPhysAddress must be set to the SS MAC Address (of the WirelessMAN interface)
 4 All other columnar objects must be initialized as specified in RFC286

<i>ifTable</i>	<i>ifIndex</i>	<i>ifType (IANA)</i>	<i>ifSpeed</i>	<i>ifPhysAddress</i>	<i>ifAdminStatus</i>	<i>ifOperStatus</i>
SS	An ifEntry for SS	ieee80216WMAN	Null	MAC address of SS	Administration Status	Operational Status
Ethernet			Null	MAC address	Administration Status	Operational Status

Table 2— Example of the Usage of ifTable objects for SS

15 Table 2 shows an example of the usage of ifTable for SS that may support one of the following
 16 MAC / PHY interfaces:

- 17 IEEE 802.16-2004, OFDM 256
- 18 IEEE 802.16-2004, OFDMA 2048
- 19 IEEE 802.16e, OFDMA 128
- 20 IEEE 802.16e, OFDMA 512
- 21 IEEE 802.16e, OFDMA 102

22 Figure 20 shows a procedure describing how BS can determine the FFT size of a SS or MS during
 23 the DL synchronization for.





Figure 20= SS/MS DL Synchronization

- 22 1. Set the Rx channel (Select a frequency for receiving DL channel)
- 23 2. Set the FFT size
- 24 3. Set the CP size
- 25 4. If a preamble is received successfully, then go to step 5; otherwise,
- 26a. If FFT size is not exhausted, then select a new FFT size, and go to step 2; otherwise,
 - 27 ▪ If channel to be scanned is exhausted, then declare SS / MS DL synchronization
 - 28 failed; otherwise, select a new channel, and go step 1
- 29 5. Set the CP size
- 30 6. If a FCH (Frame Control Header) is received successfully, then go to network entry;
- 31 otherwise,
 - 32 a. If CP size is not exhausted, then select a new CP size, and go to step 3; otherwise,
 - 33 declare SS / MS DL synchronization failed
 - 34 b. Set FFT size object

36 Figure 21 shows a procedure describing how BS can determine the MAC / PHY standard interface
 37 and capability a SS / MS can support.
 38

39
 40
 41
 42
 43
 44
 45



31
32
33
34
35
36
37
38
39
40
41
42
43
44
45

Figure 21 – SS / MS Network Entry

1. Receive RNG-REQ from SS / MS
2. If MAC version is 802.16-2004
 - Then
 - a. Set MAC version object = ieee802Dot16Of2004
 - b. Set mobility object – No Supported
 - c. Go to step 5
3. Receive REG-REQ from SS / MS
4. If Mobility Feature is supported,
 - Then
 - a. Set MAC version object = ieee802Dot16e
 - b. Set mobility object – Supported
 - Otherwise
 - a. Set MAC version object = ieee802Dot16e
 - b. Set mobility object – Not Supported
5. Continue network entry procedure

1

2 *[Add the following ASN.1 code to Annex E:]*

3

```
4 WmanIfMacVersion ::= TEXTUAL-CONVENTION
5     STATUS         current
6     DESCRIPTION
7         "Version number of IEEE 802.16."
8     SYNTAX         INTEGER {ieee802Dot16Of2001(1),
9                     ieee802Dot16cOf2002(2),
10                    ieee802Dot16aOf2003(3),
11                    ieee802Dot16Of2004(4),
12                    ieee802Dot16e(5)}
13
14
```