

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Bandwidth request for non-transparent RS	
Date Submitted	2006-11-07	
Source(s)	Yuefeng Zhou Mike Hart Sunil Vadgama	Voice: +44 (0) 20 8573 4444 FAX: +44 (0) 20 8606 4539 yuefeng.zhou@uk.fujitsu.com mike.hart@uk.fujitsu.com sunil.vadgama@uk.fujitsu.com
	Fujitsu Laboratories of Europe Ltd Hayes Park Central, Hayes End Road, Hayes, Middlesex, UB4 8FE, UK	
Re:	IEEE 802.16j-06/027: "Call for Technical Proposals regarding IEEE Project P802.16j"	
Abstract	This contribution provides some text to clarify how a non-transparent RS with distributed scheduling function requests bandwidth for the R-UL and how the MR-BS handles the reception of MAC PDUs transmitted within the allocated BW.	
Purpose	Discuss and adopt proposed text and message format.	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

Bandwidth request for non-transparent RS

Yuefeng Zhou, Mike Hart, Sunil Vadgama

Introduction

This contribution provides some text to clarify how a non-transparent RS with distributed scheduling function requests bandwidth for the R-UL and how the MR-BS handles the reception of MAC PDUs transmitted within the allocated BW.

In summary, the RS will use the methods already available in IEEE Std 802.16 to request BW on the R-UL. Based on the case of the MAC signaling header Type 1 with the largest BR field of 19bits, this gives the total request size per header of 524288 bytes. Based on a maximum frame size of 20ms and minimum frame size of 2ms this enables the RS to request a maximum rate of 262Mbytes/s and 26.21Mbytes/s, respectively, based on sending a header in every frame. Therefore, this should be sufficient for the RS to indicate its bandwidth needs to the MR-BS.

The only clarification that is required is that the RS will be allocated an R-UL burst with CID set to the basic RSCID. However, the RS may transmit MS MAC PDU's in this allocated region, setting the CID in the Generic MAC header to that of the SS transport CID for with the payload corresponds. Consequently, the MR-BS will expect for this type of RS to receive MAC PDUs in the R-UL allocation with CIDs associated with the SSs that the MR-BS knows are served by the RS. TO clarify this situation, some text is proposed.

Proposed Text Change

[Insert the following at the end of subclause 6.3.6.2]

For an RS, bandwidth requests reference the R-UL allocation requirements of an RS in order to enable it to relay buffered MAC PDUs received from the SSs connected to it. The bandwidth grant is addressed to the RS's basic CID and the RS shall use the burst allocated to transmit SS MAC PDUs to the MR-BS. The MR-BS shall expect to receive concatenated (see Section 6.3.3.2) MAC PDUs with the CIDs of SS transport connections that are associated with the RS to which the grant was made.