

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	RS access link safety region.	
Date Submitted	2007-03-05	
Source(s)	Mike Hart, Yuefeng Zhou, Sunil Vadgama Fujitsu Laboratories of Europe Ltd. Hayes Park Central Hayes, Middx, UB4 8FE, UK	Voice: +44 20 8606 4523 Fax: +44 20 8606 4539 mike.hart@uk.fujitsu.com
Re:	Call for technical proposals 802.16j-07/007r2.	
Abstract	In case of distributed control MR system where the RS is responsible for allocation of resources on the access link, there is no mechanism to enable the MR-BS (or superordinate RS) to indicate to a sub-ordinate RS to reserve a region of the access link for non-transmission at that RS. This contribution provides a technical proposal for two new IEs to be transmitted on the R-MAP to an RS to indicate the requirement to reserve a safety region for non-transmission on its access downlink and/or uplink.	
Purpose	For discussion and approval of inclusion of the proposed text into the P802.16j baseline document.	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

RS access link safety region

Mike Hart, Yuefeng Zhou, Sunil Vadgama
Fujitsu Laboratories of Europe Ltd.

Introduction

In a MR network with distributed control [1], the RS is responsible for resource allocation on its access link, constructing the DL and UL MAP information and associated IEs in the RS. Consequently, there exists no mechanism that enables the MR-BS (or superordinate RS) to send a message to the RS to instruct it not to allocate a region of the access downlink at the RS for transmission to the SSSs that it serves. The same situation also exists for the access uplink controlled by the RS.

In order to allow an MR-BS (or RS) to indicate to the RS a region that is reserved for non-transmission on its access downlink and access uplink a new DL-MAP IE and UL-MAP IE is proposed to be transmitted on the R-Link [2] from the MR-BS or RS to RS to indicate the reserved or “safety” region on its access downlink and uplink, respectively. The RS upon receiving an IE in its R-MAP will then reserve this region in the access DL or UL in the next frame through a D/UIUC=13 allocation.

Proposed text

[Change the items in Table 277a in Section 8.4.5.3.2.1 as indicated:]

0A RS Access DL Safety Region IE

~~09-0A~~ ~~Reserved~~

[Insert new subclause at the end of section 8.4.5.3.x:]

8.4.5.3.x RS Access DL Safety Region IE

In the R-DL-MAP, an MR-BS or RS may transmit DIUC = 15 with the RS Access DL Safety Region IE() to indicate the location of region that shall be reserved for non-transmission on the RS access DL in the next DL subframe.

Table 286xx – RS Access DL Safety Region IE

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>RS Access DL Safety Region IE()</u>		
<u>Extended DIUC</u>	<u>4 bits</u>	<u>RS Access DL Safety Region IE = 0x0A</u>
<u>Length</u>	<u>4 bits</u>	
<u>OFDMA symbol offset</u>	<u>8 bits</u>	
<u>OFDMA subchannel offset</u>	<u>8 bits</u>	
<u>Number of OFDMA symbols</u>	<u>7 bits</u>	
<u>Number of subchannels</u>	<u>6 bits</u>	
<u>Reserved</u>	<u>3 bits</u>	<u>Shall be set to zero.</u>
<u>}</u>		

[Change the items in Table 290a in Section 8.4.5.4.4.1 as indicated:]

0B RS Access UL Safety Region IE
0BC ... 0F *Reserved*

[Insert new subclause at the end of section 8.4.5.4:]

8.4.5.4.x RS Access UL Safety Region IE

In the R-UL-MAP, an MR-BS or RS may transmit DIUC = 15 with the RS Access UL Safety Region IE() to indicate the location of region that shall be reserved for non-transmission on the RS access UL in the next UL subframe.

Table 286xx – RS Access UL Safety Region IE

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>RS Access UL Safety Region IE() {</u>		
<u>Extended UIUC</u>	<u>4 bits</u>	<u>RS Access UL Safety Region IE = 0x0B</u>
<u>Length</u>	<u>4 bits</u>	
<u>OFDMA symbol offset</u>	<u>8 bits</u>	
<u>OFDMA subchannel offset</u>	<u>7 bits</u>	
<u>Number of OFDMA symbols</u>	<u>7 bits</u>	
<u>Number of subchannels</u>	<u>7 bits</u>	
<u>Reserved</u>	<u>3 bits</u>	<u>Shall be set to zero.</u>
<u>}</u>		

References

- [1] Okuda, M., “Relaying methods proposal for 802.16j”, IEEE C802.16j-06/132, IEEE 802.16 meeting #46, Dallas, November 2006.
- [2] Hart, M., “Frame structure for multihop relaying support”, IEEE C802.16j-06/138, IEEE 802.16 meeting #46, Dallas, November 2006.