

---

<b>Project</b>	IEEE 802.16 Broadband Wireless Access Working Group < <a href="http://ieee802.org/16">http://ieee802.org/16</a> >	
<b>Title</b>	Transmission using station CID without tunnels	
<b>Date Submitted</b>	2007-03-15	
<b>Source(s)</b>	Ranga Reddy US Army - CERDEC, USA	<a href="mailto:Ranga.Reddy@us.army.mil">Ranga.Reddy@us.army.mil</a> Voice: +1 732-532-0085
	D. J. Shyy MITRE, USA	<a href="mailto:djshyy@mitre.org">djshyy@mitre.org</a> Voice: +1 703 983 6515
	Arnaud Tonnerre  THALES COMMUNICATIONS, FRANCE	<a href="mailto:arnaud.tonnerre@fr.thalesgroup.com">arnaud.tonnerre@fr.thalesgroup.com</a> Voice: +33 1 46 13 2850
	Djamal-Eddine Meddour  FRANCE TELECOM, FRANCE	<a href="mailto:djamal.meddour@orange-ft.com">djamal.meddour@orange-ft.com</a>
	Hang Zhang, Peiying Zhu, Mo-Han Fong, Wen Tong, David Steer, Gamini Senarath, Derek Yu, Mark Naden, G.Q. Wang	<a href="mailto:WenTong@nortel.com">WenTong@nortel.com</a> <a href="mailto:pyzhu@nortel.com">pyzhu@nortel.com</a> Voice: +1 613 7631315
	Nortel 3500 Carling Avenue Ottawa, Ontario K2H 8E9	
	Jeffrey Z. Tao, Koon Hoo Teo, Jinyun Zhang	<a href="mailto:{tao, tea, jzhang}@merl.com">{tao, tea, jzhang}@merl.com</a> Voice: 617-621-{7557,7527}
	Mitsubishi Electric Research Lab 201 Broadway Cambridge, MA 02139 USA	Fax: 617-621-7550
	Toshiyuki Kuze  Mitsubishi Electric Corp 5-1-1 Ofuna Kamakura, Kanagawa 2478501, Japan	<a href="mailto:Kuze.Toshiyuki@ah.MitsubishiElectric.co.jp">Kuze.Toshiyuki@ah.MitsubishiElectric.co.jp</a> Voice: +81-467-41-2885 Fax: +81-467-41-2486
<b>Re:</b>	Call for Technical Comments and Contributions regarding IEEE 802.16j	
<b>Abstract</b>	Provide a method for streamlining MPDU transmission and reducing overhead when a tunnel is	

---

not present

<b>Purpose</b>	To amend the text of baseline document for Section 6.3.3.8.2 and Section 6.3.2
<b>Notice</b>	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.
<b>Release</b>	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.
<b>Patent Policy and Procedures</b>	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < <a href="http://ieee802.org/16/ipr/patents/policy.html">http://ieee802.org/16/ipr/patents/policy.html</a> >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < <a href="mailto:chair@wirelessman.org">mailto:chair@wirelessman.org</a> > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < <a href="http://ieee802.org/16/ipr/patents/notices">http://ieee802.org/16/ipr/patents/notices</a> >.

## Transmission using station CID without tunnels

### Purpose

In 802.16j, tunnel based forwarding is introduced. Proposed is an alternative method for transmission of MPDUs when a tunnel is not present. This method proposes using destination/source basic CID based forwarding, and enables source-based QoS control may be employed. This method takes advantage of the a priori knowledge RS has regarding forwarding. This knowledge comes from the fact that during SF setup intermediate RSs keep a routing table, which includes the corresponding next hop RS identity for each SF.

Using this scheme, for DL data forwarding, MR-BS can include the destination RS basic CID and QoS info in the relay MAC header. The intermediate RS can schedule the transmission of this PDU based on QoS information along with the received PDU and identify the next hop RS based on the routing table; for UL, the access RS includes its source CID and QoS information in the relay MAC header. The intermediate RS shall make the corresponding process like that for DL.

This scheme provides the following benefits:

- lower signaling overhead – the signaling overhead regarding the tunnel setup, tunnel binding to a path (including tunnel and QoS population) can be significantly reduced
- Much less storage space for routing table/QoS profile in intermediate RS – size of the routing/QoS profile table is much less
- Very simpler process of intermediate RS – intermediate RS can simple process QoS information from sender to decide scheduling. An intermediate RS doesn't need to be populated and keep any information such as tunnel CID and associated QoS profiles

The purpose of this contribution is to amend text for Section 6.3.3.8.2 “Transmission using station CID” and Section 6.3.2 “MAC PDU Formats” in order to provide a method for streamlining MPDU transmission and supporting QoS in instances when tunnels are not used.

### Amendment Text

Add the following text to Section 6.3.3.8.2 “Transmission using station CID”

For this type of data forwarding, the routing table in intermediate RS shall simply include the destination RS CID and the corresponding next hop RS identity. Intermediate RS's may concatenate MPDUs from various CID's in the same PHY burst when those CID's share the same next hop (from viewpoint of transmitting intermediate RS).

For DL data forwarding, the MR-BS can include the destination RS basic CID and QoS info in the relay MAC header. The intermediate RS can schedule the transmission of this PDU based on QoS information along with the received PDU and identify the next hop RS based on the routing table; for UL, the access RS includes its source CID and QoS information in the relay MAC header. The intermediate RS shall make the corresponding process like that for DL.

Add the following text to the end of 6.3.2.1.1 (DL), please refer to C802.16j-07\_198r2

For data forwarding using the access basic CID based routing, the CID field in relay MAC header shall be the basic CID of the access RS. For DL, this field is equivalent to a destination identity.

For relay MPDU with payload, the bit #3 (fourth MSB in the header) in the first byte of relay MAC header is used as “Source QoS control”. If this bit is set, the QoS subheader is included and this subheader immediately follows the generic relay MAC header.

Add the following subclausue 6.3.2.1.11.1

#### 6.3.2.1.11.1 QoS subheader (DL)

If “Source QoS control” bit in generic relay MAC header is set, a QoS subheader presents in the Relay MAC PDU and will be the first subheader in the relay MPDU. This subheader is used for source QoS control and is inserted by the station which creates a Relay MPDU. Such a station can be MR-BS for DL data transmission or an access relay station for UL data relay. The QoS subheader is shown in Table XXX.

Table XXX: QoS Subheader Format

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>QoS Subheader</u>	<u>8</u>	<u>TBD</u>

Add the following text to the end of 6.3.2.1.2 (UL), please refer to C802.16j-07\_198r2

For data forwarding using the access basic CID based routing, the CID field in relay MAC header shall be the basic CID of the access RS. For UL, this field is equivalent to a source identity.

For relay MPDU with payload, the bit #5 (sixth MSB in the header) in the first byte of relay MAC header is used as “Source QoS control”. If this bit is set, the QoS subheader is included and this subheader immediately follows the generic relay MAC header.

Add the following subclausue 6.3.2.1.12.1

#### 6.3.2.1.12.1 QoS subheader (UL)

If “Source QoS control” bit in generic relay MAC header is set, a QoS subheader presents in the Relay MAC PDU and will be the first subheader in the relay MPDU. This subheader is used for source QoS control and is inserted by the station which creates a Relay MPDU. Such a station can be MR-BS for DL data transmission or an access relay station for UL data relay. The QoS subheader is shown in Table XXX.

Table XXX: QoS Subheader Format

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>QoS Subheader</u>	<u>8</u>	<u>TBD</u>