

Project	IEEE 802.16 Broadband Wireless Access Working Group < <a href="http://ieee802.org/16">http://ieee802.org/16</a> >	
Title	Clarification of Subheader related to MIMO mode feedback	
Date Submitted	2005-03-16	
Source(s)	Yongseok Jin, Bin-Chul Ihm, Jinyoung Chun  LG Electronics, Inc. 533, Hogye-1dong, Dongan-gu, Anyang-shi, Kyongki-do, Korea	Voice: 82-31-450-7187 Fax: 82-31-450-7912  [mailto: {jayjay, bcihm, jychun03}@lge.com]
	Mo-Han Fong Nortel Networks	<a href="mailto:mhfong@nortelnetworks.com">mhfong@nortelnetworks.com</a>
Re:	This is a response to a Call for Comments on IEEE P802.16e-D6	
Abstract	we suggest using UL MIMO mode feedback subheader which merges the two subheaders together	
Purpose	Adoption of proposed changes into P802.16e /D6. <b>Pink color indicates revised texts</b>	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < <a href="http://ieee802.org/16/ipr/patents/policy.html">http://ieee802.org/16/ipr/patents/policy.html</a> >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < <a href="mailto:chair@wirelessman.org">mailto:chair@wirelessman.org</a> > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < <a href="http://ieee802.org/16/ipr/patents/notices">http://ieee802.org/16/ipr/patents/notices</a> >.	

# Clarification of Subheader related to MIMO mode feedback

*Yongseok Jin, Bin-chul Ihm and Jinyoung Chun*  
*LG Electronics*

*Mo-Han Fong*  
*Nortel Networks*

## 1. Introduction

In the current spec, there are two subheaders related to the MIMO mode. One is the Mode Selection Feedback Subheader and the other is the Fast UL Feedback Subheader. A MSS uses the Mode Selection Feedback Subheader to provide its feedback in terms of the mode selection described by Table 298. MSS also uses the Fast UL Feedback subheader to provide MIMO Mode Feedback as described by Table 298b. Each subheader has some problems.

Problems are as follow.

- First, for the Mode Selection Feedback subheader, the contents of Table 298 which describes this subheader is included in Table 298b, thus resulting in possible duplication.
- Second, for the Fast UL Feedback subheader, there is no indication of methods to tell the existence of the Fast UL Feedback Subheader unlike the Mode selection feedback subheader.

In attempt to solve these two problems, we suggest using UL MIMO mode feedback subheader which merges the two subheaders together and uses ESF to indicate the existence and includes the feedback contents as described by Table 298b. This subheader is used for the case when the selected MIMO mode feedback has changed from the one previously reported and when the MSS has UL resource assigned to transmit UL traffic.

## 2. Proposed Text Change

*[Change name in Table 13c in page 28]*

Table 13c- Description of extended subheaders(UL)

ESF bit	Name	Length(bytes)	Descritipon
Bit #0 (LSB)	<del>Mode selection feedback</del> <a href="#">UL_MIMO mode feedback</a>	1	See 6.3.2.2.7.1
Bits #1-10	Reserved		

*[Remove section 6.3.2.2.7]*

~~6.3.2.2.7.1 Mode Selection Feedback Extended Subheader~~

*[Insert new section 6.3.2.2.7]*

[6.3.2.2.7.1 ~~UL~~ MIMO mode Feedback Extended subheader](#)

[The format of the ~~UL~~ MIMO mode feedback Extended subheader is specified in Table 13d. The support of the ~~UL~~ MIMO mode feedback Extended subheader is PHY specific. An MS uses the ~~UL~~ MIMO Feedback Extended Subheader to provide its feedback in terms of MIMO mode feedback. \*\*When there is an UL MAC PDU payload to be transmitted at the same time\*\*, this subheader shall only be used if the MS has successfully](#)

negotiated support of ~~UL~~ MIMO mode feedback Extended subheader with BS through the capabilities exchange dialog (SBC-REQ/RSP).

Table 13d – ~~UL~~ MIMO mode Feedback extended subheader format

<u>Name</u>	<u>Length (bits)</u>	<u>Description</u>
<u>Feedback type</u>	<u>2</u>	<del>00: MIMO mode and Permutation, or The number of Stream feedback type '000' as defined in Table 302a 01: Antenna grouping feedback type '001' as defined in Table 302a 10: Antenna selection feedback type '010' as defined in Table 302a 11: Precoding matrix code book feedback type '011' as defined in Table 302a</del>
<u>Feedback contents</u>	<u>6</u>	<del>Feedback contents and the corresponding feedback payload (6 bits) are the same as that defined in Table 302a and sections 8.4.5.4.10.4, 8.4.5.4.10.5, 8.4.5.4.10.6, 8.4.5.4.10.7, 8.4.5.4.10.8, 8.4.5.4.10.9, 8.4.5.4.10.10 Feedback content is as described in Table 298b, and if Feedback type is '01', see Table 298c, if '10', see Table 298d, if '11', see Table 298e.</del>

For each MSS, if a MIMO mode Feedback Extended subheader is present, it shall only appear in the first unicast PDU addressed to that MS in that frame.

**[Remove section 6.3.2.2.7.2 ]**

~~6.3.2.2.7.2 Fast UL Feedback subheader~~

**[Change the table as indicated]**

11.8.2 Capabilities for construction and transmission of MAC PDUs

Type	Length	Value	Scope
4	1	Bit #0: Ability to receive requests piggybacked with data Bit #1: Specifies the size of FSN values used when forming MAC PDUs on non-ARQ connections 0: Only 3-bit FSN values are supported 1: Only 11-bit FSN values are supported Bit #2: <del>Specifies support for MSF extended subheader</del> <u>Specifies support for <del>UL</del> MIMO mode feedback subheader (see 6.3.2.2.7.1)</u> Bit #3: Specifies support for Generic Sleep Extended subheader. (see 6.3.2.2.7.2) Bit #4: Specifies support for Feedback Request Extended subheader (see 6.3.2.2.7.3) Bit #5-#7 :Reserved, Shall be set to zero	<del>REG-REQ REG-RSP SBC-REQ SBC-RSP</del>