

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Proposed numerology and basic frame structure	
Date Submitted	2008-05-05	
Source(s)	Tetsu Ikeda NEC	E-mail: t-ikeda@ap.jp.nec.com
	Yuefeng Zhou NEC Europe	yuefeng.zhou@eu.nec.com
Re:	IEEE 802.16m-08/016r1, Call for SDD Comments and Contributions (2008-03-20)	
Abstract	This contribution provides updated numerology for IEEE 802.16m OFDMA. Introduce varieties of fractional symbols.	
Purpose	To be discussed and approved by TGm for use in the 802.16m SDD.	
Notice	<i>This document does not represent the agreed views of the IEEE 802.16 Working Group or any of its subgroups. It represents only the views of the participants listed in the "Source(s)" field above. It is offered as a basis for discussion. It is not binding on the contributor(s), who reserve(s) the right to add, amend or withdraw material contained herein.</i>	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy	The contributor is familiar with the IEEE-SA Patent Policy and Procedures: < http://standards.ieee.org/guides/bylaws/sect6-7.html#6 > and < http://standards.ieee.org/guides/opman/sect6.html#6.3 >. Further information is located at < http://standards.ieee.org/board/pat/pat-material.html > and < http://standards.ieee.org/board/pat >.	

Proposed numerology and basic frame structure

Yuefeng Zhou, Tetsu Ikeda
NEC Europe, NEC

Introduction

This contribution proposes some updates and clarifications for the set of OFDMA numerology for IEEE802.16m proposed in the rapporteur contribution IEEE 802.16m-008/118r1. This contribution also proposes the frame structure that supports multiple CP sizes within the same cell/frame. The introduction of fractional symbols enables smaller idle time and higher throughput together with legacy support.

Baseline Frame Structure

The baseline frame structure prepared by the Frame Structure Rapporteur Group [1] provides multiple CP size to support various communication environments. In such cases, existence of nonnegligible idle time is generally unavoidable and it leads to waste of radio resource. To combat with this issue, half symbol is proposed in [2]. Introduction of half symbol may reduce the idle time in the subframe. We expand the usage of fractional symbols to 1/3 and 1/4 symbols. Introduction of varieties of fractional symbols enables flexible subframe size with small idle time.

Proposed numerology leads to minimized idle time and maximized radio resource usage.

Proposed numerology is based on [3].

Proposed Text Change

To modify the proposed SDD text in C802.16m-08/003r1 as follows:

----- Start of Text-----

11.3 OFDMA Parameters

Modify '[Table 11.3-1: OFDMA parameters for IEEE 802.16m] → proposal-2' on page 5 as follows:

Parameter		Unit	Parameter Values							
Channel Bandwidth(BW)		MHz	5	6	7	8.75	10	12	14	20
FFT size			512	1024	1024	1024	1024	2048	2048	2048
Sampling Frequency (F_s)		MHz	6.4	12.8	12.8	12.8	12.8	25.6	25.6	25.6
Sub-carrier Spacing (Δf)	Full symbol	KHz	12.5							
	Half symbol	KHz	25							
	1/3 symbol	KHz	37.5							
	1/4 symbol	KHz	50							

Number of Used sub-carriers (N_{used})	Full symbol		400	480	560	700	800	960	1120	1600
	Half symbol		200	240	280	350	400	480	560	800
	1/3 symbol		133	160	186	233	266	320	373	533
	1/4 symbol		100	120	140	175	200	240	280	400
CP Length (T_{cp})	Short CP	μs	2.5							
	Normal CP	μs	10							
	Long CP	μs	15							

[Table 11.3-1: OFDMA parameters for IEEE 802.16m] → proposal-2

11.4.1 Basic Frame structure

[Adopt the following text modification begin from line #7]

A subframe is defined as contiguous time allocation with a fixed directionality i.e. downlink or uplink. Therefore, there are two types of subframes: DL subframes and UL subframes. A subframe consists of one or more permutation zones and may include the subsequent idle time to accommodate direction switching. Each subframe may have independent CP length to support various environments. A subframe may include fractional symbols to support legacy MS's subframe timing and to reduce idle time that is not for direction switching.

-----End of Text-----

4. References

- [1] C802.16m-08/118r1, "Proposed 802.16m Frame Structure Baseline Content Suitable for Use in the 802.16m SDD"
- [2] C802.16m-08/228r1, "Frame Structure to Support Multiple CP Sizes with Fixed Sub-frame Size"
- [3] C802.16m-08/236r3, "Further Considerations on IEEE 802.16m OFDMA Numerology"