
Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >
Title	Power control clarification
Date Submitted	May 5, 2005
Source(s)	Atul Salvekar Atul.salvekar@intel.com Roger Eline Roger.eline@intel.com Baraa Al-Dabagh Baraa.al.dabagh@intel.com Ambroise Popper ambroise@sequans.com Cavalli Giulio Giulio.Cavalli@siemens.com
Re:	IEEE 802.16-2004 and Corrigenda
Abstract	Application of the power control command and step size
Purpose	To clarify the time when the UL power change should apply and the step range
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.

Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.

Suggested changes

Section 6.3.2.3.6 add the following

Power Adjust Information

If this field is not included, no adjustment shall be made. [For OFDM the maximum gain change shall be limited to the range of +/- 10 dB.](#)

Section 6.3.2.3.34 add at the end of the last paragraph:

[For OFDM the maximum gain change shall be limited to the range of +/- 10 dB.](#)

Section 8.3.6.3.5 add at the end of the first paragraph

8.3.6.3.5 UL-MAP Power control IE format

[For OFDM the maximum gain change shall be limited to the range of +/- 10 dB.](#)

Apply the following changes to table 342:

System	Name	Time Reference	Minimum Value	Default Value	Maximum Value
SS	FPC processing time	Max.time between reception of Fast Power Control management messages and compliance to its instructions by SS			2.5 msec from the start of the frame (n+1) were frame n is the frame containing the FPC. If there is an UL allocation to the SS before the 2.5 msec in frame n+1 then the power change shall be applied before the end of the frame n+1

SS	RNG-RSP processing	Time allowed for an SS following receipt of a RNG-RSP before it is expected to apply the corrections instructed by the BS			25-msec 2.5 msec <u>from the start of the frame (n+1) were frame n is the frame containing the RNG_RSP. If there is an UL allocation to the SS before the 2.5 msec in frame n+1 then the power change shall be applied before the end of the frame n+1</u>
SS	power control IE	Time allowed for an SS following receipt of a UL-MAP including a power control IE before it is expected to apply the corrections instructed by the BS			25-msec 2.5 msec <u>from the start of the frame (n+1) were frame n is the frame containing the UL map containing the power control IE. If there is an UL allocation to the SS before the 2.5 msec in frame n+1 then the power change shall be applied before the end of the frame n+1</u>