

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Nibble-alignment for HARQ MAP IE	
Date Submitted	2005-05-04	
Source(s)	Yeongmoon Son, Junhyung Kim, Geunhwi Lim, Yong Chang	Ym1004.son@samsung.com junhyung77.kim@samsung.com geunhwi.lim@samsung.com , yongchang@samsung.com
	Samsung Electronics Co. Ltd.	
Re:	IEEE P802.16e/D7	
Abstract	The document contains error correction of nibble-alignment for HARQ MAP IE	
Purpose	Adoption of proposed changes into P802.16e /D5a-2004	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures (Version 1.0) < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, if there is technical justification in the opinion of the standards-developing committee and provided the IEEE receives assurance from the patent holder that it will license applicants under reasonable terms and conditions for the purpose of implementing the standard."	
	Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:r.b.marks@ieee.org > as early as possible, in written or electronic form, of any patents (granted or under application) that may cover technology that is under consideration by or has been approved by IEEE 802.16. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

Nibble-alignment for HARQ MAP IE

Yeongmoon Son, Junhyung Kim, Geunhwi Lim, Yong Chang

Samsung Electronics Co. Ltd

1 Motivation

Each HARQ Map IE and sub-burst IE shall be nibble-aligned. When there is an if-else clause, regardless of whether the ‘if’ clause or the ‘else’ clause is executed the resulting Map IE shall be nibble-aligned. When there is a loop, nibblealignment shall be required before the loop starts and inside the loop.

But Some HARQ MAP IEs do not observe the rule of nibble-alignment.

2 Nibble-alignment for HARQ MAP IE

2.1 Problem

Each HARQ MAP IE and sub-burst IE shall be nibble-aligned. When there is a loop, nibble-alignment shall be required inside the loop. But following tables didn’t nibble-aligned.

2.2 Remedy & Text change

[Change Ttable 285n in 8.4.5.3.22 HARQ DL MAP IE as follows]

Table 285n—DL HARQ Chase sub-burst IE format

Syntax	Size(bits)	Notes
DL HARQ Chase sub-burst IE() {	—	—
N sub burst[ISI]	5	Number of sub-bursts in the 2D region
Reserved	3	
For (j=0; j<N sub burst; j++){	—	—
RCID IE()	<i>variable</i>	—
Duration	10	Duration in slots
Sub-Burst DIUC Indicator	1	If Sub-Burst DIUC Indicator is 1, it indicates that DIUC is explicitly assigned for this sub-burst. Otherwise, the this sub-burst will use the same DIUC as the previous sub-burst If j is 0 then this indicator shall be 1.
Reserved	1	
If(Sub-Burst DIUC Indicator == 1){		
DIUC	4	
Repetition Coding Indication	2	0b00 – No repetition coding 0b01 – Repetition coding of 2 used 0b10 – Repetition coding of 4 used 0b11 – Repetition coding of 6 used
Reserved	2	
}		
ACID	4	—

AI_SN	1	—
ACK disable	1	When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.
Dedicated DL Control Indicator	+2	LSB #0 indicates inclusion of CQI control -LSB #1 indicates inclusion of Dedicated DL Control IE
If(LSB #0 of Dedicated DL Control Indicator== 1){	—	—
Duration (d)	4	A CQI feedback is transmitted on the CQI channels indexed by the (CQI Channel Index) by the SS for 2(d-1) frames. If d is 0b0000, deallocates all CQI feedback when the current ACID is completed successfully. If d is 0b1111, the MSS should report until the BS command for the MSS to stop
If (Duration != 0b0000){		
Allocation Index	6	Index to the channel in a frame the CQI report should be transmitted by the SS
Period (p)	3	A CQI feedback is transmitted on the CQI channels indexed by the (CQI Channel Index) by the SS in every 2p frames.
Frame offset	3	The MSS starts reporting at the frame of which the number has the same 3 LSB as the specified frame offset. If the current frame is specified, the MSS should start reporting in 8 frames.
}	—	—
} Elseif (LSB #1 of Dedicated DL Control Indicator ==1) {	—	—
Dedicated DL Control IE ()	<i>variable</i>	—
}	—	—
}	—	—
}	—	—

[Change table in 8.4.5.3.22 HARQ DL MAP IE as follows]

Table 285o—DL HARQ IR CTC sub-burst IE format

Syntax	Size(bits)	Notes
DL HARQ IR CTC sub-burst IE() {	—	—
N sub burst	5	—
Reserved	3	—
For (j=0; j< N sub burst; j++){	—	—
RCID IE()	<i>variable</i>	—
Nep	4	—
Nsch	4	—
SPID	2	—
ACID	4	—
AI_SN	1	—
ACK disable	1	When this bit is 1 no ACK channel is allocated and the SS shall not reply with an ACK.
Reserved	2	—
Dedicated DL Control Indicator	+2	LSB #0 indicates inclusion of CQI control LSB #1 indicates inclusion of Dedicated DL Control IE
If(LSB #0 of Dedicated DL Control Indicator == 1){	—	—
Duration (d)	4	A CQI feedback is transmitted on the CQI channels indexed by the (CQI Channel Index) by the SS for 2(d-1) frames. If d is 0b0000, deallocates all CQI feedback when the current ACID is completed successfully. If d is 0b1111, the MSS should report until the BS command for the MSS to stop

If (Duration != 0b0000){		
Allocation index	6	Index to the channel in a frame the CQI report should be transmitted by the SS
Period(p)	3	A CQI feedback is transmitted on the CQI channels indexed by the (CQI Channel Index) by the SS in every 2p frames.
Frame offset	3	The MSS starts reporting at the frame of which the number has the same 3 LSB as the specified frame offset. If the current frame is specified, the MSS should start reporting in 8 frames.
}		
}	—	—
ElseIf (LSB #1 of Dedicated DL Control Indicator ==1) {	—	—
Dedicated DL Control IE ()	<i>variable</i>	—
}	—	—
}	—	—
}	—	—

[Change table in 8.4.5.3.22 HARQ DL MAP IE as follows]

Table 285p—DL HARQ IR CC sub-burst IE format

Syntax	Size(bits)	Notes
DL HARQ IR CTC sub-burst IE() {	—	—
N sub burst	5	—
Reserved	3	—
For (j=0; j< N sub burst; j++) {	—	—
RCID IE()	<i>variable</i>	—
Duration	10	—
Sub-Burst DIUC Indicator	1	If Sub-Burst DIUC Indicator is 1, it indicates that DIUC is explicitly assigned for this sub-burst. Otherwise, the this sub-burst will use the same DIUC as the previous sub-burst If j is 0 then this indicator shall be 1.
Reserved	1	—
If(Sub-Burst DIUC Indicator == 1){	—	—
DIUC	4	—
Repetition Coding Indication	2	0b00 – No repetition coding 0b01 – Repetition coding of 2 used 0b10 – Repetition coding of 4 used 0b11 – Repetition coding of 6 used
Reserved	2	—
}	—	—
ACID	4	—
AI SN	1	—
SPID	2	—
ACK disable	1	When this bit is "1" no ACK channel is allocated and the SS shall not reply with an ACK.
Dedicated DL Control Indicator	2	LSB #0 indicates inclusion of CQI control LSB #1 indicates inclusion of Dedicated DL Control IE
Reserved	2	—
If(LSB #0 of Dedicated DL Control Indicator == 1) {	—	—
Duration (d)	4	A CQI feedback is transmitted on the CQI channels indexed by the (CQI Channel Index) by the SS for 2(d-1) frames. If d is 0b0000, deallocates all CQI feedback when the current ACID is completed successfully.

		If d is 0b1111, the MSS should report until the BS command for the MSS to stop
If (Duration != 0b0000) {		
Allocation index	6	Index to the channel in a frame the CQI report should be transmitted by the SS
Period(p)	3	A CQI feedback is transmitted on the CQI channels indexed by the (CQI Channel Index) by the SS in every 2 ^p frames.
Frame offset	3	The MSS starts reporting at the frame of which the number has the same 3 LSB as the specified frame offset. If the current frame is specified, the MSS should start reporting in 8 frames.
}	—	—
}	—	—
Elseif ((LSB #1 of Dedicated DL Control Indicator ==1) {	—	—
Dedicated DL Control IE ()	<i>variable</i>	—
}	—	—
}	—	—
}	—	—

[Change table in 8.4.5.3.23 DL HARQ ACK IE as follows]

Table 285q—HARQ_ACK IE

Syntax	Size(bits)	Notes
HARQ_ACK IE() {	—	—
Extended-2 DIUC	4	HARQ_ACK IE () = 0x08
Length	8	Length in bytes
Bitmap	<i>variable</i>	Bitmap size is determined by Length field
}	—	—

[Change table in 8.4.5.3.24 Enhanced DL MAP IE as follows]

Table 285r—Enhanced DL MAP IE

Syntax	Size(bits)	Notes
Enhanced_DL_MAP IE() {	—	—
Extended-2 DIUC	4	Enhanced_DL_MAP IE () = 0x09
Length	8	Length in bytes
Num_Assignment	4	Number of assignments in this IE
For (i=0; i<Num_Assignment;i++) {	—	—
if (INC_CID == 1) {	—	The DL-MAP starts with INC_CID =0. INC_CID is toggled between 0 and 1 by the CID-SWITCH_IE() (8.4.5.3.7)
N_CID	8	Number of CIDs
For (n=0; n<N_CID; n++) {	—	—
CID	16	—
}	—	—
}	—	—
DIUC	4	—
Boosting	3	Refer to Table 273.
Repetition Coding Indication	2	—
Region ID	8	Index to the DL region defined in DL channel definition TLV in DCD
Reserved	3	—
}	—	—

}	—	—
---	---	---

[Change table in 8.4.5.4.1 Dedicated UL Control IE as follows]

Table 302o—Dedicated UL control IE format

Syntax	Size(bits)	Notes
Dedicated UL control IE() {	—	—
Length	4	Length of following control information in Nibble.
Control Header	4	Bit #0: SDMA Control Info Bit #1-3: Reserved
If(SDMA Control Info Bit == 1){		
Num SDMA layers	2	This value plus one indicates the total number of SDMA layers associated with the HARQ UL MAP IE
Pilot pattern	2	00 = pattern A 01 = pattern B 10 = pattern C 11 = pattern D
}		
<i>Padding bits</i>	<i>variable</i>	
}	—	—