

COM 3.70 with 3.1 Configuration Updates, Fixes, and Exploratory Features including Package/Die Load Ladder

Richard Mellitz, Samtec

Contributors


Samtec: Adam Gregory, Brandon Gore

Intel: Mike Peng Li, Hsinho Wu, Masashi Shimanouchi, Jenny Xiaohong Jiang

March 23, 2022

Reference Nomenclature

Green is an addition



D3.1 update, Additional Exploratory COM Capability, Expanded Tx FFE taps, and minor improvements

- ❑ Changed output
 - $\text{total_IL_wpkgs_dB_at_Fnq}$ to $\text{VIP_to_VIM_IL_dB_at_Fnq}$
- ❑ Fixed .3bj backward compatibility issue.
 - Tr caused error for 100G Base CR4
 - No change to prior configuration spreadsheets.
 - i.e., backward compatible
- ❑ Fix for floating tap algorithm for computing consecutive taps spacing.
 - Impact from a few tests: < 0.05 dB COM
- ❑ Expands syntax for Tx FFE to any number of taps
 - Syntax $c(n)$ where n is an a positive of negative non-zero integer.
 - Rules: all tap ranges up to n must be specified. Set $c(n)$ to zero if tap is not used.
 - Example
 - $C(-4) = [0.1 ; 0.05 ; 0]$
 - $C(-3)=0$
 - $C(-2)=[0.1 ; 0.05 ; 0]$
 - $C(-1)=0$
- ❑ Exploratory implementation of ran_3ck_03_0122 for SNR_Tx
 - By setting keyword to 1 (default is 0 if not specified)
- ❑ Speed up for C2M
- ❑ CR and C2M d3.1 spreadsheet change

IEEE802.3 ck Package Model (single sided representation)





Table 93A-1 parameters

Parameter	Setting	Units	Information
C_d	[1.2e-4 1.2e-4]	nF	[TX RX]
L_s	[0.12, 0.12]	nH	[TX RX]
C_b	[0.3e-4 0.3e-4]	nF	[TX RX]
z_p select	[1 2]		[test cases to run]
z_p (TX)	[12 31; 1.8 1.8]	mm	[test cases]
z_p (NEXT)	[12 29; 1.8 1.8]	mm	[test cases]
z_p (FEXT)	[12 31; 1.8 1.8]		[test cases]
z_p (RX)	[12 29; 1.8 1.8]	mm	[test cases]
C_p	[0.87e-4 0.87e-4]	nF	[TX RX]
R_0	50	Ohm	
R_d	[45 45]	Ohm	[TX RX]
A_v	0.39	V	vp/vf=.694
A_fe	0.39	V	vp/vf=.694
A_ne	0.578	V	

Table 93A-3 parameters


Parameter	Setting	Units
package_tl_gamma0_a1_a2	[0 0.0009909 0.0002772]	
package_tl_tau	6.141E-03	ns/mm
package_Z_c	[87.5 87.5 ; 92.5 92.5]	Ohm

Replace Cd and Ls with a Ladder



C_d	[C_d C_{d2} C_{d3} C_{d4} ... C_{dn} ; C_d C_{d2} C_{d3} C_{d4} ... C_{dn}]	nF	[TX ; RX]
L_s	[L_s L_{s2} L_{s3} L_{s4} ... L_{sn} ; L_s L_{s2} L_{s3} L_{s4} ... L_{sn}]	nH	[TX ; RX]

Example: T-coil ladder data in li_3df_02_220316



C_d	[0.4e-4 0.9e-4 1.1e-4 ; 0.4e-4 0.9e-4 1.1e-4]	nF	[TX RX]
L_s	[0.13 0.15 0.14; 0.13 .15 0.14]	nH	[TX RX]
C_b	[0.3e-4 0.3e-4]	nF	[TX RX]
z_p select	[1 2 3 4]		[test cases to run]
z_p (TX)	[12 31; 1.8 1.8]	mm	[test cases]
z_p (NEXT)	[12 29; 1.8 1.8]	mm	[test cases]
z_p (FEXT)	[12 31; 1.8 1.8]	mm	[test cases]
z_p (RX)	[12 29; 1.8 1.8]	mm	[test cases]
C_p	[0.4e-4 0.4e-4]	nF	[TX RX]
R_0	50	Ohm	

Parameter	Setting
package_tl_gamma0_a1_a2	[0 8.9e-4 1.55e-4]
package_tl_tau	6.14E-03
package_Z_c	[87.5 87.5 ; 92.5 92.5]

Exploratory for .3df

File list

- ❑ com_ieee8023_93a_370.m
- ❑ mellitz_3ck_01_032322.pdf
- ❑ TP0V_example.m
- ❑ config_sheets_3p1
 - config_com_ieee8023_93a=3ck_d3p1_TP0V_11_30_21.xlsx
 - config_com_ieee8023_93a=3ck_d3p1_120F_C2C_11_30_21.xlsx
 - config_com_ieee8023_93a=3ck_d3p1_120g_C2M_tp1a_9_11_30_21.xlsx
 - config_com_ieee8023_93a=3ck_d3p1_CR_CA_11_30_21.xlsx
 - config_com_ieee8023_93a=3ck_d3p1_KR_11_30_21.xlsx
 - config_com_ieee8023_93a=3ck_d3p1_MTF_tp1a_11-30-21.xlsx
 - keywords_14-Mar-2022.csv

Thank You!