

IEEE P802.3cw D1.2 400 Gb/s over DWDM systems 3rd Task Force review comments

CI 156 SC 156.10.1.1 P83 L6 # 1 [REDACTED]
 Pittala, Fabio Huawei
 Comment Type **TR** Comment Status **X**
 The first box of Figure 156-7 consists of a coherent receiver and the second box consists of the frontend correction. Both boxes make a calibrated coherent receiver.
 SuggestedRemedy
 Rename the first box of Figure 156-7 as "Coherent Receiver" instead of "Calibrated Coherent Receiver"
 Proposed Response Response Status **O**

CI 156 SC 156.10.1.2.3 P84 L13 # 4 [REDACTED]
 Pittala, Fabio Huawei
 Comment Type **TR** Comment Status **X**
 In Figure 156-8 there is a box "Carrier Phase Recovery" but no subclause is included to describe the functionality of this DSP block.
 SuggestedRemedy
 Add a new subclause 156.10.1.2.3 titled "Carrier Phase Recovery". Description text is TBD.
 Proposed Response Response Status **O**

CI 156 SC 156.10.1.2. P84 L8 # 2 [REDACTED]
 Pittala, Fabio Huawei
 Comment Type **TR** Comment Status **X**
 Requirements on the clock recovery unit should be included.
 SuggestedRemedy
 Modify Figure 156-8 changing the second block as "Clock and Frequency Offset Recovery". Include at the beginning of subclause 156.10.1.2.2 the following text "A clock recovery with a corner frequency of TBD MHz and a slope of TBD dB/decade is applied on a fixed block length of TBD symbols."
 Otherwise modify Figure 156-8 adding a block named "Clock Recovery" after the "Polarization Demux" block and add a new subclause (156.10.1.2.2) containing the following text "A clock recovery with a corner frequency of TBD MHz and a slope of TBD dB/decade is applied on a fixed block length of TBD symbols."
 Proposed Response Response Status **O**

CI 156 SC 156.7.1 P73 L25 # 5 [REDACTED]
 Jackson, Kenneth Sumitomo Electric
 Comment Type **E** Comment Status **X**
 Table 156-6, Laser frequency noise mask. Eliminate TBDs?
 SuggestedRemedy
 Make reference to 156.9.6 Laser frequency noise mask.
 Proposed Response Response Status **O**

CI 156 SC 156.10.1.2.1 P84 L1 # 3 [REDACTED]
 Pittala, Fabio Huawei
 Comment Type **ER** Comment Status **X**
 There is a mismatch between the title of subclause 156.10.1.2.1 and the corresponding block in Figure 156-8.
 SuggestedRemedy
 Rename subclause 156.10.1.2.1 as "Polarization Demux"
 Proposed Response Response Status **O**

CI 156 SC 156.9.6 P79 L51 # 6 [REDACTED]
 Jackson, Kenneth Sumitomo Electric
 Comment Type **E** Comment Status **X**
 Labeling on plot (Figure 156-5—Frequency vs spectral power density) needs to reflect the table values.
 SuggestedRemedy
 change 1.0^6 to 10^6 (remove decimal) or 1.0e6
 Proposed Response Response Status **O**

IEEE P802.3cw D1.2 400 Gb/s over DWDM systems 3rd Task Force review comments

Cl 156 SC 156.9.4 P78 L41 # 7

Jackson, Kenneth Sumitomo Electric

Comment Type T Comment Status X

Figure 156-4—Transmit spectral mask (max and min)
The text says, "...lower mask is set at -9 dB up to half the baud rate....", yet the Figure shows (30.8,-9). Isn't half the baud rate 29.9?

SuggestedRemedy

If my understanding is correct, the figure should be changed to reflect half the baud-rate.

Proposed Response Response Status O

Cl 155 SC 155.6 P61 L23 # 10

Lewis, David Lumentum

Comment Type T Comment Status X

Loopback information is needed.

SuggestedRemedy

Contribution with proposed baseline text and figures will be made at a task force meeting. If the baseline is accepted, the editor's note can be removed. The task force could also decide that looback details are not needed, in which case subclause 155.6 can be removed.

Proposed Response Response Status O

Cl 155 SC 155.4 P61 L10 # 8

Lewis, David Lumentum

Comment Type T Comment Status X

Detailed functions and state diagrams for 400GBASE-ZR PCS and PMA are needed.

SuggestedRemedy

Contribution with proposed baseline text and figures will be made at a task force meeting. If the baseline is accepted, the editor's note can be removed. The task force could also decide that the detailed functions and state diagrams are not needed, in which case subclause 155.4 can be removed.

Proposed Response Response Status O

Cl 155 SC 155.8 P63 L1 # 11

Lewis, David Lumentum

Comment Type T Comment Status X

PICS tables are needed.

SuggestedRemedy

Contribution with proposed tables will be made at a task force meeting.

Proposed Response Response Status O

Cl 155 SC 155.5 P61 L17 # 9

Lewis, David Lumentum

Comment Type T Comment Status X

Management information for 400GBASE-ZR PCS and PMA is needed.

SuggestedRemedy

Contribution with proposed baseline text and figures will be made at a task force meeting. If the baseline is accepted, the editor's note can be removed. The task force could also decide that management details are not needed, in which case subclause 155.5 can be removed.

Proposed Response Response Status O

Cl 155 SC 155.1.2 P34 L26 # 12

Huber, Tom Nokia

Comment Type T Comment Status X

Text says the 400GMII extender sublayers are shown in the figure, but the figure does not include them.

SuggestedRemedy

Delete the second sentence of the first paragraph of 155.1.2, beginning with "The sublayers of a 400GMII Extended Sublayer..."

Proposed Response Response Status O

IEEE P802.3cw D1.2 400 Gb/s over DWDM systems 3rd Task Force review comments

Cl 155 SC 155.2.4.1 P39 L14 # 13

Huber, Tom Nokia
 Comment Type T Comment Status X

The sentence about rate matching not being necessary could be more clear. Rate matching as described in 119.2.4.1 has two purposes: making room for alignment markers, and aligning the two clock domains. It is not needed in 400GBASE-ZR both because the AMs are not inserted into the stream of transcoded blocks (they are instead part of the 400GBASE-ZR frame) and because GMP handles the clock domain transition.

SuggestedRemedy

Modify the second sentence of the first paragraph to read: "The rate matching described in 119.2.4.1 is not required for the 400GBASE-ZR PCS because the transcoded block stream is mapped into a 400GBASE-ZR frame structure that includes space for alignment markers, and clock compensation between the two clock domains is provided by this mapping."

Proposed Response Response Status O

Cl 155 SC 155.2.4.3 P39 L38 # 14

Huber, Tom Nokia
 Comment Type E Comment Status X

The right-hand curly brace, two horizontal lines, and word 'Frame' on the right hand side of the figure don't seem to add any clarity. The figure title is 400GBASE-ZR frame structure, and the text describes the structure clearly.

SuggestedRemedy

Delete the right-hand curly brace, horizontal lines and 'Frame', leaving only the frame itself in the figure.

Proposed Response Response Status O

Cl 155 SC 155.2.4.4.1 P40 L53 # 15

Huber, Tom Nokia
 Comment Type T Comment Status X

The description of the alignment markers repeats some details from clause 119 that create ambiguity regarding the transmission order, and also doesn't mention that the 3-bit status described in clause 119 is not included.

SuggestedRemedy

Rewrite the clause as follows:
 Alignment markers are used to provide frame delineation for the 400GBASE-ZR frame. They are inserted before FEC encoding and removed after FEC decoding (see Figure 155-2). The variable am_mapped<1919:0> is constructed in a manner that yields the same result as the process described in 119.2.4.4.2. The 133-bit pad and 3-bit status fields are not added. The resulting 1920-bit value is inserted in the AM field of each 400GBASE-ZR frame.

Proposed Response Response Status O

Cl 155 SC 155.2.4.4.3 P41 L18 # 16

Huber, Tom Nokia
 Comment Type T Comment Status X

The overhead in G.709.1 does not include the 'LDI' field described in 155.2.4.4.5; that is only in the 400ZR IA. As such the statement that the contents of the overhead are described in G.709.1 clauses 8.1 and 9.2 is not accurate.

SuggestedRemedy

Since G.709.1 and the 400ZR IA have different descriptive techniques, and neither one uses the same bit numbering convention of 802.3, it may be more expedient to create a figure in P802.3cw that shows the structure of the first set of 320 bits rather than to try and reference either document. Revise the text to say: The overhead is organized into four sets of 320 bits that are interleaved in groups of 10 bits to form the 1280 bit field. The contents of the first 320 bits are as shown in Figure 155-X and described below. The contents of the second through fourth sets of 320 bits are all zeros.

Proposed Response Response Status O

IEEE P802.3cw D1.2 400 Gb/s over DWDM systems 3rd Task Force review comments

CI 155 SC 155.2.4.4.4 P41 L23 # 17

Huber, Tom Nokia

Comment Type E Comment Status X

155.2.4.4.4, 155.2.4.4.5, and 155.2.4.4.6 are all describing specific aspects of the 400GBASE-ZR overhead field. As such, it would probably be better if they were renumbered to be subclauses of 155.2.4.4.3.

SuggestedRemedy

Change the numbering to 155.2.4.4.3.1 through 155.2.4.4.3.3.

Proposed Response Response Status O

CI 155 SC 155.2.4.4.5 P41 L41 # 18

Huber, Tom Nokia

Comment Type T Comment Status X

More detail about the LDI field is needed. While it is generally better to cross-reference, and the intent is clearly to match the behavior in the 400ZR IA, the IA treats these bits as part of the STAT byte rather than a separate field, and it also refers back to `tx_sf<2:0>` in its definition, so it would be better to describe how `LDI<2:0>` relates to `tx_am_sf<2:0>` directly. The text in the IA appears to align with the definitions of `tx_am_sf<2:0>` for PHY XS FEC Degradate signaling in 118.2.2 of 802.3 (the 'extra processing' in the IA seems to be described in this clause). The order of the bits in the Status byte is different than in `tx_am_sf<2:0>`.

SuggestedRemedy

Add the following text to paragraph 4:
The contents of `LDI<2:0>` are as follows:
`LDI<2>` corresponds to `tx_am_sf<0>` in 118.2.2. `LDI<1>` corresponds to `tx_am_sf<2>` in 118.2.2. `LDI<0>` corresponds to `tx_am_sf<1>` in 118.2.2.

Proposed Response Response Status O

CI 155 SC 155.2.4.9 P46 L3 # 19

Huber, Tom Nokia

Comment Type E Comment Status X

The figure contains a mix of lighter and heavier horizontal lines. The heavier lines don't appear to mean anything.

SuggestedRemedy

Revise the figure to remove the heavy lines, or make clear what they mean if there is an intended meaning to them.

Proposed Response Response Status O

CI 155 SC 155.2.4.9 P46 L25 # 20

Huber, Tom Nokia

Comment Type T Comment Status X

The last 6 rows in the first column are shaded, presumably because they are the 6 blocks of padding, but the shading is not maintained in the other columns.

SuggestedRemedy

Remove the shading of the pad blocks and relabel the left-most column to just show 10976 blocks of 119b, as the details of which blocks are pad blocks are not really important to this figure.

Proposed Response Response Status O

CI 155 SC 155.2.4.10 P46 L38 # 21

Huber, Tom Nokia

Comment Type E Comment Status X

No need for a hyphen in "It adds 9-bits of parity..."

SuggestedRemedy

To maximize clarity, reword as "It adds 9 parity bits..."

Proposed Response Response Status O

CI 155 SC 155.2.5.6 P48 L50 # 22

Huber, Tom Nokia

Comment Type T Comment Status X

The title of the clause is "CRC-32 check", but the text is mostly about error marking

SuggestedRemedy

Revise the title to be "CRC-32 check and error marking"

Proposed Response Response Status O

IEEE P802.3cw D1.2 400 Gb/s over DWDM systems 3rd Task Force review comments

Cl 155 SC 155.2.5.7 P49 L6 # 23
 Huber, Tom Nokia
 Comment Type E Comment Status X
 There should be a hyphen in CRC32
 SuggestedRemedy
 Change to CRC-32
 Proposed Response Response Status O

Cl 156 SC 156.8 P75 L41 # 26
 Maniloff, Eric Ciena
 Comment Type T Comment Status X
 Interferometric crosstalk is not required to be specified for point-to-point applications.
 SuggestedRemedy
 Remove Interferometric crosstalk from Table 156-8
 Proposed Response Response Status O

Cl 155 SC 155.2.5.7.2 P49 L48 # 24
 Huber, Tom Nokia
 Comment Type T Comment Status X
 Additional detail about the LDI field and how it relates to tx_am_sf<2:0> in clause 118 is needed.
 SuggestedRemedy
 Add a cross-reference to the description of the LDI bits in the Transmit clause (this is currently 155.2.4.4.5, but may be changed to 155.2.4.4.3.2 based on another comment)
 Proposed Response Response Status O

Cl 156 SC 156.7.2 P74 L23 # 27
 Maniloff, Eric Ciena
 Comment Type T Comment Status X
 Receiver OSNR is only defined for average receive power ≥ -12 dBm
 SuggestedRemedy
 Remove text "For average receive power < -12 dBm"
 Proposed Response Response Status O

Cl 156 SC 156.9.20 P81 L32 # 25
 Maniloff, Eric Ciena
 Comment Type T Comment Status X
 Optical Path Power penalty is not required for the defined application.
 SuggestedRemedy
 Remove 156.9.20
 Proposed Response Response Status O

Cl 156 SC 156.7.2 P74 L26 # 28
 Maniloff, Eric Ciena
 Comment Type T Comment Status X
 Receiver OSNR tolerance is only defined for average receive power ≥ -12 dBm
 SuggestedRemedy
 Remove text "For average receive power ≥ -12 dBm" from receiver OSNR tolerance
 Proposed Response Response Status O

Cl 156 SC 156.9.17 P81 L18 # 29
 Maniloff, Eric Ciena
 Comment Type E Comment Status X
 Add table reference for Receiver OSNR tolerance
 SuggestedRemedy
 Change "Receiver OSNR tolerance" to "The Receiver OSNR tolerance is specified in Table 156-7. Receiver OSNR tolerance is defined..."
 Proposed Response Response Status O

IEEE P802.3cw D1.2 400 Gb/s over DWDM systems 3rd Task Force review comments

Cl 156 SC 156.7.2 P74 L30 # 30
 Issenhuth, Tom Huawei
 Comment Type E Comment Status X
 Table 156-7 has a blank line at the end of the table
 SuggestedRemedy
 Remove the blank line
 Proposed Response Response Status O

Cl 156 SC 156.13.4.4 P91 L25 # 34
 Issenhuth, Tom Huawei
 Comment Type T Comment Status X
 PICS table needs to be updated as "I-Q offset" was changed to "I-Q (max instantaneous)" and "I-Q (mean)"
 SuggestedRemedy
 Change "I-Q offset" to "I-Q (max instantaneous)" and add entry for "I-Q (mean)" for subclause 156.9.12
 Proposed Response Response Status O

Cl 156 SC 156.10.1.2.1 P84 L5 # 31
 Issenhuth, Tom Huawei
 Comment Type T Comment Status X
 Number of block samples is TBD
 SuggestedRemedy
 Replace TBD with "1000"
 Proposed Response Response Status O

Cl 156A SC 156A P95 L1 # 35
 Issenhuth, Tom Huawei
 Comment Type T Comment Status X
 Majority and possibly all of the annex no longer needed with the removal of the unamplified specification
 SuggestedRemedy
 Delete 156A.2 onward retaining 156A.1 which contains DWDM black link examples or remove the entire annex from the draft including references in clause 156.
 Proposed Response Response Status O

Cl 156 SC 156.10.1.2.2 P84 L11 # 32
 Issenhuth, Tom Huawei
 Comment Type T Comment Status X
 Number of symbols is TBD
 SuggestedRemedy
 Replace TBD with "1000"
 Proposed Response Response Status O

Cl 156 SC 156.10.1.2.4 P84 L19 # 33
 Issenhuth, Tom Huawei
 Comment Type T Comment Status X
 Number of symbols is TBD
 SuggestedRemedy
 Replace TBD with "1000"
 Proposed Response Response Status O